

Porting SimpliciTI to the SmartRF CCxx10 Target Board

By Siri Johnsrud

Keywords

- CC1110Fx
- CC2510Fx
- SmartRF CCxx10 Target Board
- SimpliciTI
- CC1110 Mini DK
- CC2510 Mini DK

1 Introduction

The purpose of this design note is to show how to easily port the existing SimpliciTI examples [1] to the SmartRF CCxx10 Target Board. The

SmartRF CCxx10 Target Boards are included in the CCxx10 Mini DKs. In this document, CCxx10 refers to CC1110 and CC2510.




Table of Contents

KEYWORDS.....	1
1 INTRODUCTION.....	1
2 ABBREVIATIONS.....	2
3 STEP BY STEP GUIDE	3
4 REFERENCES.....	7
5 GENERAL INFORMATION	8
5.1 DOCUMENT HISTORY.....	8

2 Abbreviations

DK	Development Kit
LED	Light Emitting Diode
RF	Radio Frequency

3 Step by Step Guide

1. Start by downloading the newest revision of SimpliciTl [1]. By default the SimpliciTl software is placed in a folder called Texas Instruments on C:\.
2. Download the CC1110 and CC2510 Mini DK Software Example [2]. The user must decide where the code should be downloaded. For this design note, it is assumed that the software is downloaded to a folder called CCxx10MiniKit located on C:\
3. Under C:\Texas Instruments\SimpliciTI-IAR-1.1.0\Components\bsp\boards, create a new folder called srfccxx10 as shown Figure 1.




Figure 1. Create the srfccxx10 Folder

4. Copy all content from C:\CCxx10MiniKit\source\components\simpliciti\bsp\boards\srfccxx10 to C:\Texas Instruments\SimpliciTI-IAR-1.1.0\Components\bsp\boards\srfccxx10




Figure 2. Copy Files from CC1110 and CC2510 Mini DK Software Example

Design Note DN118

- Under C:\Texas Instruments\SimpliciTI-IAR-1.1.0\Projects\Examples, take a copy of the SRF04 folder, paste it under the Examples folder, and name it srfccxx10 (see Figure 3). The examples in the SRF04 folder is written for the CC1110 and CC2510 radios and can easily be modified to work on the SmartRF CCxx10 Target Boards.




Figure 3. The srfccxx10 Folder Containing all the SimpliciTI Examples

The next step is to change the project settings. This design note will show how this is done for one of the examples (Polling with AP), but the procedure will be identical for all of the examples.

- Open the Polling with AP workspace found under: C:\Texas Instruments\SimpliciTI-IAR-1.1.0\Projects\Examples\srfccxx10\Polling_with_AP\IAR.
- Select **Edit Configuration** in the **Project** pull-down menu (see Figure 4).




Figure 4. Edit Configuration

- Remove all configurations that are not for the CC1110 or CC2510. The configurations are removed by selecting them and pressing the **Remove** button, as shown in Figure 5.




Figure 5. Remove Configuration

Design Note DN118

- Right-click on **Polling_with_AP – CC1110-Sender** and select **Options..** from the menu as shown in Figure 6.




Figure 6. Options..

- In the C/C++ Compiler category, change
\$PROJ_DIR\$\\.\.\.\.\Components\bsp\boards\SRF04EB to
\$PROJ_DIR\$\\.\.\.\.\Components\bsp\boards\srfccxx10 as shown in Figure 7.




Figure 7. Change Include Directories

- Repeat step 10 for all 8 configurations (see Figure 8).




Figure 8. All Configurations

Design Note DN118

The project is now ready to be compiled and downloaded to the SmartRF CCxx10 Target Boards as described in the CC1110 & CC2510 Mini Development Kit User's Guide [3]. Each of the SimpliciTI sample applications require some form of user input via two logical buttons (Button 1 and Button 2) and provide status display via two "logical" LEDs (LED1 And LED2). The mapping of physical to logical buttons and LEDs for the SmartRF CCxx10 Target Board is shown in Table 1.

Button 1	Button 2	LED1	LED2
S1 MASTER	S2 SLAVE	Green	Red

Table 1. Mapping of Physical to Logical Buttons and LEDs

4 References

- [1] SimpliCI (<http://www.ti.com/simpliCI>)
- [2] CC1110 and CC2510 Mini DK Software Example (<http://www.ti.com/lit/zip/swrc133>)
- [3] CC1110 & CC2510 Mini Development Kit User's Guide ([swru236.pdf](#))

Design Note DN118

5 General Information

5.1 Document History

Revision	Date	Description/Changes
SWRA311	2009.11.19	Initial release.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
RF/IF and ZigBee® Solutions	www.ti.com/lprf

Applications

Audio	www.ti.com/audio
Automotive	www.ti.com/automotive
Broadband	www.ti.com/broadband
Digital Control	www.ti.com/digitalcontrol
Medical	www.ti.com/medical
Military	www.ti.com/military
Optical Networking	www.ti.com/opticalnetwork
Security	www.ti.com/security
Telephony	www.ti.com/telephony
Video & Imaging	www.ti.com/video
Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2009, Texas Instruments Incorporated