TPSI3052 15-V ゲート電源内蔵、絶縁スイッチ・ドライバ

1 特長

- 絶縁型二次電源は不要
- 外部パワー・トランジスタまたは SCR を駆動
- 3-kV_{RMS} basic isolation
- 1.5/3A ピークのソースおよびシンク電流の 15-V ゲート・ドライブ
- 外部補助回路に対して最大 50mW の電力を供給
- AC または DC スイッチングをサポート
- 2 線式または 3 線式モードをサポート
- 7 レベルの電力伝送、抵抗が選択可能
- 機能安全対応
  - 機能安全システム設計に役立つ資料を利用可能
- 周囲温度：-40 ~ 125℃
- 安全関連認証
  - DIN EN IEC 60747-17 (VDE 0884-17) に準拠した基本絶縁耐圧：4243V_{PK}
  - UL 1577 に準拠した絶縁耐圧：3kV_{RMS} (1 分間)

2 アプリケーション

- ソリッド・ステート・リレー (SSR)
- ビル・オートメーション
- ファクトリ・オートメーションおよび制御

3 概要

TPSI3052 は、統合型の絶縁スイッチ・ドライバで、外部パワー・スイッチと組み合わせることにより、完全な絶縁型ソリッド・ステート・リレー (SSR) を形成します。公称ゲート駆動電圧 15 V で、1.5/3.0A ピークのソースおよびシンク電流という性能を備えているので、さまざまな外部パワー・スイッチを選択して、幅広いアプリケーションに対応できます。TPSI3052 は、1 次側から供給された電源によって独自の 2 次バイアス電源を生成するので、絶縁型の 2 次側電源バイアスは不要です。さらに、TPSI3052 は、各種のアプリケーションのニーズに対応する外部のサポート回路に電力を供給することもできます。

TPSI3052 は、必要な入力ピンの数によって 2 つの動作モードをサポートしています。2 線式モードは、通常は機械式リレーの駆動に使用され、スイッチの制御に必要なピンは 2 本だけで、6.5V ~ 48V の広い電圧範囲で動作できます。3 線式モードでは、3V ~ 5.5V の 1 次電源が外部から供給され、スイッチは別のイネーブルによって制御されます。TPSI3052S は、スイッチの制御方式として、3 線式モードのみで利用可能なワンショット・イネーブルを備えています。この機能は、通常は電流パルス 1 つだけでトリガできる SCR の駆動に便利です。

2 次側は、15 V の安定化されたフローティング電源レールを提供し、2 次側バイアス電源を必要とせずに各種パワー・スイッチを駆動します。このアプリケーションは、DC アプリケーション用のシングル・パワー・スイッチ、または AC アプリケーション用のデュアル・バック・ツー・バック・パワー・スイッチ、および各種 SCR を駆動できます。TPSI3052 の内蔵絶縁保護は、非常に堅牢で、従来の機械式リレーやフォトカプラに比べて高信頼性、低消費電力で、温度範囲が広くなっています。

TPSI3052 の電力伝送は、PXFR ピンと VSSP の間の外付け抵抗を使って、7 つの電力レベル設定のいずれかを選択することにより調整できます。この操作により、アプリケーションのニーズに応じて、2 次側の供給電力と消費電力とのトレードオフが可能になります。

パッケージ情報

部品番号	パッケージ(1)	本体サイズ (公称)
TPSI3052	SOIC 8 ピン (DWZ)	7.50mm × 5.85mm
TPSI3052S		

(1) 利用可能なすべてのパッケージについては、データシートの末尾にある注文情報を参照してください。



TPSI3052 の概略回路図

英語版の TI 製品についての情報を翻訳したこの資料は、製品の概要を確認する目的で便宜的に提供しているものです。該当する正式な英語版の最新情報は、www.ti.com で閲覧でき、その内容が常に優先されます。TI では翻訳の正確性および妥当性につきましては一切保証いたしません。実際の設計などの前には、必ず最新版の英語版をご参照くださいますようお願いいたします。

Table of Contents

1 特長 ... 1
2 アプリケーション ... 1
3 概要 ... 1
4 Revision History ... 2
5 Pin Configuration and Functions ... 3
6 Specifications ... 4
6.1 Absolute Maximum Ratings ... 4
6.2 ESD Ratings ... 4
6.3 Recommended Operating Conditions ... 4
6.4 Thermal Information ... 5
6.5 Power Ratings ... 5
6.6 Insulation Specifications ... 5
6.7 Safety-Related Certifications ... 6
6.8 Safety Limiting Values ... 7
6.9 Electrical Characteristics ... 7
6.10 Switching Characteristics ... 10
6.11 Insulation Characteristic Curves ... 12
6.12 Typical Characteristics ... 13
7 Parameter Measurement Information ... 15
8 Detailed Description ... 17
8.1 Overview ... 17
8.2 Functional Block Diagram ... 17
8.3 Feature Description ... 17
8.4 Device Functional Modes ... 24
9 Application and Implementation ... 25
9.1 Application Information ... 25
9.2 Typical Application ... 25
9.3 Power Supply Recommendations ... 32
9.4 Layout ... 32
10 Device and Documentation Support ... 36
10.1 Related Links ... 36
10.2 ドキュメントの更新通知を受け取る方法 ... 36
10.3 サポート・リソース ... 36
10.4 Trademarks ... 36
10.5 静電気放電に関する注意事項 ... 36
10.6 用語集 ... 36
11 Mechanical, Packaging, and Orderable Information ... 36

4 Revision History

資料番号末尾の英字は改訂を表しています。その改訂履歴は英語版に準じています。

Changes from Revision A (April 2023) to Revision B (August 2023)	Page
• Updated Safety-Related Certifications section with associated file and certificate numbers	4

Changes from Revision * (April 2022) to Revision A (April 2023)	Page
• デバイス・ステータスを「事前情報」から「量産データ」に変更	1
• テキサス・インスツルメンツの最新のデータシートの標準に合わせて先頭ページのフォーマットを変更	1

Copyright © 2023 Texas Instruments Incorporated

5 Pin Configuration and Functions



図 5-1. TPSI3052, TPSI3052S 8-Pin SOIC Top View

表 5-1. Pin Functions

PIN		I/O	TYPE(1)	DESCRIPTION
NO.	NAME			
1	EN	I	—	Active high driver enable
2	PXFR	I	—	Power transfer can be adjusted by selecting one of seven power level settings using an external resistor from the PXFR pin to VSSP. In three-wire mode, a given resistor setting sets the duty cycle of the power converter (see 表 8-1) and hence the amount of power transferred. In two-wire mode, a given resistor setting adjusts the current limit of the EN pin (see 表 8-2) and hence the amount of power transferred.
3	VDDP	—	P	Power supply for primary side
4	VSSP	—	GND	Ground supply for primary side
5	VSSS	—	GND	Ground supply for secondary side
6	VDDM	—	P	Generated mid supply
7	VDDH	—	P	Generated high supply
8	VDRV	O	—	Active high driver output

(1) P = power, GND = ground, NC = no connect

Copyright © 2023 Texas Instruments Incorporated

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

PARAMETER(1)		MIN	MAX	UNIT
Primary Side Supply(2)	VDDP	–0.3	6	V
Primary Side Supply(2)	EN	–0.3	60	V
Primary Side Supply(2)	PXFR	–0.3	60	V
Secondary Side Supply(3)	VDRV	–0.3	18	V
Secondary Side Supply(3)	VDDH	–0.3	18	V
Secondary Side Supply(3)	VDDM	–0.3	6	V
Secondary Side Supply(3)	VDDH-VDDM	–0.3	12	V
Junction temperature, T_J	Junction temperature, T_J	–40	150	°C
Storage temperature, T_{stg}		–65	150	°C

(1) Operation outside the Absolute Maximum Ratings may cause permanent device damage. Absolute Maximum Ratings do not imply functional operation of the device at these or any other conditions beyond those listed under Recommended Operating Conditions. If used outside the Recommended Operating Conditions but within the Absolute Maximum Ratings, the device may not be fully functional, and this may affect device reliability, functionality, performance, and shorten the device lifetime.
(2) All voltage values are with respect to VSSP.
(3) All voltage values are with respect to VSSS.

6.2 ESD Ratings

				VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human body model (HBM), per ANSI/ESDA/JEDEC JS-001(2)		±2000	V
		Charged device model (CDM), per ANSI/ESDA/JEDEC JS-002(3)	Corner pins (1, 4, 5, and 8)	±750	
			Other pins	±500	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process. Manufacturing with less than 500-V HBM is possible if necessary precautions are taken.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process. Manufacturing with less than 250-V CDM is possible if necessary precautions are taken.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	NOM	MAX	UNIT
VDDP	Primary side supply voltage in three-wire mode(1)	3.0		5.5	V
EN	Enable in two-wire mode(1)	0		48.0	V
	Enable in three-wire mode(1)	0		5.5	V
PXFR	Power transfer control(1)	0		5.5	V
C_{VDDP}	Decoupling capacitance on VDDP and VSSP, two-wire mode(3)	220		330	nF
	Decoupling capacitance on VDDP and VSSP, three-wire mode(3)	0.22		20	µF
C_{DIV1} (2)	Decoupling capacitance across VDDH and VDDM(3)	0.004		15	µF
C_{DIV2} (2)	Decoupling capacitances across VDDM and VSSS(3)	0.012		40	µF

Copyright © 2023 Texas Instruments Incorporated

6.3 Recommended Operating Conditions (continued)

over operating free-air temperature range (unless otherwise noted)

		MIN	NOM	MAX	UNIT
T_A	Ambient operating temperature	–40		125	°C
T_J	Operating junction temperature	–40		150	°C
$\|\Delta V_{EN}/\Delta t\|$	EN rise and fall rates, two-wire mode.	65			V/ms

(1) All voltage values are with respect to VSSP.
(2) C_{DIV1} and C_{DIV2} should be of same type and tolerance. C_{DIV2} capacitance value should be at least three times the capacitance value of C_{DIV1} i.e. $C_{DIV2} \geq 3 \times C_{DIV1}$.
(3) All capacitance values are absolute. Derating should be applied where necessary.

6.4 Thermal Information

THERMAL METRIC(1) (2)		DEVICE DWZ(SOIC) 8 PINS	UNIT
$R_{\Theta JA}$	Junction-to-ambient thermal resistance	89.3	°C/W
$R_{\Theta JC(top)}$	Junction-to-case (top) thermal resistance	40.3	°C/W
$R_{\Theta JB}$	Junction-to-board thermal resistance	45.2	°C/W
ψ_{JT}	Junction-to-top characterization parameter	10.3	°C/W
Ψ_{JB}	Junction-to-board characterization parameter	44.4	°C/W

(1) Estimate only.
(2) For more information about traditional and new thermal metrics, see the Semiconductor and IC Package Thermal Metrics application report.

6.5 Power Ratings

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
P_D	Maximum power dissipation, VDDP.	V_{VDDP} = 5 V, R_{PXFR} = 20 kΩ, three-wire mode, C_{VDRV} = 100 pF, C_{DIV1} = 33 nF, C_{DIV2} = 100 nF f_{EN} = 1-kHz square wave, V_{EN} = 5 V peak to peak.			250	mW
	Maximum power dissipation, EN.	R_{PXFR} = 20 kΩ, two-wire mode, C_{VDRV} = 100 pF, C_{DIV1} = 33 nF, C_{DIV2} = 100 nF f_{EN} = 1-kHz square wave, V_{EN} = 48 V peak to peak.k.			350	mW

6.6 Insulation Specifications

PARAMETER		TEST CONDITIONS	SPECIFICATION	UNIT
CREEPAGE AND TRACKING				
CLR	External clearance(1)	Shortest terminal-to-terminal distance through air	≥ 8.5	mm
CPG	External Creepage(1)	Shortest terminal-to-terminal distance across the package surface	≥ 8.5	mm
DTI	Distance through the insulation	Minimum internal gap (internal clearance)	≥ 120	µm
CTI	Comparative tracking index	DIN EN 60112 (VDE 0303-11); IEC 60112	≥ 600	V
	Material Group	According to IEC 60664-1	I	
	Overvoltage category per IEC 60664-1	Rated mains voltage ≤ 600 V_{RMS}	I-IV	
		Rated mains voltage ≤ 1000 V_{RMS}	I-III	

Copyright © 2023 Texas Instruments Incorporated

6.6 Insulation Specifications (continued)

PARAMETER		TEST CONDITIONS	SPECIFICATION	UNIT
DIN EN IEC 60747-17 (VDE 0884-17)				
V_{IORM}	Maximum repetitive peak isolation voltage	AC voltage (bipolar)	1414	V_{PK}
V_{IOWM}	Maximum isolation working voltage	AC voltage (sine wave)	1000	V_{RMS}
		DC voltage	1414	V_{DC}
V_{IOTM}	Maximum transient isolation voltage	$V_{TEST} = V_{IOTM}$; t = 60 s (qualification test)	4243	V_{PK}
		$V_{TEST} = 1.2 \times V_{IOTM}$; t = 1 s (100% production test)	5091	V_{PK}
V_{IMP}	Maximum impulse voltage(3)	Tested in air; 1.2/50-µs waveform per IEC 62638-1	4500	V_{PK}
V_{IOSM}	Maximum surge isolation voltage(3)	Tested in oil (qualification test); 1.2/50-µs waveform per IEC 62638-1	5850	V_{PK}
q_{pd}	Apparent charge(4)	Method a: After input-output safety test subgroup 2/3, $V_{ini} = V_{IOTM}$, t_{ini} = 60 s; $V_{pd(m)} = 1.2 \times V_{IORM}$, t_m = 10 s.	≤ 5	pC
		Method a: After environmental tests subgroup 1, $V_{ini} = V_{IOTM}$, t_{ini} = 60 s; $V_{pd(m)} = 1.3 \times V_{IORM}$, t_m = 10 s.	≤ 5	
		Method b1: At routine test (100% production test) and preconditioning (type test), $V_{ini} = V_{IOTM}$, t_{ini} = 1 s; $V_{pd(m)} = 1.5 \times V_{IORM}$, t_m = 1 s.	≤ 5	
C_{IO}	Barrier capacitance, input to output(5)	V_{IO} = 0.4 × sin (2πft), f = 1 MHz	3	pF
R_{IO}	Insulation resistance, input to output(5)	V_{IO} = 500 V, T_A = 25°C	> 10^{12}	Ω
		V_{IO} = 500 V, 100°C ≤ T_A ≤ 125°C	> 10^{11}	
		V_{IO} = 500 V at T_S = 150°C	> 10^{9}	
	Pollution degree		2	
	Climatic category		40/125/21	
UL 1577				
V_{ISO}	Withstand isolation voltage	$V_{TEST} = V_{ISO}$ = 3000 V_{RMS}, t = 60 s (qualification test), $V_{TEST} = 1.2 \times V_{ISO}$ = 3600 V_{RMS}, t = 1 s (100% production test)	3000	V_{RMS}

(1) Creepage and clearance requirements should be applied according to the specific equipment isolation standards of an application. Care should be taken to maintain the creepage and clearance distance of a board design to ensure that the mounting pads of the isolator on the printed-circuit board do not reduce this distance. Creepage and clearance on a printed-circuit board become equal in certain cases. Techniques such as inserting grooves, ribs, or both on a printed-circuit board are used to help increase these specifications.
(2) Testing is carried out in air to determine the intrinsic surge immunity of the package.
(3) Testing is carried out in oil to determine the intrinsic surge immunity of the isolation barrier.
(4) Apparent charge is electrical discharge caused by a partial discharge (pd).
(5) All pins on each side of the barrier tied together creating a two-pin device.

6.7 Safety-Related Certifications

VDE	UL
Certified according to DIN EN IEC 60747-17 (VDE 0884-17)	Recognized under UL 1577 Component Recognition Program
Basic insulation; Maximum transient isolation voltage, 4243 V_{PK}; Maximum repetitive peak isolation voltage, 1414 V_{PK}; Maximum surge isolation voltage, 5850 V_{PK}	Single protection, 3000 V_{RMS}
Certificate number: 40047657	File number: UL-US-2300613-0

Copyright © 2023 Texas Instruments Incorporated

6.8 Safety Limiting Values

PARAMETER(1) (2)		TEST CONDITIONS	MIN	TYP	MAX	UNIT
I_S	Safety input, output, or supply current	$R_{\theta JA}$ = 89.3°C/W, V_{VDDP} = 5.5 V, T_J = 150°C, T_A = 25°C, three-wire mode.			254	mA
		$R_{\theta JA}$ = 89.3°C/W, V_{EN} = 24 V, T_J = 150°C, T_A = 25°C, two-wire mode.			58	
		$R_{\theta JA}$ = 89.3°C/W, V_{EN} = 48 V, T_J = 150°C, T_A = 25°C, two-wire mode.			29	
P_S	Safety input, output, or total power	$R_{\theta JA}$ = 89.3°C/W, T_J = 150°C, T_A = 25°C.			1.4	W
T_S	Maximum safety temperature				150	°C

(1) Safety limiting intends to minimize potential damage to the isolation barrier upon failure of input or output circuitry. A failure of the I/O can allow low resistance to ground or the supply and, without current limiting, dissipate sufficient power to overheat the die and damage the isolation barrier, potentially leading to secondary system failures.

(2) The safety-limiting constraint is the maximum junction temperature specified in the data sheet. The power dissipation and junction-to-air thermal impedance of the device installed in the application hardware determines the junction temperature. The assumed junction-to-air thermal resistance in the Thermal Information table is that of a device installed on a high-K test board for leaded surface-mount packages. The power is the recommended maximum input voltage times the current. The junction temperature is then the ambient temperature plus the power times the junction-to-air thermal resistance.

6.9 Electrical Characteristics

over operating free-air temperature range (unless otherwise noted). Typicals at T_A = 25°C. C_{VDDP} = 220 nF (two-wire mode), C_{VDDP} = 1 µF (three-wire mode) , C_{DIV1} = 5.1 nF, C_{DIV2} = 15 nF, C_{VDRV} = 100 pF, R_{PXFR} = 7.32 kΩ ±1%

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
COMMON						
$V_{VDDP_UV_R}$	VDDP under-voltage threshold rising	VDDP rising	2.50	2.70	2.90	V
$V_{VDDP_UV_F}$	VDDP under-voltage threshold falling	VDDP falling	2.35	2.55	2.75	V
$V_{VDDP_UV_HYS}$	VDDP under-voltage threshold hysteresis			75		mV
$V_{VDDH_UV_R}$	VDDH under-voltage threshold rising	VDDH rising.	12.5	13	13.4	V
$V_{VDDH_UV_F}$	VDDH under-voltage threshold falling.	VDDH falling.	9.9	10.4	10.9	V
$V_{VDDH_UV_HYS}$	VDDH under-voltage threshold hysteresis.			2.5		V
$V_{VDDM_UV_R}$	VDDM under-voltage threshold rising	VDDM rising.	2.8	3.3	3.7	V
$V_{VDDM_UV_F}$	VDDM under-voltage threshold falling	VDDM falling.	2.6	3	3.5	V
$V_{VDDM_UV_HYS}$	VDDM under-voltage threshold hysteresis.			0.3		V
I_{Q_VDDH}	Internal quiescent current of VDDH supply.			45		µA
R_{DSON_VDRV}	Driver on resistance in low state.	Force V_{VDDH} = 15 V, sink I_{VDRV} = 50 mA.		1.7		Ω
	Driver on resistance in high state.	Force V_{VDDH} = 15 V, source I_{VDRV} = 50 mA.		2.5		Ω

Copyright © 2023 Texas Instruments Incorporated

6.9 Electrical Characteristics (continued)

over operating free-air temperature range (unless otherwise noted). Typicals at T_A = 25℃. C_{VDDP} = 220 nF (two-wire mode), C_{VDDP} = 1 µF (three-wire mode) , C_{DIV1} = 5.1 nF, C_{DIV2} = 15 nF, C_{VDRV} = 100 pF, R_{PXFR} = 7.32 kΩ ±1%

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
I_{VDRV_PEAK}	VDRV peak output current during rise	V_{VDDH} in steady state, transition EN low to high, measure peak current.		1.5		A
	VDRV peak output current during fall	V_{VDDH} in steady state, transition EN high to low, measure peak current.		3		A
TSD	Temperature shutdown			173		℃
TSDH	Temperature shutdown hysteresis			32		℃
CMTI	Common-mode transient immunity	$\|V_{CM}\|$ = 1000 V	100			V/ns
TWO-WIRE MODE						
V_{IH_EN}	Minimum voltage on EN to be detected as a valid logic high.		6.5			V
V_{IL_EN}	Maximum voltage on EN to be detected as a valid logic low.				2.0	V
I_{EN_START}	Enable current at startup	EN = 0 V → 6.5 V		27		mA
I_{EN}	Enable current steady state	EN = 6.5 V, R_{PXFR} = 7.32 kΩ, R_{PXFR} ≥100 kΩ or R_{PXFR} ≤1 kΩ, V_{VDDH} in steady state.		1.9		mA
		EN = 6.5 V, R_{PXFR} = 20 kΩ, V_{VDDH} in steady state.		6.8		mA
V_{VDDP_AVG}	VDDP average voltage.	EN = 6.5 V, V_{VDDH} in steady state, measure average VDDP voltage.		4.5		V
V_{VDDH}	VDDH output voltage	EN = 6.5 V, V_{VDDH} in steady state.	13.9	15	16.2	V
V_{VDRV_H}	VDRV output voltage driven high	EN = 6.5 V, V_{VDDH} in steady state, no DC loading.	13.9	15	16.2	V
V_{VDRV_L}	VDRV output voltage driven low	EN = 6.5 V → 0 V, V_{VDDH} in steady state, sink 10 mA load.			0.1	V
V_{VDDM_IAUX}	Average VDDM voltage when sourcing external current.	EN = 6.5 V, steady state. R_{PXFR} = 7.32 kΩ, R_{PXFR} ≥ 100 kΩ or R_{PXFR} ≤ 1 kΩ, C_{DIV1} = 75 nF, C_{DIV2} = 220 nF, source 0.20 mA from VDDM, measure VDDM voltage.	4.6		5.5	V
	Average VDDM voltage when sourcing external current.	EN = 6.5 V, steady state. R_{PXFR} = 20 kΩ, C_{DIV1} = 75 nF, C_{DIV2} = 220 nF, source 1.2 mA from VDDM, measure VDDM voltage.	4.6		5.5	V
THREE-WIRE MODE						
V_{IH_EN}	Minimum voltage on EN to be detected as a valid logic high. $V_{IH(min)}$ = 0.7 x V_{VDDP}	V_{VDDP} = 3 V	2.1			V
		V_{VDDP} = 5.5 V	3.85			V
V_{IL_EN}	Maximum voltage on EN to be detected as a valid logic low.	V_{VDDP} = 3 V			0.9	V
		V_{VDDP} = 5.5 V			1.65	V

Copyright © 2023 Texas Instruments Incorporated

6.9 Electrical Characteristics (continued)

over operating free-air temperature range (unless otherwise noted). Typicals at T_A = 25°C. C_{VDDP} = 220 nF (two-wire mode), C_{VDDP} = 1 µF (three-wire mode) , C_{DIV1} = 5.1 nF, C_{DIV2} = 15 nF, C_{VDRV} = 100 pF, R_{PXFR} = 7.32 kΩ ±1%

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
I_{VDDP}	VDDP average current in steady state	EN = 3.3 V, V_{VDDP} = 3.3 V, R_{PXFR} = 7.32 kΩ, R_{PXFR} ≥ 100 kΩ or R_{PXFR} ≤ 1 kΩ, C_{VDDP} = 10 µF, V_{VDDH} in steady state, measure I_{VDDP}.		3.1		mA
		EN = 3.3 V, V_{VDDP} = 3.3 V, R_{PXFR} = 20 kΩ, C_{VDDP} = 10 µF, V_{VDDH} in steady state, measure I_{VDDP}.		26		
		EN = 5 V, V_{VDDP} = 5 V, R_{PXFR} = 7.32 kΩ, R_{PXFR} ≥ 100 kΩ or R_{PXFR} ≤ 1 kΩ, C_{VDDP} = 10 µF, V_{VDDH} in steady state, measure I_{VDDP}.		4.8		mA
		EN = 5 V, V_{VDDP} = 5 V, R_{PXFR} = 20 kΩ, C_{VDDP} = 10 µF, V_{VDDH} in steady state, measure I_{VDDP}.		37		mA
V_{VDDM_IAUX}	Average VDDM voltage when sourcing external current.	V_{VDDP} = 3.3 V, EN = 0.0 V, steady state. R_{PXFR} = 7.32 kΩ, C_{DIV1} = 75 nF, C_{DIV2} = 220 nF, Source 0.35 mA from VDDM measure V_{VDDM}.	4.6		5.5	V
V_{VDDM_IAUX}	Average VDDM voltage when sourcing external current.	V_{VDDP} = 5.0 V, EN = 0.0 V, steady state. R_{PXFR} = 7.32 kΩ, C_{DIV1} = 75 nF, C_{DIV2} = 220 nF, Source 0.50 mA from VDDM measure V_{VDDM}.	4.6		5.5	V
V_{VDDM_IAUX}	Average VDDM voltage when sourcing external current.	V_{VDDP} = 3.3 V, EN = 0.0 V, steady state. R_{PXFR} = 20 kΩ C_{DIV1} = 75 nF, C_{DIV2} = 220 nF, Source 3.0 mA from VDDM measure V_{VDDM}.	4.6		5.5	V
V_{VDDM_IAUX}	Average VDDM voltage when sourcing external current.	V_{VDDP} = 5.0 V, EN = 0.0 V, steady state. R_{PXFR} = 20 kΩ C_{DIV1} = 75 nF C_{DIV2} = 220 nF Source 5.0 mA from VDDM measure V_{VDDM}.	4.6		5.5	V

Copyright © 2023 Texas Instruments Incorporated

6.9 Electrical Characteristics (continued)

over operating free-air temperature range (unless otherwise noted). Typicals at T_A = 25°C. C_{VDDP} = 220 nF (two-wire mode), C_{VDDP} = 1 µF (three-wire mode) , C_{DIV1} = 5.1 nF, C_{DIV2} = 15 nF, C_{VDRV} = 100 pF, R_{PXFR} = 7.32 kΩ ±1%

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
V_{VDDH}	VDDH output voltage	V_{VDDP} = 3.0 V, EN = 3.0 V, V_{VDDH} in steady state.	13.9	15	16.2	V
V_{VDRV_H}	VDRV output voltage driven high	V_{VDDP} = 3.0 V, EN = 3.0 V, V_{VDDH} in steady state, no DC loading.	13.9	15	16.2	V
V_{VDRV_L}	VDRV output voltage driven low	V_{VDDP} = 3.0 V, EN = 0 V, V_{VDDH} in steady state, VDRV sinking 10 mA.			0.1	V

6.10 Switching Characteristics

over operating free-air temperature range (unless otherwise noted). Typicals at T_A = 25°C. C_{VDDP} = 220 nF (two-wire mode), C_{VDDP} = 1 µF (three-wire mode) , C_{DIV1} = 5.1 nF, C_{DIV2} = 15 nF, C_{VDRV} = 100 pF, R_{PXFR} = 7.32 kΩ ±1%

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
TWO-WIRE MODE						
t_{LO_EN}	Low time of EN.		5			µs
t_{LH_VDDH}	Propagation delay time from EN rising to VDDH at 50% level.	EN = 0 V → 6.5 V, V_{VDDH} = 7.5 V.		165		µs
t_{LH_VDRV}	Propagation delay time from EN rising to VDRV at 90% level.	EN = 0 V → 6.5 V, V_{VDRV} = 13.5 V.		185		µs
t_{HL_VDRV}	Propagation delay time from EN falling to VDRV at 10% level.	EN = 6.5 V → 0 V, V_{VDRV} = 1.5 V.		2.4	3	µs
t_{R_VDRV}	VDRV rise time from EN rising to VDRV from 15% to 85% level.	EN = 0 V → 6.5 V, V_{VDRV} = 2.25 V to 12.75 V.		6		ns
t_{F_VDRV}	VDRV fall time from EN falling to VDRV from 85% to 15% level.	EN = 6.5 V → 0 V, V_{VDRV} = 12.75 V to 2.25 V.		5		ns
THREE-WIRE MODE						
t_{LO_EN}	Low time of EN.	V_{VDDP} = 3.3 V, V_{VDDH} = steady state.	5			µs
t_{HI_EN}	High time of EN.	V_{VDDP} = 3.3 V, V_{VDDH} = steady state.	5			µs
t_{HI_VDRV}	High time of VDRV in one-shot enable mode. TPSI3052S only. One-shot enable only available in three-wire mode.	V_{VDDP} = 3.3 V, steady state.		2.5		µs
t_{LH_VDDH}	Propagation delay time from VDDP rising to VDDH at 50% level.	EN = 0 V, V_{VDDP} = 0 V → 3.3 V at 1 V/µs, V_{VDDH} = 7.5 V. C_{DIV1} = 3.3 nF, C_{DIV2} = 220 nF.		85		µs
t_{LH_VDRV}	Propagation delay time from EN rising to VDRV at 90% level	V_{VDDP} = 3.3 V, V_{VDDH} steady state, EN = 0 V → 3.3 V, V_{VDRV} = 13.5 V.		3	4.5	µs
t_{HL_VDRV}	Propagation delay time from EN falling to VDRV at 10% level	V_{VDDP} = 3.3 V, V_{VDDH} steady state, EN = 3.3 V → 0 V, V_{VDRV} = 1.5 V.		2.5	3	µs

Copyright © 2023 Texas Instruments Incorporated

6.10 Switching Characteristics (continued)

over operating free-air temperature range (unless otherwise noted). Typicals at T_A = 25°C. C_{VDDP} = 220 nF (two-wire mode), C_{VDDP} = 1 µF (three-wire mode) , C_{DIV1} = 5.1 nF, C_{DIV2} = 15 nF, C_{VDRV} = 100 pF, R_{PXFR} = 7.32 kΩ ±1%

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$t_{HL_VDRV_PD}$	Propagation delay time from VDDP falling to VDRV at 10% level. Timeout mechanism due to loss of power on primary supply.	EN = 3.3 V, V_{VDDP} = 3.3 V → 0 V at -1 V/µs, V_{VDRV} = 1.5 V.		300		µs
t_{R_VDRV}	VDRV rise time from EN rising to VDRV from 15% to 85% level	V_{VDDP} = 3.3 V, V_{VDDH} steady state, EN = 0 V → 3.3 V, V_{VDRV} = 2.25 V to 12.75 V.		6		ns
t_{F_VDRV}	VDRV fall time from EN falling to VDRV from 85% to 15% level	V_{VDDP} = 3.3 V, V_{VDDH} steady state, EN = 3.3 V → 0 V, V_{VDRV} = 12.75 V to 2.25 V.		5		ns

Copyright © 2023 Texas Instruments Incorporated

6.11 Insulation Characteristic Curves



図 6-1. Thermal Derating Curve for Limiting Current per VDE and IEC, Three-Wire Mode



図 6-2. Thermal Derating Curve for Limiting Current per VDE and IEC, Two-Wire Mode



図 6-3. Thermal Derating Curve for Limiting Power per VDE and IEC

Copyright © 2023 Texas Instruments Incorporated

6.12 Typical Characteristics



Three-wire mode | VDDP = 5.0 V | R_{PXFR} = 7.32 kΩ
C_{DIV1} = 5.1 nF | C_{VDRV} = 100 pF | T_A = 25°C
C_{DIV2} =15 nF | C_{VDDP} = 1 µF | I_{AUX} = 0 mA

図 6-4. t_{LH_VDRV}, Three-Wire Mode



Three-wire mode | VDDP = 5.0 V | R_{PXFR} = 7.32 kΩ
C_{DIV1} = 5.1 nF | C_{VDRV} = 100 pF | T_A = 25°C
C_{DIV2} =15 nF | C_{VDDP} = 1 µF | I_{AUX} = 0 mA

図 6-5. t_{HL_VDRV}, Three-Wire Mode



Three-wire mode | VDDP = 3.3 V | R_{PXFR} = 7.32 kΩ
C_{DIV1} = 2.2 µF | C_{DIV2} = 2.2 µF

図 6-6. t_{LH_VDRV} versus C_{VDRV}



Three-wire mode | VDDP = 3.3 V | R_{PXFR} = 7.32 kΩ
C_{DIV1} = 2.2 µF | C_{DIV2} = 2.2 µF

図 6-7. t_{HL_VDRV} versus C_{VDRV}



Two-wire mode | EN = 12 V | R_{PXFR} = 7.32 kΩ
C_{DIV1} = 33 nF | C_{VDRV} = 100 pF | T_A = 25°C
C_{DIV2} =100 nF | C_{VDDP} = 220 nF | I_{AUX} = 0 mA

図 6-8. t_{LH_VDRV}, Two-Wire Mode



Two-wire mode | EN = 12 V | R_{PXFR} = 7.32 kΩ
C_{DIV1} = 33 nF | C_{VDRV} = 100 pF | T_A = 25°C
C_{DIV2} =100 nF | C_{VDDP} = 220 nF | I_{AUX} = 0 mA

図 6-9. t_{HL_VDRV}, Two-Wire Mode

Copyright © 2023 Texas Instruments Incorporated

6.12 Typical Characteristics (continued)



tSTART represents the time from VDDP rising to VDDM and VDDH fully discharged rails reaching > 95% of their final levels.

Three-wire mode VDDP = 5.0 V T_A = 25°C
I_{AUX} = 0 mA

図 6-10. t_{START} versus C_{DIV1}, C_{DIV2}



tSTART represents the time from VDDP rising to VDDM and VDDH fully discharged rails reaching > 95% of their final levels.

Three-wire mode VDDP = 3.3 V T_A = 25°C
I_{AUX} = 0 mA

図 6-11. t_{START} versus C_{DIV1}, C_{DIV2}



Three-wire mode VDDP = 5.0 V T_A = 25°C
I_{AUX} = 0 mA

図 6-12. Max. f_{EN} versus Q_{LOAD} = 10 nC to 100 nC



Three-wire mode VDDP = 5.0 V T_A = 25°C
I_{AUX} = 0 mA

図 6-13. Max. f_{EN} versus Q_{LOAD} = 100 nC to 1000 nC



Three-wire mode R_{PXFR} = 20 kΩ T_A = 25°C
C_{DIV1} = 150 nF C_{DIV2} = 470 nF C_{VDDP} = 1 µF

図 6-14. V_{VDDM} versus I_{AUX}



Three-wire mode R_{PXFR} = 11 kΩ T_A = 25°C
C_{DIV1} = 150 nF C_{DIV2} = 470 nF C_{VDDP} = 1 µF

図 6-15. V_{VDDM} versus I_{AUX}

Copyright © 2023 Texas Instruments Incorporated

7 Parameter Measurement Information



図 7-1. Two-Wire Mode Timing, Standard Enable (TPSI3052 Only)



図 7-2. Three-Wire Mode Timing, Standard Enable (TPSI3052 Only)



図 7-3. Three-Wire Mode Timing, One-Shot Enable (TPSI3052S Only)



図 7-4. Common-Mode Transient Immunity Test Circuit

Copyright © 2023 Texas Instruments Incorporated

8 Detailed Description

8.1 Overview

The TPSI3052 is a fully integrated, isolated power switch driver, which when combined with an external power switch, forms a complete isolated Solid State Relay (SSR). With a nominal gate drive voltage of 15 V and 1.5/3.0-A peak source and sink current, a large variety of external power switches can be chosen to meet a wide range of applications. The TPSI3052 generates its own secondary supply from the power received from its primary side, so no isolated secondary bias supply is required.

The *Functional Block Diagram* shows the primary side that includes a transmitter that drives an alternating current into the primary winding of an integrated transformer at a rate determined by the setting of the PXFR pin and the logic state of the EN pin. The transmitter operates at high frequency to optimally drive the transformer to its peak efficiency. In addition, the transmitter uses spread spectrum techniques to greatly improve EMI performance, allowing many applications to achieve CISPR 25 - Class 5. During transmission, data information transfers to the secondary side alongside with the power. On the secondary side, the voltage induced on the secondary winding of the transformer is rectified, and the shunt regulator regulates the output voltage level of VDDH. Lastly, the demodulator decodes the received data information and drives VDRV high or low based on the logic state of the EN pin.

8.2 Functional Block Diagram



8.3 Feature Description

8.3.1 Transmission of the Enable State

The TPSI3052 and TPSI3052S use a modulation scheme to transmit the switch enable state information across the isolation barrier. The transmitter modulates the EN signal with an internally generated, high frequency carrier (89-MHz typical), and differentially drives the primary winding of the isolation transformer. The receiver on the secondary side demodulates the received signal and asserts VDRV high or low based on the data received.

8.3.2 Power Transmission

The TPSI3052 and TPSI3052S do not use an isolated supply for their power. The secondary side power is obtained by the transferring of the primary side input power across the isolation transformer. The modulation scheme uses spread spectrum of the high frequency carrier (89-MHz typical) to improve EMI performance assisting applications in meeting the CISPR 25 Class 5 standards.

8.3.3 Gate Driver

The TPSI3052 and TPSI3052S have an integrated gate driver that provides a nominal 15-V gate voltage with 1.5/3.0-A peak source and sink current sufficient for driving many power transistors or Silicon-Controlled Rectifiers (SCR). When driving external power transistors, TI recommends bypass capacitors (C_{DIV2} = 3 * C_{DIV1}) from VDDH to VDDM and VDDM to VSSS of 20 times the equivalent gate capacitance.

The gate driver also includes an active clamp keep off circuit. This feature helps to keep the driver output, VDRV, low should power be lost on the secondary supply rails e.g. power loss on the VDDP supply prevents power transfer. Should power be lost, the active clamp keep off circuit will attempt to clamp the voltage of VDRV to under 2 V relative to VSSS.

Copyright © 2023 Texas Instruments Incorporated

8.3.4 Modes Overview

The TPSI3052 and TPSI3052S have two modes of operation: two-wire mode and three-wire mode.

In two-wire mode, the power on the primary side is provided directly by the EN pin. Setting EN high causes power transfer to the secondary side. As power transfers, the secondary rails, VDDM and VDDH, begin to rise. After sufficient power is available on the secondary side, VDRV is asserted high. Setting EN low causes VDRV to assert low and halts power transfer to the secondary side.

In three-wire mode, the power on the primary side is provided by a dedicated, low output impedance supply connected to VDDP. In this case, power transfer is independent from the enable state. If VDDP power is present, power is transferred from the primary side to the secondary side regardless of the EN state. In steady state conditions, when sufficient power is available on the secondary side, setting EN high causes VDRV to assert high. Setting EN low causes VDRV to assert low.

In standard enable, available only on the TPSI3052, VDRV follows the state of the EN pin and is used in most load switch applications. In one-shot enable mode, available only on the TPSI3052S in three-wire mode, when a rising transition occurs on EN, VDRV is asserted high momentarily and then automatically asserted low, forming a one-shot pulse on VDRV. This event is useful for driving SCR devices that require only one burst of power to trigger. To re-trigger VDRV, EN must first transition low, followed by another rising transition.

8.3.5 Three-Wire Mode

Three-wire mode is used for applications that require higher levels of power transfer or the shortest propagation delay TPSI3052 can offer. VDDP is supplied independently from the EN pin by a low output impedance external supply that can deliver the required power. In this mode, power from the primary side to the secondary side always occurs regardless of the state of the EN pin. Setting the EN pin logic high or low asserts or de-asserts VDRV, thereby enabling or disabling the external switch, respectively. 図 8-1 shows the basic setup required for three-wire mode operation which requires EN, VDDP, and VSSP signals. EN can be driven up to 5.5 V which is normally driven from the circuitry residing on the same rail as VDDP. In this example, the TPSI3052 is being used to drive back-to-back MOSFETs in a common-source configuration. C_{VDDP} provides the required decoupling capacitance for the VDDP supply rail of the device. C_{DIV1} and C_{DIV2} provide the required decoupling capacitances of the VDDH and VDDM supply rails that provide the peak current to drive the external MOSFETs.

図 8-2 and 図 8-3 show the basic operation from start-up to steady-state conditions. 図 8-2 shows operation using standard enable of the TPSI3052. After power up, the TPSI3052 begins to transfer power from VDDP to the secondary side for a fixed time period (25-µs typical) at a duty cycle rate determined by R_{PXFR}, which begins to charge up the VDDH (and VDDM) secondary side rails. Power transfer continues as long as VDDP is present. The time required to fully charge VDDH depends on several factors including the values of VDDP, C_{DIV1}, C_{DIV2}, R_{PXFR}, and the overall power transfer efficiency. When the application drives the EN pin to a logic high, the TPSI3052 signals information from the primary side to the secondary side to assert VDRV and drive it high. Similarly, setting EN pin to a logic low causes VDRV to be driven low. 図 8-3 shows operation using one-shot enable of the TPSI3052S. The start-up behavior is identical. In one-shot enable, when the application drives the EN pin to a logic high, VDRV is asserted high (t_{HI_VDRV}), then is automatically asserted low by the TPSI3052S. To assert VDRV high again, the EN pin must transition low first, followed by a transition high.



図 8-1. Three-Wire Mode Simplified Schematic

Copyright © 2023 Texas Instruments Incorporated



図 8-2. Three-Wire Mode with TPSI3052 (Standard Enable)



図 8-3. Three-Wire Mode with TPSI3052S (One-shot Enable)

To reduce average power, the TPSI3052 transfers power from the primary side to the secondary side in a burst fashion. The period of the burst is fixed while the burst on time is programmable by selecting one of seven appropriate resistor values, R_{PXFR}, from the PXFR to VSSP pins, thereby changing the duty cycle of the power converter. This action provides flexibility in the application, allowing tradeoffs in power consumed versus power delivered. Higher power converter settings increase the burst on time which, in turn, increases average power consumed from the VDDP supply and increases the amount of power transferred to the secondary side VDDH and VDDM supplies. Similarly, lower power converter settings decrease the burst on time which, in turn, decreases average power consumed from the VDDP supply and decreases the amount of power transferred to the secondary side.

表 8-1 summarizes the three-wire mode power transfer selection.

Copyright © 2023 Texas Instruments Incorporated

表 8-1. Three-Wire Mode Power Transfer Selection

R_{PXFR} (1) (2)	Power Converter Duty Cycle (Three-Wire Mode, Nominal)	Description
7.32 kΩ	13.3%	The device supports seven, fixed power transfer settings, by selection of a corresponding R_{PXFR} value . Selecting a given power transfer setting adjusts the duty cycle of the power converter and hence the amount of power transferred. Higher power transfer settings leads to an increased duty cycle of the power converter leading to increased power transfer and consumption. During power up, the power transfer setting is determined and remains fixed at that setting until VDDP power cycles.
9.09 kΩ	26.7%	
11 kΩ	40.0%	
12.7 kΩ	53.3%	
14.7 kΩ	66.7%	
16.5 kΩ	80.0%	
20 kΩ	93.3%	

(1) Standard resistor (EIA E96), 1% tolerance, nominal value.
(2) $R_{PXFR} \geq 100$ kΩ or $R_{PXFR} \leq 1$ kΩ sets the duty cycle of the power converter to 13.3%.

8.3.6 Two-Wire Mode

図 8-4 shows the basic setup required for two-wire mode operation, which requires the EN signal and VSSP ground signal. EN can be driven up to 48 V. No current limiting resistor is required on EN because the TPSI3052 limits the input current based on the values set by the R_{PXFR} resistor (see 表 8-2). In this example, the TPSI3052 is being used to drive back-to-back MOSFETs in a common-source configuration. C_{VDDP} provides the required decoupling capacitance for the VDDP supply rail of the device. C_{DIV1} and C_{DIV2} provide the required decoupling capacitance of the VDDH and VDDM supply rails that provide the peak current to drive the external MOSFETs.

図 8-5 shows the typical operation in two-wire mode configured for standard enable. The application drives EN to a logic high and the TPSI3052 begins its power-up sequence. During power up, the current provided by the EN pin, I_{EN}, begins to charge up the external capacitance, C_{VDDP}, and the voltage on VDDP begins to rise until it reaches V_{VDDP_H}. After VDDP reaches its peak, V_{VDDP_H}, the TPSI3052 transfers stored energy on C_{VDDP} to the secondary side for a fixed time (3.3-µs typical) which begins to charge up the VDDH (and VDDM) secondary side rails thereby discharging the voltage on VDDP. In steady state, this results in an average voltage on VDDP, V_{VDDP_AVG}. This cycle repeats until the VDDH (and VDDM) secondary side rails are fully charged. The time required to fully charge VDDH depends on several factors including the values of C_{VDDP}, C_{DIV1}, C_{DIV2}, R_{PXFR}, and the overall power transfer efficiency. After VDDH is fully charged, VDRV is asserted high and remains high while the EN pin remains at a logic high. When the application drives the EN pin to a logic low, the charge on VDDP begins to discharge. Prior to VDDP reaching its UVLO falling threshold, TPSI3052 signals information from the primary side to the secondary side to de-assert VDRV and drive it low. Because power is no longer being transferred, all rails begin to fully discharge.



図 8-4. Two-Wire Mode Simplified Schematic

Copyright © 2023 Texas Instruments Incorporated



図 8-5. Two-Wire Mode with Standard Enable (TPSI3052 Only)

In two-wire mode, power is supplied directly by the EN pin. When EN is asserted high, the TPSI3052 transfers power to the secondary side for a fixed time (3.3-µs nominal) while the time period varies. The period varies due to the hysteretic control of the power transfer that ensures the average current supplied through the EN pin is maintained. The amount of average current, and hence the amount of power transferred, is programmable by selecting one of seven appropriate resistor values, R_{PXFR}, from the PXFR to VSSP pins. Higher settings of R_{PXFR} increase I_{EN} which increases the average power consumed from the EN pin and increases the amount of power transferred to the secondary side VDDH supply. Similarly, lower settings of R_{PXFR} decrease I_{EN}, which decreases the average power consumed from the EN pin and decreases the amount of power transferred to the secondary side.

表 8-2 summarizes the two-wire mode power selection.

表 8-2. Two-Wire Mode Power Selection

R_{PXFR} (1) (2)	I_{EN} (Two-Wire Mode, Nominal)	Description
7.32 kΩ	1.9 mA	The device supports seven, fixed EN input current limit options selected by the corresponding R_{PXFR} specified value. Higher current limit selections lead to increased power transfer and consumption. During power up, the EN input current limit is determined and remains fixed at that setting until VDDP power cycles.
9.09 kΩ	2.8 mA	
11 kΩ	3.7 mA	
12.7 kΩ	4.5 mA	
14.7 kΩ	5.2 mA	
16.5 kΩ	6.0 mA	
20 kΩ	6.7 mA	

(1) Standard resistor (EIA E96), 1% tolerance, nominal value.
(2) $R_{PXFR} \geq 100$ kΩ or $R_{PXFR} \leq 1$ kΩ sets the I_{EN} to 1.9 mA.

8.3.7 VDDP, VDDH, and VDDM Undervoltage Lockout (UVLO)

TPSI3052 and TPSI3052S implement an internal UVLO protection feature for both input and output power supplies, VDDP, VDDH, and VDDM. When VDDP is lower than the UVLO threshold voltage, power ceases to be transferred to the VDDM and VDDH rails. Over time the VDDH and VDDM rails will begin to discharge. If enough charge is available on VDDP, the device will attempt to signal VDRV to assert low. If not enough charge is available on VDDP, a timeout mechanism will ensure VDRV asserts low after the timeout has been reached. When either VDDH or VDDM are lower than their respective UVLO thresholds, VDRV will be asserted low regardless of the EN state. The UVLO protection blocks feature hysteresis, which helps to improve the

Copyright © 2023 Texas Instruments Incorporated

noise immunity of the power supply. During turn-on and turn-off, the driver sources and sinks a peak transient current, which can result in voltage drop of the VDDH, VDDM power supplies. The internal UVLO protection block ignores the associated noise during these normal switching transients.

8.3.8 Power Supply and EN Sequencing

During power up, the device will automatically determine if two-wire or three-wire mode is to be entered. Once two-wire or three-wire mode is determined, the mode is maintained until another power cycle is performed. Therefore, it is important to understand different scenarios that may affect the device operation.

In two-wire mode, the device is supplied power from a single external voltage source via EN, which charges the C_{VDDP} capacitance on VDDP. The voltage supply is required to meet the power supply needs at the selected PXFR setting, as well as, meet the recommended minimum ramp time, $|\Delta V_{EN}/\Delta t|$. To ensure two-wire mode is entered properly, V_{EN} must reach V_{IH_EN} prior to V_{VDDP} reaching $V_{VDDP_UV_R}$. This is summarized in 図 8-6. Similarly, it is recommend that V_{EN} meet the minimum recommended ramp down time to V_{IL_EN}. Too slow a ramp down time may cause insufficient power to be transferred while slowly transitioning between V_{IH_EN} and V_{IL_EN} leading to intermittent de-assertions and assertions of VDRV. This may continue until the power transfer reduces sufficiently to maintain VDRV low.



図 8-6. Two-wire Mode Entry

In most three-wire mode applications, EN and VDDP are supplied by the same voltage rail and source. It is recommended that V_{EN} remain below V_{IL_EN} until V_{VDDP} reaches $V_{VDDP_UV_R}$. It is also possible in some applications to connect EN directly to the VDDP supply. These two scenarios are shown in 図 8-7.



図 8-7. Three-wire Mode Power Sequences

Copyright © 2023 Texas Instruments Incorporated

In three-wire mode applications with separate voltage sources supplying EN and VDDP, it is recommended that V_{EN} remain below V_{IL_EN} until V_{VDDP} reaches $V_{VDDP_UV_R}$. If V_{EN} reaches V_{IH_EN} prior to V_{VDDP} reaching $V_{VDDP_UV_R}$, current from the supply that sources EN will attempt to power VDDP. Depending on the other supply's impedance residing on VDDP and the amount of power available from the EN pin, V_{VDDP} may begin to rise and eventually exceed $V_{VDDP_UV_R}$. At that point, the device will begin to transfer power to the secondary and start charging the VDDM and VDDH rails. If VDDP remains above $V_{VDDP_UV_R}$, the device will continue to transfer power to the secondary eventually charging the VDDM and VDDH rails and VDRV may assert high.

8.3.9 Thermal Shutdown

The device contains an integrated temperature sensor to monitor its local temperature. When the sensor reaches its threshold, it automatically ceases power transfer from the primary side to the secondary side. In addition, if power is still present on VDDP, the driver is automatically asserted low. The power transfer is disabled until the local temperature reduces enough to re-engage.

Copyright © 2023 Texas Instruments Incorporated

8.4 Device Functional Modes

表 8-3 summarizes the functional modes for the TPSI3052 and TPSI3052S.

表 8-3. TPSI3052, TPSI3052S Device Functional Modes

VDDP(6)	VDDH	EN(6)	VDRV	COMMENTS
Powered up(2)	Powered up(4)	L	L	TPSI3052 normal operation: VDRV output state assumes logic state of EN logic state.
		H	H	
		L	L	TPSI3052S normal operation (three-wire mode only): rising edge of EN causes VDRV to be singly pulsed high. EN must be asserted low first to assert another pulse.
		L → H	L → H → L	
Powered down(3)	Powered down(5)	X(1)	L	Disabled operation: VDRV output disabled, keep off circuitry applied.
Powered up(2)	Powered down(5)	X(1)	L	Disabled operation: VDRV output disabled, keep off circuitry applied.
Powered down(3)	Powered up(4)	X(1)	L	Disabled operation: when VDDP is powered down, output driver is disabled automatically after timeout, keep off circuitry applied.

(1) X: do not care.
(2) V_{VDDP} ≥ VDDP undervoltage lockout rising threshold, $V_{VDDP_UV_R}$.
(3) V_{VDDP} < VDDP undervoltage lockout falling threshold, $V_{VDDP_UV_F}$.
(4) V_{VDDH} ≥ VDDH undervoltage lockout rising threshold, $V_{VDDH_UV_R}$.
(5) V_{VDDH} < VDDH undervoltage lockout falling threshold, $V_{VDDH_UV_F}$.
(6) Refer to Power Supply and EN Sequencing for additional information.

Copyright © 2023 Texas Instruments Incorporated

9 Application and Implementation

注

以下のアプリケーション情報は、TI の製品仕様に含まれるものではなく、TI ではその正確性または完全性を保証いたしません。個々の目的に対する製品の適合性については、お客様の責任で判断していただくことになります。お客様は自身の設計実装を検証しテストすることで、システムの機能を確認する必要があります。

9.1 Application Information

The TPSI3052 is a fully integrated, isolated switch driver with integrated bias, which when combined with an external power switch, forms a complete isolated solid state relay solution. With a nominal gate drive voltage of 15 V with 1.5/3.0-A peak source and sink current, a large variety of external power switches such as MOSFETs, IGBTs, or SCRs can be chosen to meet a wide range of applications. The TPSI3052 generates its own secondary bias supply from the power received from its primary side, so no isolated secondary supply bias is required.

The TPSI3052 supports two modes of operation based on the number of input pins required. In two-wire mode, typically found in driving mechanical relays, controlling the switch requires only two pins and supports a wide voltage range of operation of 6.5 V to 48 V. In three-wire mode, the primary supply of 3 V to 5.5 V is supplied externally, and the switch is controlled through a separate enable. Available in three-wire mode only, the TPSI3052S features a one-shot enable for the switch control. This feature is useful for driving SCRs that typically require only one pulse of current to trigger.

The secondary side provides a regulated, floating supply rail of 15 V for driving a large variety of power switches with no need for a secondary bias supply. The TPSI3052 can support driving single power switch, dual back-to-back, parallel power switches for a variety of AC or DC applications. The TPSI3052 integrated isolation protection is extremely robust with much higher reliability, lower power consumption, and increased temperature ranges than those found using traditional mechanical relays and optocouplers.

The power dissipation of the TPSI3052 can be adjusted by an external resistor from the PXFR pin to VSSP. This feature allows for tradeoffs in power dissipation versus power provided on the secondary depending on the needs of the application.

9.2 Typical Application

The circuits in 図 9-1 and 図 9-2 show a typical application for driving silicon based MOSFETs in three-wire mode and two-wire mode, respectively.



図 9-1. TPSI3052 Three-Wire Mode Driving MOSFETs



図 9-2. TPSI3052 Two-Wire Mode Driving MOSFETs

9.2.1 Design Requirements

表 9-1 lists the design requirements of the TPSI3052 gate driver.

表 9-1. TPSI3052 Design Requirements

DESIGN PARAMETERS	
Total gate capacitance	100 nC
FET turn-on time	1 µs
Propagation delay	< 4 µs
Switching frequency	10 kHz
Supply voltage (VDDP)	5 V ± 5%

9.2.2 Detailed Design Procedure

9.2.2.1 Two-Wire or Three-Wire Mode Selection

The first design decision is to determine if two-wire or three-wire mode can be used in the application. For this design, note that the overall propagation delay is less than 4 µs and only three-wire mode is able to meet this requirement. In this case, two-wire mode is not applicable. Two-wire mode, due to its limited power transfer, is typically limited to very low frequency applications of less than a few kHz or when enable times are not critical.

9.2.2.2 Standard Enable, One-Shot Enable

Next, based on the application a decision must be if standard enable or one-shot enable mode is required. In this design, assume that after the switch is enabled, it is desired that the switch remain enabled until commanded to be disabled. Therefore, standard enable mode is assumed. In most applications that involve driving FETs, standard enable is appropriate. If driving SCRs or TRIACS, one-shot mode can be beneficial.

9.2.2.3 C_{DIV1}, C_{DIV2} Capacitance

The C_{DIV1} and C_{DIV2} capacitances required depends on the amount of drop that can be tolerated on the VDDH rail during switching of the external load. The charge stored on the CDIV1 and CDIV2 capacitances is used to provide the current to the load during switching. During switching, charge sharing occurs and the voltage on VDDH drops. At a minimum, TI recommends that the total capacitance formed by the series combination of C_{DIV1} and C_{DIV2} be sized to be at least 30 times the total gate capacitance to be switched. This sizing results in an approximate 0.5-V drop of the VDDH supply rail that is used to supply power to the VDRV signal. 式 1 and 式 2 can be to used to calculate the amount of capacitance required for a specified voltage drop.

C_{DIV1} and C_{DIV2} must be of the same type and tolerance.

$$C_{DIV1} = \left(\frac{n+1}{n}\right) \times \frac{Q_{LOAD}}{\Delta V},\ n \geq 3.0 \quad (1)$$

$$C_{DIV2} = n \times C_{DIV1},\ n \geq 3.0 \quad (2)$$

where

- n is a real number greater than or equal to 3.0.

Copyright © 2023 Texas Instruments Incorporated

- C_{DIV1} is the external capacitance from VDDH to VDDM.
- C_{DIV2} is the external capacitance from VDDM to VSSS.
- Q_{LOAD} is the total charge of the load from VDRV to VSSS.
- ΔV is the voltage drop on VDDH when switching the load.

注

C_{DIV1} and C_{DIV2} represent absolute capacitances and components selected must be adjusted for tolerances and any derating necessary to achieve the required capacitances.

Larger values of ΔV can be used in the application, but excessive droop can cause the VDDH undervoltage lockout falling threshold ($V_{VDDH_UVLO_F}$) to be reached and cause VDRV to be asserted low. Note that as the series combination of C_{DIV1} and C_{DIV2} capacitances increases relative to Q_{LOAD}, the VDDH supply voltage drop decreases, but the initial charging of the VDDH supply voltage during power up increases.

For this design, assuming n = 3 and ΔV≅ 0.5 V, then

$$C_{DIV1} = \left(\frac{3+1}{3}\right) \times \frac{120\,nC}{0.5\,V} = 320\,nF \tag{3}$$

$$C_{DIV2} = 3 \times 320\,nF = 960\,nF \tag{4}$$

For this design, C_{DIV1} = 330 nF and C_{DIV2} = 1 µF standard capacitor values were selected.

9.2.2.4 R_{PXFR} Selection

The selection of R_{PXFR} allows for a tradeoff between power consumed and power delivered, as described in the *Three-wire Mode* section. For this design, one must choose an appropriate R_{PXFR} selection that ensures enough power is transferred to support the amount of load being driven at the specified switching frequency.

During switching of the load, Q_{LOAD} of charge on VDDH is transferred to the load and VDDH supply voltage droops. After each switching cycle, this charge must be replenished before the next switching cycle occurs. This action ensures that the charge residing on VDDH does not deplete over time due to subsequent switching cycles of the load. The time it takes to recover this charge, $t_{RECOVER}$, can be estimated as follows:

$$t_{RECOVER} = \frac{1}{f_{MAX}} \cong \frac{Q_{LOAD}}{I_{OUT}} \tag{5}$$

where

- Q_{LOAD} is the load charge in Coulombs.
- I_{OUT} is the average current available from VDDH supply in Amperes (A).
- f_{MAX} is maximum switching frequency in Hertz (Hz).

For this design, Q_{LOAD} = 100 nC and f_{MAX} = 10 kHz are known, so I_{OUT} required can be estimated as

$$I_{OUT} \cong 100\,nC \times 10\,kHz = 1.0\,mA \tag{6}$$

I_{OUT} represents the minimum average current required to meet the design requirements. Using the TPSI3052 calculator tool, one can easily find the R_{PXFR} necessary by referring to the I_{OUT} or f_{MAX} columns directly. 表 9-2 shows the results from the tool, assuming VDDP = 4.75 V, to account for the supply tolerance specified in the design requirements. The TPSI3052 Calculator tool can be found at *Design Calculator*.

表 9-2. Results from the TPSI3052 Calculator Tool, T_A = 25°C, Three-Wire Mode

R_{PXFR}, kΩ	Power Converter Duty Cycle, %	I_{VDDP}, mA	P_{IN}, mW	P_{OUT}, mW	I_{OUT}, mA	t_{START}, µs	$t_{RECOVER}$, µs	f_{EN_MAX}, kHz	I_{AUX_MAX}, mA
7.32	13.3	5.3	25.0	5.9	0.35	N/A	N/A	N/A	N/A
9.09	21.1	8.3	39.6	10.0	0.62	N/A	N/A	N/A	N/A
11	40.0	15.8	75.1	26.8	1.74	2076	56.3	17.8	2.3

Copyright © 2023 Texas Instruments Incorporated

表 9-2. Results from the TPSI3052 Calculator Tool, T_A = 25°C, Three-Wire Mode (continued)

R_{PXFR}, kΩ	Power Converter Duty Cycle, %	I_{VDDP}, mA	P_{IN}, mW	P_{OUT}, mW	I_{OUT}, mA	t_{START}, µs	$t_{RECOVER}$, µs	f_{EN_MAX}, kHz	I_{AUX_MAX}, mA
12.7	53.3	21.1	100.1	36.1	2.35	1581	41.8	23.9	4.1
14.7	66.7	26.4	125.2	45.5	2.98	1287	33.2	30.2	6.0
16.5	80.0	31.6	150.2	58.8	3.86	1032	25.7	39.0	8.6
20	93.3	36.9	175.2	68.8	4.52	905	21.9	45.6	10.0

表 9-3 summarizes the various output parameters of the calculator tool.

表 9-3. TPSI3052 Calculator Tool Parameter Descriptions

Parameter	Description
R_{PXFR}	External resistor setting that controls the amount of power transferred to the load by adjusting the duty cycle. Higher R_{PXFR} settings lead to increased power transfer and power consumption.
Power Converter Duty Cycle	Nominal duty cycle of the power converter. Higher R_{PXFR} settings leads to higher duty cycles of the power converter and higher power transfer.
I_{VDDP}	Average current consumed from the VDDP supply
P_{IN}	Average power consumed from the VDDP supply
P_{OUT}	Average power delivered to the VDDH supply
I_{OUT}	Average current delivered to the VDDH supply
t_{START}	Start-up time from VDDP rising until VDDH supply rail is fully charged. This parameter assumes VDDH and VDDM supply rails are fully discharged initially.
$t_{RECOVER}$	Represents the time for the VDDH rail to recover after switching the load present on VDRV
f_{MAX}	Maximum switching frequency possible for a given R_{PXFR} setting for the applied loading conditions
I_{AUX_MAX}	Maximum auxiliary current available at current user input settings. There is an inverse relationship between f_{MAX} and I_{AUX_MAX}.

For this design example, R_{PXFR} must be configured to the 9.09-kΩ setting or higher to transfer enough power to support switching the specified load at the required 10-kHz frequency.

9.2.2.5 C_{VDDP} Capacitance

For two-wire mode, the recommended capacitance C_{VDDP} from VDDP to VSSP is 220 nF.

For this design, three-wire mode is required to meet the design requirements. For three-wire mode, increasing the amount of capacitance, C_{VDDP}, improves the ripple on the VDDP supply. For this design, 1 µF in parallel with 100 nF is used.

9.2.2.6 Gate Driver Output Resistor

The optional external gate driver resistors, R_{GSRC} and R_{GSNK}, along with the diode are used to:

1. Limit ringing caused by parasitic inductances and capacitances
2. Limit ringing caused by high voltage switching dv/dt, high current switching di/dt, and body-diode reverse recovery
3. Fine-tune gate drive strength for sourcing and sinking
4. Reduce electromagnetic interference (EMI)

The TPSI3052 has a pullup structure with a P-channel MOSFET with a peak source current of 1.5 A. Therefore, the peak source current can be predicted with:

$$I_{O+} \cong min\left(1.5\ A,\ \frac{V_{VDDH}}{R_{DSON_VDRV} + R_{GSRC} + R_{GFET_INT}}\right) \quad (7)$$

where

Copyright © 2023 Texas Instruments Incorporated

- R_{GSRC}: external turn-on resistance.
- R_{DSON_VDRV}: TPSI3052 driver on resistance in high state. See *Electrical Characteristics*.
- V_{VDDH}: VDDH voltage. Assumed 15.1 V in this example.
- R_{GFET_INT}: external power transistor internal gate resistance, found in the power transistor data sheet. Assume 0 Ω for this example.
- I_{O+}: peak source current. The minimum value between 1.5 A, the gate driver peak source current, and the calculated value based on the gate drive loop resistance.

For this example, R_{DSON_VDRV} = 2.5Ω, R_{GSRC} = 10 Ω, and R_{GFET_INT} = 0 Ω results in:

$$I_{O+} \cong min\left(1.5\ A, \frac{15.1\ V}{2.5\ \Omega + 10\ \Omega + 0\ \Omega}\right) = 1.21\ A \quad (8)$$

Similarly, the TPSI3052 has a pulldown structure with an N-channel MOSFET with a peak sink current of 3.0 A. Therefore, assuming R_{GFET_INT} = 0 Ω, the peak sink current can be predicted with:

$$I_{O-} \cong min\left[3.0\ A, (V_{VDDH} \times (R_{GSRC} + R_{GSNK}) - R_{GSRC} \times V_F) \times \frac{1}{R_{GSRC} \times R_{GSNK} + R_{DSON_VDRV} \times (R_{GSRC} + R_{GSNK})}\right] \quad (9)$$

where

- R_{GSRC}: external turn-on resistance.
- R_{GSNK}: external turn-off resistance.
- R_{DSON_VDRV}: TPSI3052 driver on resistance in low state. See *Electrical Characteristics*.
- V_{VDDH}: VDDH voltage. Assumed 15.1 V in this example.
- V_F: diode forward voltage drop. Assumed 0.7 V in this example.
- I_{O-}: peak sink current. The minimum value between 3.0 A, the gate driver peak sink current, and the calculated value based on the gate drive loop resistance.

For this example, assuming R_{DSON_VDRV} = 1.7 Ω, R_{GSRC} = 10 Ω, R_{GSNK} = 5.0 Ω, and R_{GFET_INT} = 0 Ω, results in:

$$I_{O-} \cong min\left[3.0\ A, (15.1\ V \times (10\ \Omega + 5\ \Omega) - 10\Omega \times 0.7\ V) \times \frac{1}{10\ \Omega \times 5\ \Omega + 1.7\ \Omega \times (10\Omega + 5\ \Omega)}\right] = 2.91\ A \quad (10)$$

Importantly, the estimated peak current is also influenced by PCB layout and load capacitance. Parasitic inductance in the gate driver loop can slow down the peak gate drive current and introduce overshoot and undershoot. Therefore, TI strongly recommends to minimize the gate driver loop.

9.2.2.7 Start-up Time and Recovery Time

As described in the *C_{DIV1}, C_{DIV2} Capacitance* section, the start-up time of the fully discharged VDDH rail depends on the amount of capacitance present on the VDDH supply. The rate at which this capacitance is charged depends on the amount of power transferred from the primary side to the secondary side. The amount of power transferred can be adjusted by choosing R_{PXFR}. Increasing the resistor settings for R_{PXFR} transfers more power from the primary supply (VDDP) to the secondary supply (VDDH), thereby reducing the overall start-up and recovery times.

9.2.2.8 Supplying Auxiliary Current, I_{AUX} From VDDM

The TPSI3052 is capable of providing power from VDDM to support external auxiliary circuitry as shown in 図 9-3. In this case, the required transfer power must include the additional power consumed by the auxiliary circuitry on the VDDM rail. The R_{PXFR} value must be set to meet the overall power requirements.

Copyright © 2023 Texas Instruments Incorporated



図 9-3. Supplying Auxiliary Power From VDDM

As an example, assume that the auxiliary circuitry requires an average current of 4 mA. 表 9-4 summarizes the results from the TPSI3052 calculator tool. The Calculator tool can be found at *Design Calculator*.

表 9-4. Results from the TPSI3052 Calculator Tool, T_A = 25°C, Three-Wire Mode with I_{AUX} = 4 mA

R_{PXFR}, kΩ	Power Converter Duty Cycle, %	I_{VDDP}, mA	P_{IN}, mW	P_{OUT}, mW	I_{OUT}, mA	t_{START}, µs	$t_{RECOVER}$, µs	f_{EN_MAX}, kHz	I_{AUX_MAX}, mA
7.32	13.3	5.3	25.0	5.9	0.35	N/A	N/A	N/A	N/A
9.09	21.1	8.3	39.6	10.0	0.62	N/A	N/A	N/A	N/A
11	40.0	15.8	75.1	26.8	1.74	N/A	N/A	N/A	N/A
12.7	53.3	21.1	100.1	36.1	2.35	3557	96.0	10.4	4.1
14.7	66.7	26.4	125.2	45.5	2.98	2285	60.1	16.6	6.0
16.5	80.0	31.6	150.2	58.8	3.86	1549	39.3	25.5	8.6
20	93.3	36.9	175.2	68.8	4.52	1262	31.2	32.1	10.0

Based on the results in 表 9-4, several observations can be made:

- With R_{PXFR} = 7.32 kΩ , R_{PXFR} = 9.09 kΩ, and R_{PXFR} = 11 kΩ, insufficient power is available to meet the application power needs specified in the design requirements in 表 9-1.
- With R_{PXFR} = 12.7 kΩ and higher, sufficient power is transferred to meet the specified design requirements, however, for this design, R_{PXFR} = 14.7 kΩ was selected for additional margin.
- For a given R_{PXFR}, because a significant amount of the transferred power is being provided to the auxiliary circuitry, t_{START} is longer, and f_{MAX} reduced when compared to the results shown in 表 9-4 with I_{AUX} = 0 mA.

9.2.2.9 VDDM Ripple Voltage

Note that when supplying power from VDDM, that is when I_{AUX} > 0 mA, additional voltage ripple is present on the VDDM rail. For a given R_{PXFR} setting, this ripple can be reduced by applying additional capacitance from VDDM to VSSS or increasing the R_{PXFR} setting for more power tranfser. For this design example, the ripple on VDDM, $VDDM_{ripple}$, computed in the calculator tool is 35 mV.

Copyright © 2023 Texas Instruments Incorporated

9.2.3 Application Curves



Three-wire mode　VDDP = 5.0 V　R_{PXFR} = 11 kΩ
C_{DIV1} = 330 nF　C_{DIV2} = 1 µF
I_{AUX} = 0 mA　C_{VDRV} = 6.8 nF　T_A = 25°C

図 9-4. Power Up, V_{EN} = V_{VDDP}, Three-Wire Mode, TPSI3052



Three-wire mode　VDDP = 5.0 V　R_{PXFR} = 11 kΩ
C_{DIV1} = 330 nF　C_{DIV2} = 1 µF
I_{AUX} = 0 mA　C_{VDRV} = 6.8 nF　T_A = 25°C

図 9-5. t_{LH_VDRV}, Three-Wire Mode, TPSI3052



Three-wire mode　VDDP = 5.0 V　R_{PXFR} = 11 kΩ
C_{DIV1} = 330 nF　C_{DIV2} = 1 µF
I_{AUX} = 0 mA　C_{VDRV} = 6.8 nF　T_A = 25°C

図 9-6. t_{HL_VDRV}, Three-Wire Mode, TPSI3052



Three-wire mode　VDDP = 5.0 V　R_{PXFR} = 11 kΩ
C_{DIV1} = 330 nF　C_{DIV2} = 1 µF
I_{AUX} = 0 mA　C_{VDRV} = 6.8 nF　T_A = 25°C

図 9-7. Three-Wire Mode, f_{EN} = 10 kHz, TPSI3052



Three-wire mode　VDDP = 5.0 V　R_{PXFR} = 14.7 kΩ
C_{DIV1} = 330 nF　C_{DIV2} = 1 µF
I_{AUX} = 4 mA　C_{VDRV} = 6.8 nF　T_A = 25°C

図 9-8. Power Up, V_{EN} = V_{VDDP}, Three-Wire Mode, TPSI3052



Three-wire mode　VDDP = 5.0 V　R_{PXFR} = 14.7 kΩ
C_{DIV1} = 330 nF　C_{DIV2} = 1 µF
I_{AUX} = 4 mA　C_{VDRV} = 6.8 nF　T_A = 25°C

図 9-9. t_{LH_VDRV}, Three-Wire Mode, TPSI3052

Copyright © 2023 Texas Instruments Incorporated

9.2.3 Application Curves (continued)



Three-wire mode | VDDP = 5.0 V | R_{PXFR} = 14.7 kΩ
C_{DIV1} = 330 nF | C_{DIV2} = 1 µF
I_{AUX} = 4 mA | C_{VDRV} = 6.8 nF | T_A = 25°C

図 9-10. t_{HL_VDRV}, Three-Wire Mode, TPSI3052



Three-wire mode | VDDP = 5.0 V | R_{PXFR} = 14.7 kΩ
C_{DIV1} = 330 nF | C_{DIV2} = 1 µF
I_{AUX} = 4 mA | C_{VDRV} = 6.8 nF | T_A = 25°C

図 9-11. Three-Wire Mode, f_{EN} = 10 kHz, TPSI3052

9.3 Power Supply Recommendations

In three-wire mode, to help ensure a reliable supply voltage, TI recommends that the C_{VDDP} capacitance from VDDP to VSSP consists of a 0.1-µF bypass capacitor for high frequency decoupling in parallel with a 1 µF for low frequency decoupling.

In two-wire mode, TI recommends that the C_{VDDP} capacitance placed from VDDP to VSSP consists of a 220-nF capacitor connected close to the device between the VDDP and VSSP pins. The recommended absolute capacitance must be 220 nF, so if derating is required, a higher component value can be needed.

Low-ESR and low-ESL capacitors must be connected close to the device between the VDDP and VSSP pins.

9.4 Layout

9.4.1 Layout Guidelines

Designers must pay close attention to PCB layout to achieve optimum performance for the TPSI3052. Some key guidelines are:

- Component placement:
  - Place the driver as close as possible to the power semiconductor to reduce the parasitic inductance of the gate loop on the PCB traces.
  - Connect low-ESR and low-ESL capacitors close to the device between the VDDH and VDDM pins and the VDDM and VSSS pins to bypass noise and to support high peak currents when turning on the external power transistor.
  - Connect low-ESR and low-ESL capacitors close to the device between the VDDP and VSSP pins.
  - Minimize parasitic capacitances on the R_{PXFR} pin.
- Grounding considerations:
  - Limit the high peak currents that charge and discharge the transistor gates to a minimal physical area. This limitation decreases the loop inductance and minimizes noise on the gate terminals of the transistors. Place the gate driver as close as possible to the transistors.
  - Connect the driver VSSS to the Kelvin connection of MOSFET source or IGBT emitter. If the power device does not have a split Kelvin source or emitter, connect the VSSS pin as close as possible to the source or emitter terminal of the power device package to separate the gate loop from the high power switching loop.
- High-voltage considerations:

Copyright © 2023 Texas Instruments Incorporated

  - To ensure isolation performance between the primary and secondary side, avoid placing any PCB traces or copper below the driver device. TI recommends a PCB cutout or groove to prevent contamination that can compromise the isolation performance.
- Thermal considerations:
  - Proper PCB layout can help dissipate heat from the device to the PCB and minimize junction-to-board thermal impedance (θ_{JB}).
  - If the system has multiple layers, TI also recommends connecting the VDDH and VSSS pins to internal ground or power planes through multiple vias of adequate size. These vias must be located close to the IC pins to maximize thermal conductivity. However, keep in mind that no traces or coppers from different high voltage planes are overlapping.

9.4.2 Layout Example

図 9-12 shows a PCB layout example with the signals and key components labeled.



図 9-12. 3-D PCB View

図 9-13 and 図 9-14 show the top and bottom layer traces and copper.



図 9-13. Top Layer

Copyright © 2023 Texas Instruments Incorporated



図 9-14. Bottom Layer

10 Device and Documentation Support

10.1 Related Links

The table below lists quick access links. Categories include technical documents, support and community resources, tools and software, and quick access to order now.

表 10-1. Related Links

PARTS	PRODUCT FOLDER	ORDER NOW	TECHNICAL DOCUMENTS	TOOLS & SOFTWARE	SUPPORT & COMMUNITY
TPSI3052	Click here	Click here	Click here	Click here	Click here
TPSI3052S	Click here	Click here	Click here	Click here	Click here

10.2 ドキュメントの更新通知を受け取る方法

ドキュメントの更新についての通知を受け取るには、ti.com のデバイス製品フォルダを開いてください。「更新の通知を受け取る」をクリックして登録すると、変更されたすべての製品情報に関するダイジェストを毎週受け取れます。変更の詳細については、修正されたドキュメントに含まれている改訂履歴をご覧ください。

10.3 サポート・リソース

TI E2E™ サポート・フォーラムは、エンジニアが検証済みの回答と設計に関するヒントをエキスパートから迅速かつ直接得ることができる場所です。既存の回答を検索したり、独自の質問をしたりすることで、設計で必要な支援を迅速に得ることができます。

リンクされているコンテンツは、該当する貢献者により、現状のまま提供されるものです。これらは TI の仕様を構成するものではなく、必ずしも TI の見解を反映したものではありません。TI の使用条件を参照してください。

10.4 Trademarks

TI E2E™ is a trademark of Texas Instruments.
すべての商標は、それぞれの所有者に帰属します。

10.5 静電気放電に関する注意事項

この IC は、ESD によって破損する可能性があります。テキサス・インスツルメンツは、IC を取り扱う際には常に適切な注意を払うことを推奨します。正しい取り扱いおよび設置手順に従わない場合、デバイスを破損するおそれがあります。

ESD による破損は、わずかな性能低下からデバイスの完全な故障まで多岐にわたります。精密な IC の場合、パラメータがわずかに変化するだけで公表されている仕様から外れる可能性があるため、破損が発生しやすくなっています。

10.6 用語集

テキサス・インスツルメンツ用語集　この用語集には、用語や略語の一覧および定義が記載されています。

11 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

Copyright © 2023 Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable part number	Status (1)	Material type (2)	Package | Pins	Package qty | Carrier	RoHS (3)	Lead finish/ Ball material (4)	MSL rating/ Peak reflow (5)	Op temp (°C)	Part marking (6)
TPSI3052DWZR	Active	Production	SO-MOD (DWZ) | 8	1000 | LARGE T&R	Yes	NIPDAU	Level-3-260C-168 HR	-40 to 125	I3052
TPSI3052DWZR.A	Active	Production	SO-MOD (DWZ) | 8	1000 | LARGE T&R	Yes	NIPDAU	Level-3-260C-168 HR	-40 to 125	I3052
TPSI3052DWZR.B	Active	Production	SO-MOD (DWZ) | 8	1000 | LARGE T&R	-	Call TI	Call TI	-40 to 125	
TPSI3052SDWZR	Active	Production	SO-MOD (DWZ) | 8	1000 | LARGE T&R	Yes	NIPDAU	Level-3-260C-168 HR	-40 to 125	I3052S
TPSI3052SDWZR.A	Active	Production	SO-MOD (DWZ) | 8	1000 | LARGE T&R	Yes	NIPDAU	Level-3-260C-168 HR	-40 to 125	I3052S
TPSI3052SDWZR.B	Active	Production	SO-MOD (DWZ) | 8	1000 | LARGE T&R	-	Call TI	Call TI	-40 to 125	

(1) **Status:** For more details on status, see our product life cycle.

(2) **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

(3) **RoHS values:** Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

(4) **Lead finish/Ball material:** Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

(5) **MSL rating/Peak reflow:** The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

(6) **Part marking:** There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF TPSI3052 :

- Automotive : TPSI3052-Q1

NOTE: Qualified Version Definitions:

- Automotive - Q100 devices qualified for high-reliability automotive applications targeting zero defects

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TPSI3052DWZR	SO-MOD	DWZ	8	1000	330.0	16.4	12.05	6.15	3.3	16.0	16.0	Q1
TPSI3052SDWZR	SO-MOD	DWZ	8	1000	330.0	16.4	12.05	6.15	3.3	16.0	16.0	Q1

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TPSI3052DWZR	SO-MOD	DWZ	8	1000	350.0	350.0	43.0
TPSI3052SDWZR	SO-MOD	DWZ	8	1000	350.0	350.0	43.0

PACKAGE OUTLINE

DWZ0008A

SOIC - 2.8 mm max height

SMALL OUTLINE PACKAGE



NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 mm per side.
4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
5. Ref. JEDEC registration MS-013



LAND PATTERN EXAMPLE
9.1 mm NOMINAL CLEARANCE/CREEPAGE
SCALE: 6X



NON SOLDER MASK
DEFINED

SOLDER MASK
DEFINED

SOLDER MASK DETAILS

4226306/A 09/2020

NOTES: (continued)

5. Publication IPC-7351 may have alternate designs.
6. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SOLDER PASTE EXAMPLE
BASED ON 0.125 mm THICK STENCIL
SCALE: 6X

4226306/A 09/2020

NOTES: (continued)

7. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
8. Board assembly site may have different recommendations for stencil design.

重要なお知らせと免責事項

TI は、技術データと信頼性データ (データシートを含みます)、設計リソース (リファレンス デザインを含みます)、アプリケーションや設計に関する各種アドバイス、Web ツール、安全性情報、その他のリソースを、欠陥が存在する可能性のある「現状のまま」提供しており、商品性および特定目的に対する適合性の黙示保証、第三者の知的財産権の非侵害保証を含むいかなる保証も、明示的または黙示的にかかわらず拒否します。

これらのリソースは、TI 製品を使用する設計の経験を積んだ開発者への提供を意図したものです。(1) お客様のアプリケーションに適した TI 製品の選定、(2) お客様のアプリケーションの設計、検証、試験、(3) お客様のアプリケーションに該当する各種規格や、その他のあらゆる安全性、セキュリティ、規制、または他の要件への確実な適合に関する責任を、お客様のみが単独で負うものとします。

上記の各種リソースは、予告なく変更される可能性があります。これらのリソースは、リソースで説明されている TI 製品を使用するアプリケーションの開発の目的でのみ、TI はその使用をお客様に許諾します。これらのリソースに関して、他の目的で複製することや掲載することは禁止されています。TI や第三者の知的財産権のライセンスが付与されている訳ではありません。お客様は、これらのリソースを自身で使用した結果発生するあらゆる申し立て、損害、費用、損失、責任について、TI およびその代理人を完全に補償するものとし、TI は一切の責任を拒否します。

TI の製品は、 TI の販売条件 、 TI の総合的な品質ガイドライン 、 ti.com または TI 製品などに関連して提供される他の適用条件に従い提供されます。TI がこれらのリソースを提供することは、適用される TI の保証または他の保証の放棄の拡大や変更を意味するものではありません。 TI がカスタム、またはカスタマー仕様として明示的に指定していない限り、TI の製品は標準的なカタログに掲載される汎用機器です。

お客様がいかなる追加条項または代替条項を提案する場合も、TI はそれらに異議を唱え、拒否します。

Copyright © 2025, Texas Instruments Incorporated

最終更新日：2025 年 10 月