

CC3100/CC3200 WLAN RF Transmit Power Peak and Average Measurements

Application Report



Literature Number: SWRA460

June 2014

1	Wireless LAN Transmit Power Measurements	3
2	Peak Versus Average Wireless LAN Transmit Power Measurements	4
3	References	5

CC3100/CC3200 WLAN RF Transmit Power Peak and Average Measurements

Embedded Processing Applications

ABSTRACT

This application report considers factors that impact radio-frequency transmit power measurements and, in particular, the difference between peak and average measurements recorded on systems using the Texas Instruments CC3100 SimpleLink™ Wi-Fi^(R) Network Processor and CC3200 SimpleLink™ Wi-Fi^(R) Wireless MCU. The document also describes the situations in which each type of power measurement is typically used.

1 Wireless LAN Transmit Power Measurements

RF transmit power is an important performance parameter for a wireless LAN system. The transmit power value is important because it can impact system regulatory compliance. The transmit power of two systems that are otherwise similar can also provide an indication of which system supports the greatest communication range to the receiver.

In order to compare different transmit power values, it is important to know several characteristics of the measurements. These include understanding:

- If the measurement was made over the air with antennas in place, or if the measurement was made using cables to produce a conducted measurement.
- For conducted measurements, it is important to know the location in the system where the power was measured. Common measurement points are at the power amplifier chip pin or at the input to the antenna.
- The Wireless LAN modulation scheme and physical layer data rate in use during the measurement should also be specified. Common examples include:
 - 802.11b 1 Mbps DSSS
 - 802.11b 11 Mbps CCK
 - 802.11g 6 Mbps OFDM
 - 802.11g 54 Mbps OFDM
 - 802.11n 72 Mbps MCS7
- The frequency and channel where the measurement was taken as well as the channel width (typically 20 MHz)
- The method used to measure the power over time, for example, average power or peak power and the period of time when the measurement was made.
- The ambient temperature when the measurement was made.
- If this is a measurement from an individual system or the result of a series of measurements of many systems presented as a minimum, typical or maximum value.

Reference documents [1], [2] and [3] describe a variety of techniques for making RF transmit power measurements using lab test equipment from various vendors.

2 Peak Versus Average Wireless LAN Transmit Power Measurements

If two transmit power figures are compared, it is especially important that they both be measured using the same method. For example, they both be peak measurements or they both be average measurements. Generally, technical documentation such as chip data sheets and system application notes quote average transmit power. Regulatory filings, such as those presented to the FCC in the USA, generally quote peak transmit power figures.

The difference between a peak transmit power measurement and an average transmit power measurement is a strong function of the transmit waveform shape, and in the case of wireless LAN, the transmit waveform shape is a function of the modulation scheme being used.

Table 1 shows peak and average transmit power measurements that were recorded in a conducted test with a probe placed at the antenna port on a CC3100 evaluation system. The individual measurements were taken from a single evaluation system at room temperature operating on channel 7. The average and peak transmit powers were measured for a series of physical layer rates and modulation schemes.

Table 1. Peak and Average Transmit Power Measurements

Physical Layer Rate and Modulation	Average Power	Peak Power
	dBm	dBm
1 DSSS	18.2	20.3
11 CCK	18.6	20.5
6/9 OFDM	17.5	23.0
12/18OFDM MCS 1/2	17.3	22.8
24/36OFDM MCS 3/4	16.1	22.8
48/54OFDM MCS 5/6	14.5	22.7
MCS0_MM	17.4	23.2
MCS7_MM	13.2	22.7

It can be seen from Table 1 that the difference between average and peak measurements varies significantly as the physical layer rate and modulation change. For the case of an 802.11b 1Mbps DSSS waveform, the difference between average power and peak power measurements is 2.1dB. For the case of 802.11n 72 Mbps MCS7 in mixed mode, the difference between average power and peak power is 9.5dB. It can also be seen from the table that modulation rates that have the same peak power have differing average power measurements. For example, 12/18OFDM and 24/36OFDM which both resulted in a 22.8 dBm peak power measurement, support different average power levels.

The change in the difference between the average power and peak power measurements as a function of modulation reflects the change in the Wireless LAN waveform. While the peak and average value of a waveform can be calculated mathematically, there are other system factors that determine the measured difference in peak and average power. One such factor is the change in linearity of the wireless LAN system, as the RF chain is automatically reconfigured for optimal performance as the modulation scheme changes.

Table 1 clearly shows that average and peak power figures differ significantly and that there is no easily computed conversion factor, so measurements obtained using these different methods should not generally be directly compared.

3 References

1. *Fundamentals of RF Microwave Power Measurements*: Agilent April 2001
(<http://cp.literature.agilent.com/litweb/pdf/5965-6630E.pdf>)
2. *Power Measurements of OFDM Signals* by Briggs, Martinez and Bare
(<http://www.elliottlabs.com/documents/OFDM.pdf>)
3. *Practical Manufacturing Testing of 802.11 OFDM Wireless Devices*: LitePoint : 2012
(http://www.litepoint.com/wp-content/uploads/2014/02/Testing-802.11-OFDM-Wireless-Devices_WhitePaper-1.pdf)

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com