

PMP6003 Rev. C BOM
230VAC to 32V/350mA TRIAC Dimmable LED Driver

Qty	RefDes	DESCRIPTION	MFR	PART NUMBER
1	BR1	IC RECT BRIDGE 0.5A 600V 4SOIC	Diodes	MB6S
1	C1	CAP .22UF/400VDC METAL POLY	Panasonic	ECQ-E4224KF
1	C2	CAP CER 15000PF 250V X7R 1206	Std	Std
1	C3	CAP CER 10000PF 50V X7R 0603	Std	Std
1	C4	CAP CER .1UF 50V X7R 10% 0603	Std	Std
1	C5	CAP 100UF 25V ELECT RADIAL 2.5MM	Std	Std
2	C6,C7	CAP CER 2.2UF 100V X7R 1210	Std	Std
1	C8	CAP 560UF 50V ELECT HE RADIAL	Std	Std
1	C9	CAP .022UF/630VDC METAL POLY	Panasonic	ECQ-E6223KF
5	C10,C15,C17,C18,C19	CAP CER 10000PF 25V X7R 0603	Std	Std
1	C11	CAP CER 2.2NF X1/Y1 RADIAL	muRata	DE1E3KX222M
1	C12	CAP CER 220PF 630VDC U2J 1206	Std	Std
1	C13	CAP CER 0.33UF 16V X7R 0603	Std	Std
1	C14	CAP CER 1UF 16V X7R 0805	Std	Std
1	C16	CAP CER .1UF 25V 0805	Std	Std
1	C21	CAP .022UF/305VAC X2 METAL POLYPRO	Epcos	B32921C3223M
1	D1	DIODE ULTRA FAST 800V 1A SMA	ST	STTH108A
1	D3	DIODE ULTRA FAST 200V SOT-23	Fairchild	MMBD1404
1	D4	DIODE ZENER 18V 225MW SOT-23	Std	Std
1	D5	DIODE GPP FAST 1A 600V DO-41	Std	UF4005
1	D6	DIODE GPP FAST 1A 600V SMA	Std	RS1J
1	D8	SHUNT REGULATOR 5.0V SOT-23	TI	LM4040C50
1	D9	DIODE, SWITCHING 70V SC-70	Std	BAW56W
1	F1	FUSE PICO FAST 2.5A 250V AXIAL	Littelfuse	026302.5WRT1L
1	L1	IND COMMON MODE CHOKE 40MH	Würth	750311650
1	L2	JUMPER (RES 0.0 OHM 1206)	Std	Std
1	Q1	MOSFET N-CH 650V 7.3A TO-220FP	Infineon	SPA07N60C3
1	Q2	TRANSISTOR NPN 100V 1A SOT-89	Diodes	FCX493TA
1	Q6	TRANSISTOR NPN GP 40V SOT23	Std	MMBT3904
3	R1,R2,R31	RES 560K OHM 1/4W 1% 0805 SMD	Std	Std
3	R3,R6,R15	RES 100K OHM 1/10W 1% 0603 SMD	Std	Std
1	R4	RES 75.0K OHM 1/4W 1% 1206 SMD	Std	Std
1	R5	RES 510 OHM METAL FILM 2W 5%	Std	Std
1	R7	RES 464K OHM 1/10W 1% 0603 SMD	Std	Std
1	R8	RES 4.42K OHM 1/10W 1% 0603 SMD	Std	Std
1	R9	RES 39.2 OHM 1/8W 1% 0805 SMD	Std	Std
1	R10	RES 1.0K OHM METAL FILM 2W 5%	Std	Std
1	R11	RES 110K OHM 1/8W 1% 0805 SMD	Std	Std
1	R12	RES 33.2K OHM 1/10W 1% 0603 SMD	Std	Std
1	R13	RES 40.2K OHM 1/10W 1% 0603 SMD	Std	Std
1	R14	RES 634K OHM 1/10W 1% 0603 SMD	Std	Std
1	R16	RES 4.99 OHM 1/10W 1% 0603 SMD	Std	Std
1	R17	RES 3.01 OHM 1/8W 1% 0805 SMD	Std	Std
1	R18	RES 10.0K OHM 1/10W 1% 0603 SMD	Std	Std
1	R19	RES .33 OHM 1/4W 1% 1206 SMD	Std	Std
1	R20	RES 365K OHM 1/10W 1% 0603 SMD	Std	Std
1	R21	RES 71.5K OHM 1/10W 1% 0603 SMD	Std	Std
1	R22	RES 200K OHM 1/10W 1% 0603 SMD	Std	Std
2	R24,R35	RES 3.01K OHM 1/10W 1% 0603 SMD	Std	Std

PMP6003 Rev. C BOM
230VAC to 32V/350mA TRIAC Dimmable LED Driver

Qty	RefDes	DESCRIPTION	MFR	PART NUMBER
2	R25,R33	RES 1.00M OHM 1/10W 1% 0603 SMD	Std	Std
1	R26	RES 2.00K OHM 1/10W 1% 0603 SMD	Std	Std
1	R27	RES 511K OHM 1/10W 1% 0603 SMD	Std	Std
2	R23,R28	RES 20.0K OHM 1/10W 1% 0603 SMD	Std	Std
1	R29	RES 12.7K OHM 1/8W 1% 0805 SMD	Std	Std
1	R30	RES 604K OHM 1/10W 1% 0603 SMD	Std	Std
1	R32	RES 17.4K OHM 1/10W 1% 0603 SMD	Std	Std
1	R40	RES 16.5K OHM 1/10W 1% 0603 SMD	Std	Std
0	R41	DNL		
0	R42	DNL		
1	R43	RES 0.0 OHM 1/20W 5% 0603 SMD	Std	Std
1	T1	TRANSFORMER FLYBACK EE20/10/6	Würth	750811145
1	U1	IC PWM CTRLR CASCODE 8-SOIC	TI	TPS92210
1	U2	OPTO ISOLATOR TRANSISTOR OUTPUT	CEL/NEC	PS2581L1
3	U3,U4,U5	IC OPAMP GP R-R 1MHZ SGL SOT23-5	TI	LMV321IDBVR
1	VR1	SUR ABSORBER 7MM 430V 1250A ZNR	Panasonic	ERZ-V07D431

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
RF/IF and ZigBee® Solutions	www.ti.com/lprf

Applications

Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Transportation and Automotive	www.ti.com/automotive
Video and Imaging	www.ti.com/video
Wireless	www.ti.com/wireless-apps

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated