

Product Change Notification Form

PCN#: LMI-PCN-0800009 **PCN Revision: A** **Issue Date: 13-May-2008**

Type of Change: Level 3 **Effective Date: N/A**

Reason(s) for Change:
 These changes are necessary for compatibility with future device revisions.

Detailed Description of Changes:

Luminary Micro recommends that customer designs do not supply VDD25 inputs from an external voltage regulator. Instead, use only the LDO output as the source of VDD25 input. Future releases of product documentation will not include the option of providing VDD25 power from external sources.

Stellaris® devices incorporating an Ethernet controller should have a 12.4-kΩ resistor connected between pin 41 (for LQFP devices) or ball K3 (for BGA devices), and GND for compatibility with future device revisions.

In future revisions, pin 41 and ball K3 will be renamed from GNDPHY to ERBIAS.

Customers should include this resistor in all new designs. Existing designs should be modified to include this change during the next board design cycle.


The 12.4-kΩ resistor should have a 1% tolerance and should be located in close proximity to pin 41 or ball K3. Power dissipation in the resistor is low, so a chip resistor of any geometry may be used.

Three of the nine Ethernet LED configuration options will not be supported in future revisions of Ethernet-enabled Stellaris® controllers and should not be used. The three options are TX Activity (0x2), RX Activity (0x3), and Collision (0x4). Future releases of the product documentation will list these options as reserved.

Register 27: Ethernet PHY Management Register 23 – LED Configuration (MR23), address 0x17

Ethernet PHY Management Register 23 – LED Configuration (MR23)

Base 0x4004.8000
 Address 0x17
 Type R/W, reset 0x0010



Bit/Field	Name	Type	Reset	Description																				
15:8	reserved	RO	0x0	Software should not rely on the value of a reserved bit. To provide compatibility with future products, the value of a reserved bit should be preserved across a read-modify-write operation.																				
7:4	LED1[3:0]	R/W	1	LED1 Source The LED1 field selects the source that toggles the LED1 signal. <table border="1"> <thead> <tr> <th>Value</th> <th>Description</th> </tr> </thead> <tbody> <tr><td>0x0</td><td>Link OK</td></tr> <tr><td>0x1</td><td>RX or TX Activity (Default LED1)</td></tr> <tr><td>0x2</td><td>Reserved</td></tr> <tr><td>0x3</td><td>Reserved</td></tr> <tr><td>0x4</td><td>Reserved</td></tr> <tr><td>0x5</td><td>100BASE-TX mode</td></tr> <tr><td>0x6</td><td>10BASE-T mode</td></tr> <tr><td>0x7</td><td>Full-Duplex</td></tr> <tr><td>0x8</td><td>Link OK & Blink=RX or TX Activity</td></tr> </tbody> </table>	Value	Description	0x0	Link OK	0x1	RX or TX Activity (Default LED1)	0x2	Reserved	0x3	Reserved	0x4	Reserved	0x5	100BASE-TX mode	0x6	10BASE-T mode	0x7	Full-Duplex	0x8	Link OK & Blink=RX or TX Activity
Value	Description																							
0x0	Link OK																							
0x1	RX or TX Activity (Default LED1)																							
0x2	Reserved																							
0x3	Reserved																							
0x4	Reserved																							
0x5	100BASE-TX mode																							
0x6	10BASE-T mode																							
0x7	Full-Duplex																							
0x8	Link OK & Blink=RX or TX Activity																							

3:0	LED0[3:0]	R/W	0	LED0 Source
The LED0 field selects the source that toggles the LED0 signal.				
	Value	Description		
	0x0	Link OK (Default LED0)		
	0x1	RX or TX Activity		
	0x2	<i>Reserved</i>		
	0x3	<i>Reserved</i>		
	0x4	<i>Reserved</i>		
	0x5	10BASE-TX mode		
	0x6	10BASE-T mode		
	0x7	Full-Duplex		
	0x8	Link OK & Blink=RX or TX Activity		

Products Affected:

Part Number	Description
LM3S6618-IQC50	Microcontroller
LM3S6618-EQC50	Microcontroller
LM3S6618-IBZ50	Microcontroller

Forecasted Key Milestones: Not Applicable

Milestone	Date
N/A	N/A

Recommended Action:

Implement these changes during the next board design cycle to facilitate future design compatibility.

Reference Documents/Attachments: N/A

Should you have any issues with the timeline or content of this change, please contact the representative listed below within 90 days. No response will be deemed as customer's acceptance of the change and the change will be applicable as shown in the effective date set forth in this PCN.

For questions, concerns, or comments please direct all correspondence to: customer.service@luminarymicro.com

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
RF/IF and ZigBee® Solutions	www.ti.com/lprf

Applications

Audio	www.ti.com/audio
Automotive	www.ti.com/automotive
Broadband	www.ti.com/broadband
Digital Control	www.ti.com/digitalcontrol
Medical	www.ti.com/medical
Military	www.ti.com/military
Optical Networking	www.ti.com/opticalnetwork
Security	www.ti.com/security
Telephony	www.ti.com/telephony
Video & Imaging	www.ti.com/video
Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2009, Texas Instruments Incorporated