

# TM4C129x Connected Development Kit



The TM4C129x Connected Development Kit (DK-TM4C129X) is a versatile and feature-rich engineering platform highlighting the 120-MHz TM4C129XNCZADI microcontroller that includes an integrated 10/100 Ethernet MAC+PHY, ARM® Cortex®-M4 CPU plus many other key features.

## Development Kit Overview

Beyond the industry-leading Ethernet integration, this kit and its associated microcontroller (MCU), the TM4C129XNCZADI, also showcase integrated functions such as a color LCD interface, USB 2.0 OTG/Host/Device port, TI wireless EM connec-


tion, BoosterPack and BoosterPack XL interfaces, a Quad SSI-supported 512Mbit Flash memory, MicroSD slot, plus expansion headers providing easy access for interfacing to the MCU's high-speed USB ULPI port, Ethernet RMII / MII ports, and its external peripheral interface, which supports memories, parallel peripherals and other system functions.

## Development Kit Contents

The DK-TM4C129X development kit contains everything you need to develop and run applications for TM4C MCUs, including an In-Circuit Debug Interface (ICDI) and an extensive software offering that provides libraries

## Features


- Based on TM4C129XNCZADI
  - 120-MHz ARM Cortex-M4 CPU (DSC w/ FPU)
  - 1MB Flash / 256KB SRAM / 6KB EEPROM
  - 8 timers (8×32-bit / 16×16-bit), plus SysTick and watchdogs
  - Motion-control PWM outputs
  - 10 I<sup>2</sup>C, 8 UARTs, 4 QSPIs, 2 CAN, USB FS and HS support
  - 10/100 Ethernet MAC and PHY
  - LCD control module
  - 212-pin nBGA with up to 140 GPIOs
- External system connection options
  - Standard BoosterPack and BoosterPack XL
  - TI wireless EM interface
  - Available I/O expansion
    - ULPI USB external PHY (for high-speed USB 2.0)
    - RMII/MII external Ethernet PHY
    - EPI, Host bus 16/8
- Ethernet RJ-45 jack
- USB H/D/O micro A/B USB connector
- Color QVGA display with resistive touch screen
- QSSI connected 512Mbit Flash memory and microSD slot
- 3× user buttons, tri-color user LED and speaker
- Hardware reset button and system LED indicators
- TM4C In-Circuit Debug Interface (XDS-ICDI) and standard 20-pin JTAG debug header
- Tool chains: Code Composer Studio™ IDE, Keil, IAR, CodeBench and GCC
- TivaWare™ DriverLib under TI BSD-style license



▲ TM4C129x Development Kit

for key functions, source code examples, and important utilities to allow professional engineers to build and debug C code-based solutions quickly and efficiently in one of the several supported integrated development environments (IDEs), including Keil, Mentor Embedded, IAR, and Code Composer Studio™ IDE.

Part Number	Description
DK-TM4C129X	TM4C129x Microcontroller Development Kit



▲ TM4C129x Development Kit block diagram

For more information visit [www.ti.com/tool/dk-tm4c129x](http://www.ti.com/tool/dk-tm4c129x)

The platform bar, Code Composer Studio and TivaWare are trademarks of Texas Instruments. All other trademarks are the property of their respective owners.

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>
DLP® Products	<a href="http://www.dlp.com">www.dlp.com</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>
Clocks and Timers	<a href="http://www.ti.com/clocks">www.ti.com/clocks</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>
RFID	<a href="http://www.ti-rfid.com">www.ti-rfid.com</a>
OMAP Applications Processors	<a href="http://www.ti.com/omap">www.ti.com/omap</a>
Wireless Connectivity	<a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a>

### Applications

Automotive and Transportation	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
Communications and Telecom	<a href="http://www.ti.com/communications">www.ti.com/communications</a>
Computers and Peripherals	<a href="http://www.ti.com/computers">www.ti.com/computers</a>
Consumer Electronics	<a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>
Energy and Lighting	<a href="http://www.ti.com/energy">www.ti.com/energy</a>
Industrial	<a href="http://www.ti.com/industrial">www.ti.com/industrial</a>
Medical	<a href="http://www.ti.com/medical">www.ti.com/medical</a>
Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
Space, Avionics and Defense	<a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a>
Video and Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)