

File:UCC3917

Date: 8/29/00

DV3917 BOM

Ref Des	Qty	Part Number	Description	MFG	Size	Source
U1	1	UCC3916D	IC, Positive Floating Hot Swap Power Manager	Texas Instruments	SOIC -16	
Q1	1	IRF530S	N-FET, 0.16 Ohm, 100V	International Rectifier	TO-263 Digi-Key	
Q2, Q6, Q9	3	FMMT593	Transistor, PNP, 100V	Zetex	SOT-23 Digi-Key	
Q3, Q4	2	FMMTA06	Transistor, NPN, 80V	Zetex	SOT-23 Digi-Key	
Q5, Q7	2	MMBT5089	Transistor, NPN, 25V	Motorola	SOT-23 Digi-Key	
Q8	1	BC846B	Transistor, NPN, 65V	Motorola/Phillips	SOT-23 Digi-Key	
D1, D2, D3	3	IMBD4148	Diode, 100V, 0.35W	Diodes Inc.	SOT-23 Digi-Key	
D4 (Not Used)	1	BZX84C4V3ZX	Diode, Zener, 4.3V, 0.35W	Zetex	SOT-23 Digi-Key	
D5 (Not Used)	1	BZX84C5V6	Diode, Zener, 5.6V, 0.3W	Zetex	SOT-23 Digi-Key	
R22	1	Std	Res, 0.05 Ohm, 1W, 2%	IRC	2512	
R15	1	Std	Res, 47 Ohm, 5%, 0.1W	Panasonic	805 Digi-Key	
R19	1	Std	Res, 2.0K, 1%, 0.1W	Panasonic	805 Digi-Key	
R14	1	Std	Res, 3.01K, 1%, 0.1W	Panasonic	805 Digi-Key	
R6, R7, R9, R10	4	Std	Res, 3.57K, 1%	Panasonic	805 Digi-Key	
R24	1	Std	Res, 4.7K, 5%, 1W	Panasonic	2512 Digi-Key	
R11	1	Std	Res, 5.6K, 5%, 1W	Panasonic	2512 Digi-Key	
R5, R8	2	Std	Res, 7.32K, 1%, 0.1W	Panasonic	805 Digi-Key	
R3	1	Std	Res, 15.4K, 1%, 0.1W	Panasonic	805 Digi-Key	
R1, R2	2	Std	Res, 34.8K, 1%, 0.1W	Panasonic	805 Digi-Key	
R4, R17, R18	3	Std	Res, 49.9K, 1%, 0.1W	Panasonic	805 Digi-Key	
R20	1	Std	Res, 150K, 1%, 0.1W	Panasonic	805 Digi-Key	
R12, R13, R23	3	Std	Res, 200K, 1%, 0.1W	Panasonic	805 Digi-Key	
R16, R21	2	Std	Res, 1Meg, 5%, 0.1W	Panasonic	805 Digi-Key	
C13, C14	2	Std	Cap, 0.01uF, 10%, 50V, X7R	Venkel	805	
C7-C9, C11	4	Std	Cap, 0.1uF, X7R, 25V, 10%	Samsung	805	
C2-C6	5	ECJ2YB1C224K	Cap, 0.22uF, X7R, 25V, 10%	Panasonic	805	
C1, C10	2	ECE-V2AA4R7P	Cap, Alum, 4.7uF, 100V	Panasonic	F-Case	
C12	1	TAJA106K006	Cap, Tant, 10uF, 6V, 10%	AVX	3216	

S1, S2, S3, S4	4 09-03201-02	Slide Switch, SPDT, Thru-hole	EAO Switch Corp	Newark
S6, S7	2 1101M2S3AQE2	Slide Switch, SPDT, Thru-hole, 6A @28V	C&K	
S5	1 219-4MST	Switch, DIP, 4-position, SMT	CTS	
P1-P3	3 22-03-2021	Header, 2-pin, 0.1" center	Molex	Digi-Key
TP1, TP2	2 22-03-2031	Header, 3-pin, 0.1" center	Molex	Digi-Key
J1, J2	2 1437671-1	Connector, Lever	AUGAT/RDI	Mouser
REF	1	PCB		

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments
Post Office Box 655303 Dallas, Texas 75265

Copyright © 2003, Texas Instruments Incorporated