

PMP30435 REV C Bill of Materials

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
C1, C4	2	15uF	EEU-EE2V150	Used in BOM report	CAP, [Technology], 15uF, 350V, +/-xx%, xxOhm ESR, [MountType]	Used in PnP output and some BOM reports
C2	1	2200pF	VJ1206Y222KXGAT5Z	Vishay-Vitramon	CAP, CERM, 2200 pF, 1000 V,+/- 10%, X7R, 1206	1206
C3	1	DNP	DNP	TDK	CAP, Film	26.5x10.5mm
C5	1	0.22uF	R474N322050A1K	TDK	CAP, Film, 0.22 uF, 440VAC,+/- 10%, TH	26.5x10.5mm
C6	1	180uF	16SVPF180M	Panasonic	CAP, Aluminum Polymer, 180 uF, 16 V,+/- 20%, 0.022 ohm, F61 SMD	F61
C7	1	470uF	EEHZK1E471P	Panasonic	CAP, Polymer Hybrid, 470 uF, 25 V,	10x10
C8, C11, C12, C14	4	DNP	Used in BOM report	Used in BOM report	CAP, CERM, xxxF, xxV, [TempCo], xx%, [PackageReference]	Used in PnP output and some BOM reports
C9	1	4.7uF	C3216X7R1H475K160AC	TDK	CAP, CERM, 4.7 uF, 50 V,+/- 10%, X7R, 1206	1206
C10	1	0.1uF	06035C104KAT2A	AVX	CAP, CERM, 0.1 uF, 50 V, +/- 10%, X7R, 0603	0603
C13	1	0.022uF	C0603C223K5RACTU	Kemet	CAP, CERM, 0.022 uF, 50 V,+/- 10%, X7R, 0603	0603
C15	1	0.033uF	06035C333JAT2A	AVX	CAP, CERM, 0.033 uF, 50 V,+/- 5%, X7R, 0603	0603
C16	1	1uF	GRM21BR71E105KA99L	MuRata	CAP, CERM, 1 uF, 25 V,+/- 10%, X7R, 0805	0805
C17, C18	2	4700pF	DE2E3KY472MB3BM02F	MuRata	CAP, CERM, 4700 pF, X1 250 VAC/Y2 300 VAC, +/- 20%, E, 10x5x13mm	10x5x13mm
C101	1	2200pF	GRM188R71H222KA01D	MuRata	CAP, CERM, 2200 pF, 50 V,+/- 10%, X7R, 0603	0603
D1	1	800V	MB8S-TP	Micro Commercial Component	Diode, Switching-Bridge, 800 V, 0.5 A, TO269AA	TO269AA
D2	1	100V	STPS8H100G-TR	STMicroelectronics	Diode, Schottky, 100 V, 8 A, DDPAK	DDPAK
D3	1	800V	US1K-13-F	Diodes Inc.	Diode, Fast Rectifier, 800 V, 1 A, SMA	SMA
D4	1	200V	ES1D-13-F	Diodes Inc.	Diode, Ultrafast, 200 V, 1 A, SMA	SMA
D5	1	30V	BAT54S-7-F	Diodes Inc.	Diode, Schottky, 30 V, 0.2 A, SOT-23	SOT-23
F1	1		37205000001	Littelfuse	Fuse, 0.5 A, 250VAC/VDC, TH	TR5 fuse 8.5mm DIA
L1	1	220uH	768772221	Würth Elektronik	Inductor, Unshielded Drum Core, Powdered Iron, 220 uH,	Dia 8x10mm
L2	1	3.3mH	744822233	Würth Elektronik	Coupled inductor, 3300uH, 1.5 A	14.7x13mm
Q1	1	800V	IPD80R4K5P7ATMA1	Infineon Technologies	MOSFET, N-CH, 800 V, DPAK	DPAK
R1, R3, R5, R6	4	1.5Meg	CRCW08051M50JNEA	Vishay-Dale	RES, 1.5 M, 5%, 0.125 W, 0805	0805
R2	1	47k	CRCW251247K0JNEG	Vishay-Dale	RES, 47 k, 5%, 1 W, AEC-Q200 Grade 0, 2512	2512
R4	1	0	CRCW12060000Z0EA	Vishay-Dale	RES, 0, 5%, 0.25 W, 1206	1206
R7	1	200	CRCW2512200RJNEG	Vishay-Dale	RES, 200, 5%, 1 W, AEC-Q200 Grade 0, 2512	2512
R8	1	33	CRCW080533R0JNEA	Vishay-Dale	RES, 33, 5%, 0.125 W, 0805	0805
R9	1	49.9	CRCW060349R9FKEA	Vishay-Dale	RES, 49.9, 1%, 0.1 W, 0603	0603
R10	1	121k	CRCW0603121KFKEA	Vishay-Dale	RES, 121 k, 1%, 0.1 W, 0603	0603
R11	1	0	CRCW06030000Z0EA	Vishay-Dale	RES, 0, 5%, 0.1 W, 0603	0603
R12	1	10.0	RC0805FR-0710RL	Yageo America	RES, 10.0, 1%, 0.125 W, 0805	0805
R13	1	49.9k	CRCW060349K9FKEA	Vishay-Dale	RES, 49.9 k, 1%, 0.1 W, 0603	0603
R14	1	1.33k	CRCW06031K33FKEA	Vishay-Dale	RES, 1.33 k, 1%, 0.1 W, 0603	0603
R15	1	29.4k	CRCW060329K4FKEA	Vishay-Dale	RES, 29.4 k, 1%, 0.1 W, 0603	0603
R16	1	3.01k	CRCW06033K01FKEA	Vishay-Dale	RES, 3.01 k, 1%, 0.1 W, 0603	0603
R17, R18, R22	3	DNP	Used in BOM report	Used in BOM report	RES, xxx ohm, x%, xW, [PackageReference]	Used in PnP output and some BOM reports
R19	1	1.20	ERJ-6RQF1R2V	Panasonic	RES, 1.20, 1%, 0.125 W, 0805	0805
R20	1	30.1k	CRCW060330K1FKEA	Vishay-Dale	RES, 30.1 k, 1%, 0.1 W, 0603	0603

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
R21	1	13.0k	CRCW060313K0FKEA	Vishay-Dale	RES, 13.0 k, 1%, 0.1 W, 0603	0603
R23	1	100k	CRCW0805100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.125 W, 0805	0805
R24	1	10.0k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, 0603	0603
T1	1	1.5mH	750370934	Würth Elektronik	Transformer, 1500 uH, TH	29.5x27mm
TP1, TP2, TP3, TP5	4		5000	Keystone	Test Point, Miniature, Red, TH	Red Miniature Testpoint
TP4, TP6	2		5001	Keystone	Test Point, Miniature, Black, TH	Black Miniature Testpoint
U1	1		UCC28740DR	Texas Instruments	Constant-Voltage, Constant-Current Flyback Controller Using Opto-Coupler Feedback, D0007A	D0007A
U2	1		FOD817A	Fairchild Semiconductor	Optocoupler, 5 kV, 80-160% CTR, TH	DIP, 4-Leads, Body 6.86x4.83mm, Pitch 2.54mm
U3	1		ATL431AIDBZR	Texas Instruments	2.5V Low Iq Adjustable Precision Shunt Regulator, DBZ0003A (SOT-23-3)	DBZ0003A

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2019, Texas Instruments Incorporated