

Temp Profile to Maintain Optimum FIT Performance

Russell Hoppenstein

1 Trademarks

All trademarks are the property of their respective owners.

2 Introduction

Temperatures within the product cases of modern telecommunication equipment are increasing due to higher IC integration, and denser channel configurations. Even with moderately elevated environmental temperatures, IC junction temperatures are rising to near-maximum limits. Naturally, operation at elevated junction temperatures must be controlled to maintain device reliability in the field.

3 Data Sheet Junction Temperature Limits

The data sheet provides a maximum operating junction temperature of 110°C. To prevent any undesired degradation in reliability, avoid continuously operating at this temperature over extended durations.

As denoted in [Equation 1](#), cumulative operating time between 105°C and 110°C must be less than one-third of the total operating time below 100°C.

$$\int_{T_j=105^{\circ}\text{C}}^{110^{\circ}\text{C}} t \, dT_j \leq \frac{1}{3} \times \int_{T_{j,\text{min}}}^{100^{\circ}\text{C}} t \, dT_j \quad (1)$$

With standard model assumptions, the operation temperature of the device may extend beyond 105°C if the duration is offset by operating below 100°C for at least three times that amount of time. In a discrete example, say the device operates at 110 degC for 20% of time. That time must be compensated for by operating at (or below) 100°C for at least 60% of the time. For the remaining time, the device operates between 100°C and 105°C.

[Figure 1](#) illustrates an example temp profile that satisfies the previously discussed restriction. The area under the temp profile curve from 105°C to 110°C (red) is equal to one-third of the area under the curve up to 100°C (blue).




Figure 1. Example Temperature Profile

4 Conclusion

The temp profile provided in this report is strictly for illustrative purposes. It is not intended to be a recommended profile. It is simply an example of an arbitrary temp profile that satisfies the criteria in [Equation 1](#). The model supports operating up to 110°C as long as sufficient time is spent operating at cooler temperatures (< 100°C). However, it is recommended to keep junction temperatures as low as possible to maintain the best reliability.

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2019, Texas Instruments Incorporated