

C2000™ Unique Device Number

Salvatore Pezzino, Joe Prushing, David Foley

ABSTRACT

This document discusses the 32-bit value which is stored in each device during manufacturing. It describes how this value can be used as a unique device identifier, as well as the limitations associated with using this value to generate an encryption key.

Contents

1	Introduction	2
2	Class-A Devices	2
	2.1 Limitations	2
3	Class-B Devices	3
	3.1 Limitations and Variability.....	3
4	Device Table	4

List of Tables

1	Unique ID Locations on C2000 Devices	4
---	--	---

Trademarks

C2000 is a trademark of Texas Instruments.
All other trademarks are the property of their respective owners.

1 Introduction

Many C2000™ devices contain a unique device number which can be used by an application for enhancing a security solution. This unique device number may be used in a variety of ways. The following are some examples in which the unique device number may be used.

- Protection against code cloning using periodic read back and compares
- Initialization vector (IV) for encryption or decryption of a program or data
- IV for authentication
- Device identification in communications (broadcasting)
- Seed for data integrity algorithms, for example, cyclic redundancy check (CRC)

The implementation of the unique device number has evolved as the C2000 technology and devices have advanced. There are two classes of devices which are distinguished as Class-A and Class-B for the following discussion.

Class-A devices:

- F280x
- F2802x
- F2803x
- F2805x
- F2806x
- F281x
- F2823x and F2833x

Class-B devices:

- F2807x
- F2837x
- F28004x

2 Class-A Devices

For Class-A devices, the device number is pseudo-unique. The term pseudo is meant to clearly communicate that TI does not guarantee the value will be unique for every device, but rather that it should generally be unique.

The 32-bit value provided can be considered as two, 16-bit words. For optimum uniqueness over time, all 32 bits should be used. If only 16 bits are required, TI recommends that the least significant word (LSW) and most significant word (MSW) be XOR'd together. If this cannot be done, then the LSW should be used because the MSW alone may not contain enough variability across material to meet the desired requirements. For more information, see [Section 2.1](#) and [Section 2.1.1](#).

2.1 Limitations

There are a few limitations and restrictions which must be communicated for a proper evaluation concerning whether this value will work for the intended purpose in the customer application.

2.1.1 Variability

The 32-bit value is not a pseudo randomly generated number, but is instead based on simple serialization algorithms. Devices manufactured near the same time may have the same or similar MSWs, but should typically have unique LSWs. Under typical situations, LSWs may repeat within a few hundred devices or a few thousand. By using the MSW and LSW together the probability that a device number is repeated is greatly reduced.

2.1.2 Static Bits

Some of the bits within the 32-bit value will generally have a fixed value of zero. Static bits reduce the possible values for the 32-bit number. There is one static bit in the MSW and four static bits in the LSW.

2.1.3 Long-Term Reliability

The 32-bit value is not guaranteed to remain consistent across all operating conditions for the full life of the device. If the value is used, it should be copied into an on-chip, nonvolatile location, such as the user one-time programmable (OTP) memory or flash.

2.1.4 Not Tested

Devices are not rejected during factory test based on the 32-bit value. The consequence is that multiple devices may be programmed with a common value, particularly all bits being zero or one, or some other nonstandard value.

3 Class-B Devices

Class-B devices have a different offering than Class-A devices. Class-B devices offer UID_REGS registers in the OTP for device identification. The UID_REGS registers consists of a 256-bit value that is made up of both pseudo-random and sequential parts. This value can be used as a seed for code encryption. The first 192 bits are pseudo-random, the next 32 bits are sequential, and the last 32 bits are a fletcher checksum value of the previous 224 bits.

The 32-bit sequential value is the UID_UNIQUE device identification register and is unique for all devices of a particular device family (for example, F2807x, F2837x, and so on). Due to this, the 256-bit value is also unique.

3.1 Limitations and Variability

There are a few limitations and restrictions which must be communicated for a proper evaluation concerning whether this value will work for the intended purpose in the customer application.

The 192-bit, pseudo-random value is not guaranteed to have a particular degree of entropy. Therefore, use of the pseudo-random value as a cryptographic key should be carefully considered against the threat level the application must protect against. Use in cryptography as an IV is acceptable, provided there is no requirement of entropy for the IV.

The 32-bit UID_UNIQUE value is not a randomly generated pseudo-number, but is instead based on simple serialization algorithms. Although the UID_UNIQUE value is unique to a unit within a particular series of devices, there will be instances where across device series two units will carry the same UID_UNIQUE number. If uniqueness across device series is required, the UID_UNIQUE value should be cross referenced with the PARTIDH value listed in the device data sheet.

4 Device Table

Table 1 lists the memory mapped address from where the MSW and LSW can be read for several device families.

Table 1. Unique ID Locations on C2000 Devices

Device Family	MSW Location	LSW Location
F24x and F240x	N/A	N/A
F280x	0x000809	0x000808
F2802x	0x000901	0x000900
F2803x	0x000901	0x000900
F2805x	0x3D7FDB	0x3D7FDA
F2806x	0x000901	0x000900
F281x	0x000809	0x000808
F2823x and F2833x	0x000901	0x000900
F2807x ⁽¹⁾	0x0703CD	0x0703CC
F2837x ⁽¹⁾	0x0703CD	0x0703CC
F28004x ⁽¹⁾	0x0703CD	0x0703CC

⁽¹⁾ See the device data sheet and technical reference manual for more information regarding this UID_UNIQUE register.

IMPORTANT NOTICE FOR TI DESIGN INFORMATION AND RESOURCES

Texas Instruments Incorporated ("TI") technical, application or other design advice, services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using any particular TI Resource in any way, you (individually or, if you are acting on behalf of a company, your company) agree to use it solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources.

You understand and agree that you remain responsible for using your independent analysis, evaluation and judgment in designing your applications and that you have full and exclusive responsibility to assure the safety of your applications and compliance of your applications (and of all TI products used in or for your applications) with all applicable regulations, laws and other applicable requirements. You represent that, with respect to your applications, you have all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. You agree that prior to using or distributing any applications that include TI products, you will thoroughly test such applications and the functionality of such TI products as used in such applications. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

You are authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING TI RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY YOU AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

You agree to fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of your non-compliance with the terms and provisions of this Notice.

This Notice applies to TI Resources. Additional terms apply to the use and purchase of certain types of materials, TI products and services. These include; without limitation, TI's standard terms for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>), [evaluation modules](#), and [samples](http://www.ti.com/sc/docs/sampterm.htm) (<http://www.ti.com/sc/docs/sampterm.htm>).

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2017, Texas Instruments Incorporated