

# Bill of Materials

TI DESIGNS

TIDM-NFC-RW

Item	Qty	Reference	Value	Part Description	Manufacturer	Manufacturer Part Number
1	0	ANT1	0.950uH			
2	5	C1 C3 C5 C7 C9	2.2uF		Kemet	C0603C225K8PACTU
3	5	C2 C4 C6 C8 C10	0.01uF		Panasonic - ECG	ECJ-1VB1E103K
4	3	C11 C12 C22	27pF		Panasonic - ECG	ECJ-1VC1H270J
5	2	C13 C14	1500pF		Panasonic - ECG	ECJ-1VB1H152K
6	2	C15 C16	1200pF		Panasonic - ECG	ECJ-1VB1H122K
7	2	C17 C20	680pF		Panasonic - ECG	ECJ-1VC1H681J
8	1	C18	10pF		Panasonic - ECG	ECJ-1VC1H100D
9	1	C19	220pF		Panasonic - ECG	ECJ-1VC1H221J
10	1	C21	100pF		Panasonic - ECG	ECJ-1VC1H101J
11	1	C23	68pF		Panasonic - ECG	GRM1885C2A680JA01D
12	1	C24	82pF	CAP CER 82PF 100V 5% C0G 0603	Panasonic - ECG	GRM1885C2A820JA01D
13	2	C25 C26	10uF	CAP CER 10UF 6.3V X5R 0603	Taiyo Yuden	JMK107BJ106MA-T
14	1	J1	COAXIAL	RECEPTACLE_CON_COAXIAL_UFL-R-SMT	Hirose	U.FL-R-SMT-1
15	1	L1	150nH		Coilcraft	1008CS-151XJLB
16	1	L2	330nH		Coilcraft	1008CS-331XJLB
17	1	L4	4.7uH	Passive_4.7uH_IND_SM_EPL3015	Coilcraft, Inc.	EPL3015-472MLB
18	1	OSC1	13.560MHz	SMD XTAL 13.560MHz I30 series	ITT Company	1300225-13.560MHz
19	2	P1 P2	SFM-110-02-L-D-A	SMT-20pin-30Au 50ni-Double Row-Alignment pin	SAMTEC	SFM-110-02-L-D-A
20	4	R1 R2 R3 R4	10k		Panasonic - ERJ	ERJ-3GEYJ103V
21	1	R5	0		Panasonic - ERJ	ERJ-3GEYJ0R00V
22	1	R6	680		Rohm	ESR03EZPJ681
23	0	TP1 TP2 TP3 TP4 TP9 TP11	TESTVIA_018			
24	2	TP5 TP12	Black	TEST POINT .025" SQR POST HDR BLACK	Components Corporation	TP-105-01-00
25	0	TP6 TP7 TP8	TESTPAD_018			
26	1	TP10	Gray	TEST POINT .025" SQR POST HDR GRAY	Components Corporation	TP-105-01-08

Item	Qty	Reference	Value	Part Description	Manufacturer	Manufacturer Part Number
27	1	TP13	Blue	TEST POINT .025" SQR POST HDR BLUE	Components Corporation	TP-105-01-06
28	1	TP14	Green	TEST POINT .025" SQR POST HDR GREEN	Components Corporation	TP-105-01-05
29	1	TP15	Brown	TEST POINT .025" SQR POST HDR BROWN	Components Corporation	TP-105-01-01
30	1	U1	TRF7970ARHB	IC RFID/NFC AFE 13.56MHZ 32QFN	Texas Instruments	TRF7970ARHB
31	1	U2	TPS61222DCKT	+3VDC to +5VDC boost converter	Texas Instruments	TPS61222DCKT

## IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Buyers") who are developing systems that incorporate TI semiconductor products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products.

TI reference designs have been created using standard laboratory conditions and engineering practices. **TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.** TI may make corrections, enhancements, improvements and other changes to its reference designs.

Buyers are authorized to use TI reference designs with the TI component(s) identified in each particular reference design and to modify the reference design in the development of their end products. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS ARE PROVIDED "AS IS". TI MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. TI DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO TI REFERENCE DESIGNS OR USE THEREOF. TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY BUYERS AGAINST ANY THIRD PARTY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON A COMBINATION OF COMPONENTS PROVIDED IN A TI REFERENCE DESIGN. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, SPECIAL, INCIDENTAL, CONSEQUENTIAL OR INDIRECT DAMAGES, HOWEVER CAUSED, ON ANY THEORY OF LIABILITY AND WHETHER OR NOT TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, ARISING IN ANY WAY OUT OF TI REFERENCE DESIGNS OR BUYER'S USE OF TI REFERENCE DESIGNS.

TI reserves the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques for TI components are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

Reproduction of significant portions of TI information in TI data books, data sheets or reference designs is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards that anticipate dangerous failures, monitor failures and their consequences, lessen the likelihood of dangerous failures and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in Buyer's safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed an agreement specifically governing such use.

Only those TI components that TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components that have **not** been so designated is solely at Buyer's risk, and Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.