

AAC Low Complexity Encoder (v1.20) on C64x+

FEATURES

- eXpressDSP™ Digital Media (XDM 1.0 IAUDENC1) compliant
- 16-bit and 32-bit input PCM samples supported. In case of 32-bit PCM, it considers the most significant 16-bits as internal inputs
- Constant Bit Rate (CBR) encoding and Variable Bit Rate (VBR) encoding supported
- 8 kHz to 96 kHz input sampling frequencies supported
- Only AAC-LC output format supported
- Mono, stereo, and dual mono input file supported
- Bit-rates based on sampling frequency and number of channels supported
- Audio Data Interchange Format (ADIF), Audio Data Transport Stream (ADTS), and raw output format supported
- ISO/IEC 14496-3 (MPEG4 AAC) and ISO/IEC 13818-7 (MPEG 2-AAC) standards compliant
- Validated on DM644x EVM with Code

Composer Studio version 3.2.37.12 and Code Generation Tools version 6.0.8

- This codec can be used on any of TI's C64x+ based platforms such as DM644x, DM648, DM643x, DM646x, OMAP35xx and their derivatives

DESCRIPTION

AAC is one of the most popular audio compression standards across wide spectrum of application ranging from portable player, cell phones, music systems, internet, and so on. AAC Encoder is validated on DM644x EVM with Code Composer Studio version 3.2.37.12 and Code Generation Tools version 6.0.8.

PRODUCT PREVIEW



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

eXpressDSP is a trademark of Texas Instruments.
All other trademarks are the property of their respective owners.

Performance Summary

This section describes the performance of AAC Low Complexity Encoder on DM644x EVM.

Table 1. Configuration Table

CONFIGURATION	ID
AAC_LC	AACLC_ENC_001

Table 2. Cycles Information - Profiled on DM644x EVM with Code Generation Tools Version 6.0.8

CONFIGURATION ID	PERFORMANCE STATISTICS (MEGA CYCLES PER SECOND) ⁽¹⁾⁽²⁾		
	TEST DESCRIPTION	AVERAGE	PEAK ⁽³⁾
AACLC_ENC_001	44 kHz – 128 kbps	30.12	37.5

(1) Profiling is done by thrashing cache after encoding each frame of AAC.

(2) Average and peak MCPS measurements can vary by +/-5%.

(3) Measured with program memory, stack, and I/O buffers in external memory and with cache configuration 32K-bytes L1P cache, 16K-bytes L1D cache, and 64K-bytes L2 cache.

Table 3. Memory Statistics - Generated with Code Generation Tools Version 6.0.8

CONFIGURATION ID	MEMORY STATISTICS ⁽¹⁾				TOTAL
	PROGRAM MEMORY	DATA MEMORY			
		INTERNAL	EXTERNAL	STACK	
AACLC_ENC_001	116.4	Not used	85.9	5.5	207.8

(1) All memory requirements are expressed in kilobytes (1K-byte = 1024 bytes).

Table 4. Internal Data Memory Split-Up

CONFIGURATION ID	DATA MEMORY - INTERNAL ⁽¹⁾		
	SHARED		INSTANCE ⁽²⁾
	CONSTANTS	SCRATCH	
AACLC_ENC_001	Not used	Not used	Not used

(1) All memory requirements are expressed in kilobytes.

(2) Does not include I/O buffers.

Table 5. External Data Memory Split-Up

CONFIGURATION ID	DATA MEMORY - EXTERNAL ⁽¹⁾		
	SHARED		INSTANCE ⁽²⁾
	CONSTANTS	SCRATCH	
AACLC_ENC_001	22.6	8.5	54.8

(1) All memory requirements are expressed in kilobytes.

(2) Does not include I/O buffers.

Notes

- I/O buffers:
 - Input buffer size = 1024 samples per channel
 - Output buffer size = 1536 bytes
- Total data memory for N non pre-emptive instances = Constants + Run-time Tables + Scratch + N * (Instance + I/O buffers + Stack)
- Total data memory for N pre-emptive instances = Constants + Run-time Tables + N * (Instance + I/O buffers + Stack + Scratch)

References

- ISO/IEC IS 14496-3 Information Technology -- Coding of Moving Pictures and Associated Audio for Digital Storage Media at up to about 1.5 Mbps -- Part 3: Audio
- ISO/IEC IS 13818-7 Information Technology -- Generic Coding of Moving Pictures and Associated Audio Information -- Part 7 Advanced Audio Coding
- *AAC Low Complexity Encoder on C64x+ User's Guide* (literature number:SPRUEI4A)

Glossary

TERM	DESCRIPTION
Constants	Elements that go into const memory section
Scratch	Memory space that can be reused across different instances of the algorithm
Shared	Sum of Constants and Scratch
Instance	Persistent-memory that contains persistent information - allocated for each instance of the algorithm

Acronyms

ACRONYM	DESCRIPTION
AAC	Advanced Audio Coding
ADIF	Audio Data Interchange Format
ADTS	Audio Data Transport Stream
CBR	Constant Bit-rate
EVM	Evaluation Module
Kbps	Kilo bits per second
KHz	Kilo Hertz
LC	Low Complexity
MPEG	Moving Picture Experts Group
PCM	Pulse Code Modulation
VBR	Variable Bit-rate
XDM	eXpressDSP Digital Media

Revision History

This datasheet revision history highlights the changes made to the SPRS364 codec specific datasheet to make it SPRS364A.

Table 6. Revision History for AAC Low Complexity Encoder (v1.20) on C64x+

SECTION	ADDITIONS/MODIFICATIONS/DELETIONS
Section 1	Supported Features: <ul style="list-style-type: none"> • Removed XDIAS compliance • Updated XDM version • Added list of platforms supported by this codec
Table 2	Cycles Information: <ul style="list-style-type: none"> • Modified average and peak values • Added note explaining variation of average and peak MCPS measurements
Table 3	Memory Statistics: <ul style="list-style-type: none"> • Modified program and external memory
Table 5	External Data Memory Split-Up: <ul style="list-style-type: none"> • Modified constant value

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
RF/IF and ZigBee® Solutions	www.ti.com/lprf

Applications

Audio	www.ti.com/audio
Automotive	www.ti.com/automotive
Broadband	www.ti.com/broadband
Digital Control	www.ti.com/digitalcontrol
Medical	www.ti.com/medical
Military	www.ti.com/military
Optical Networking	www.ti.com/opticalnetwork
Security	www.ti.com/security
Telephony	www.ti.com/telephony
Video & Imaging	www.ti.com/video
Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright 2008, Texas Instruments Incorporated