

TI-RSLK **MAX**

Texas Instruments Robotics System Learning Kit



Module 5

Activity: Building the robot



Activity: Battery and Voltage Regulation

Battery	Voltage (V)	Storage (mAh)	Type
Alkaline	$5 \times 1.5 = 7.5$	2000	Primary
Lithium	$5 \times 1.5 = 7.5$	3000	Primary
NiCad	$6 \times 1.2 = 7.2$	1200	Secondary
NiMH	$6 \times 1.2 = 7.2$	1800	Secondary
Li-ion	$2 \times 3.6 = 7.2$	1900	Secondary

Table 1. Storage capacities of AA-sizes batteries used to power a robot at about 7V.

Question 1

Assume the robot requires 1 amp to operate. How long will each battery type listed in Table 1 last?

Question 2

Assume all batteries in Table 1 have the same weight. If cost were no object, which battery type would you choose and why?

Question 3


A battery can hold 400 mA-hr. The embedded system runs with 1 mA in active mode and 1 μ A in sleep mode. If the system runs 99.99% of the time in sleep mode, how long will the battery last?

Question 4

What is the difference between a primary and secondary battery?

Question 5

What happens if the input voltage to the 7805 is 6V? What happens if the input voltage to the 7805 is 16V? What happens if the input voltage to the 7805 is 160V?



Question 6

What do the diode and inductor do in the LM2596 regulator circuit?

Question 7

Using the family of LM78xx regulators, build a power circuit for a +12V embedded system. What battery input voltage do you need?

Question 8

Using the family of LM2596 regulators, build a power circuit for a +3.3V embedded system. What battery input voltage do you need?

ti.com/rslk

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2019, Texas Instruments Incorporated