

# Application Report

## Migration Guide from CC2640R2F to CC2640R2L



### ABSTRACT

This application report describes the hardware changes to be made when moving from the CC2640R2F to the CC2640R2L SimpleLink™ wireless MCU.

---

### Table of Contents

1 Differences Between CC2640R2F and CC2640R2L.....	2
2 PCB Design and Layout.....	2
3 RF Compliance and Certification.....	2
4 Summary.....	3
5 References.....	3
6 Revision History.....	3

### Trademarks

All other trademarks are the property of their respective owners.

## 1 Differences Between CC2640R2F and CC2640R2L

CC2640R2L is the latest generation of ultra-low power wireless MCUs for 2.4 GHz operation from Texas Instruments. The CC2640R2L supports Bluetooth® low energy as well as proprietary RF.

Please see the table below that highlights the major differences between the two devices:

**Table 1-1. Differences Between CC2640R2F and CC2640R2L**

Features	CC2640R2F	CC2640R2L
<b>Peripherals</b>		
Sensor Controller Engine	Yes	No
Comparators	Yes	No
Constant Current Source	Yes	No
<b>Packages</b>		
	RGZ (7-mm x 7-mm)	RGZ (7-mm x 7-mm)
	RHB (5-mm x 5-mm)	RHB (5-mm x 5-mm)
	RSM (4-mm x 4-mm)	
	YFV (2.7-mm x 2.7-mm)	
<b>Standby Current</b>		
No Cache RCOSC_LF	1.1 uA	1.5 uA
No Cache XOSC_LF	1.3 uA	1.7 uA
With Cache RCOSC_LF	2.8 uA	6.2 uA
With Cache XOSC_LF	3.0 uA	6.2 uA
<b>BLE 2 Mbps PHY</b>		
RF Sensitivity	-91 dBm	-90 dBm

## 2 PCB Design and Layout

From a package point of view, the corresponding packages of both devices are pin to pin compatible and a PCB design made for CC2640R2F can be reused for the CC2640R2L.

Also, the CC2640R2 Launchpad supports both CC2640R2F and CC2640R2L devices in 7x7 packages.

## 3 RF Compliance and Certification

Although CC2640R2L is similar to CC2640R2F from an RF and pin compatibility perspective, a new regulatory compliance certificate may be required if a PCB design is reused in production for the other device. This needs to be verified with an accredited test house, which needs to be made aware of the update to the BOM.

To obtain a waiver (if applicable) for drop in replacement, the customer may have to file an amendment to the regulatory authority notifying them of the differences between the two devices showing no RF performance impact.

If RF performance is impacted, a recertification may be required depending on the rules and regulation of the governing authority.

RF certification of the customer's application and end equipment is the customer's responsibility. The customer is solely responsible for the design, validation, and testing of its applications as well as for compliance with all legal and regulatory requirements concerning its applications. Industry best practices generally require that the customer and their test house conduct qualification tests on actual applications taking into account possible environmental and other conditions that the customer's application may encounter. TI recommends consulting with the accredited certification test house for further regulatory requirements.

## 4 Summary

A PCB designed for the CC2640R2F can be reused for the CC2640R2L, as the devices (in the 7x7 and 5x5 QFN package) are pin to pin compatible. However, a recertification may be required if the RF performance measured is different as a result of the replacement.

## 5 References

1. Texas Instruments: [CC2640R2L Data Sheet](#)
2. Texas Instruments: [CC13x0, CC26x0 SimpleLink™ Wireless MCU Technical Reference Manual](#)
3. Texas Instruments: [CC2640R2 LaunchPad Design Files](#)

## 6 Revision History

DATE	REVISION	NOTES
June 2020	*	Initial Release

## IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale ([www.ti.com/legal/termsofsale.html](http://www.ti.com/legal/termsofsale.html)) or other applicable terms available either on [ti.com](http://ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2020, Texas Instruments Incorporated