

Item	Designator	Description	Manufacturer	PartNumber	Quantity
1	C1	DLP	DLP	DLP	0
2	C2	CAP, Film, 0.047uF, 310Vac, +/-10%, TH	Vishay	BFC233920473	1
3	C3	CAP, CERM, 10uF, 50V, +/-10%, X7R, 1210	MuRata	GRM32ER71H106KA12L	1
4	C4	CAP, CERM, 2.2uF, 16V, +/-10%, X7R, 0805	MuRata	GRM21BR71C225KA12L	1
5	C5	DLP	DLP	DLP	0
6	C6, C7	CAP, Film, 0.1uF, 630V, +/-5%, TH	Panasonic	ECW-F6104JL	2
7	C8	CAP, CERM, 68pF, 630V, 5%, U2J, 1206	MuRata	GRM31A7U2J680JW31D	1
8	C9	CAP AL, 100uF, 100V, +/-20%, ?ohm, 10x25mm, TH	Nichicon	UHE2A101MPD	1
9	C10	CAP, CERM, 2.2uF, 100V, +/-10%, X7R, 1210	MuRata	GRM32ER72A225KA35L	1
10	C11	CAP, CERM, 0.1uF, 50V, +/-10%, X7R, 0603	MuRata	GRM188R71H104KA93D	1
11	D1	Diode, Switching-Bridge, 600V, 0.8A, MiniDIP	Diodes Inc.	RH06-T	1
12	D2	Diode 300V, 0.2A, 50nS, SOD-123	Diodes Inc.	BAV3004W-7-F	1
13	D3	Diode, Ultrafast, 75V, 0.15A, SOD-523F	Comchip	CDSU4148	1
14	D4	DIODE TVS 400V 400W UNI 5% SMA	Littelfuse	SMAJ400A	1
15	D5	Diode, Ultrafast, 600V, 3A, SMB	ST	STTH3R06	1
16	F1	Fuse - Rectangular, Slo-Blo, 1.6A, 250V	Multicomp	MST 1.6A 250 V	1
17	L1, L5	DLP	DLP	DLP	0
18	L2, L3	Inductor, Drum Ferrite 680uH 0.32A, 1.5 ohm, TH	TDK	TSL0808RA-681KR32-PF	2
19	L4	Inductor, Drum Ferrite 1mH 0.26A, 2.2ohm, TH	TDK	TSL0808RA-102KR26-PF	1
20	Q1	BJT NPN 45V, 0.5A, hfe=160-400, SOT-23	NXP	BC817-25	1
21	Q2	MOSFET N-CH, 5A, 600V, IPAK	ST	STU7NM60N	1
22	R1, R2, R17, R21, R22	RES, 0 ohm, 5%, 0.25W, 1206	Vishay-Dale	CRCW12060000Z0EA	5
23	R3, R4, R10	RES, 28.0k ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW120628K0FKEA	3
24	R5, R6, R7	RES, 100k ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW1206100KFKEA	3
25	R8	RES, 10.0 ohm, 1%, 0.125W, 0805	Vishay-Dale	CRCW080510R0FKEA	1
26	R9	RES, 0 ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW06030000Z0EA	1
27	R11	RES, 66.5k ohm, 1%, 0.125W, 0805	Vishay-Dale	CRCW080566K5FKEA	1
28	R12	RES, 11.0k ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW060311K0FKEA	1
29	R13	RES, 4.87k ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW06034K87FKEA	1
30	R14	RES, 5.23k ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW06035K23FKEA	1
31	R15	RES, 200k ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW1206200KFKEA	1
32	R16	DLP	DLP	DLP	0
33	R18	RES, 0.5 ohm, 1%, 0.5W, 1206	Stackpole Electronics Inc	CSR1206FKR500	1
34	R19	DLP	DLP	DLP	0
35	R20	RES, 750k ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW1206750KFKEA	1
36	T1	Transformer ER25	Würth Midcom	750341463	1
37	U1	Off-Line Primary Side Sensing Controller with PFC	Texas Instruments	TPS92310	1
38	VDR1	VARISTOR 275V RMS 7MM RADIAL	EPCOS	S07K275E2	1

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components which meet ISO/TS16949 requirements, mainly for automotive use. Components which have not been so designated are neither designed nor intended for automotive use; and TI will not be responsible for any failure of such components to meet such requirements.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com