

PMP20122 REV B Bill of Materials

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
C1	1	10uF	UVR1V100MDD1TA	Nichicon	CAP, AL, 10uF, 35V, +/-20%, TH	CAPPR2-5x11
C2	1	22pF	06035A220JAT2A	AVX	CAP, CERM, 22pF, 50V, +/-5%, C0G/NP0, 0603	0603
C3	1	6.8uF	400AX6R8M8x11	Rubycon	CAP, AL, 6.8uF, 400V, +/-20%, TH	8x11
C4, C5	2	15uF	EEU-ED2G150	Panasonic	CAP, AL, 15 uF, 400 V, +/- 20%, TH	D12.5xL20mm
C6	1	680uF	16ZL680MEFC10X16	Rubycon	CAP, AL, 680 uF, 16 V, +/- 20%, 0.038 ohm, TH	10x16mm
C7	1	1uF	08055C105KAT2A	AVX	CAP, CERM, 1uF, 50V, +/-10%, X7R, 0805	0805
D1	1	100V	1N4148W-7-F	Diodes Inc.	Diode, Ultrafast, 100V, 0.15A, SOD-123	SOD-123
D2	1	600V	ES1J-TP	Diodes Inc.	DIODE FAST REC 600V 1A DO214AC	SMA
D3	1	600V	RH06-T	Diodes Inc.	Diode, Switching-Bridge, 600V, 0.5A, MiniDIP	MiniDIP
D4	1	600V	ES3J	Fairchild Semiconductor	Diode, Fast Rectifier, 600 V, 3 A, SMC	SMC
L1	1	1mH	7447462102	Würth Elektronik eiSos	Inductor, Unshielded Drum Core, Ferrite, 1mH, 0.25A, 4.38 ohm, TH	D6 x 8.5mm
L2	1	47uH	SLF12575T-470M2R7-PF	TDK	Inductor, Shielded, Ferrite, 47 uH, 3 A, 0.0528 ohm, SMD	Inductor, 12.5x7.5x12.5mm
Q1	1	600V	STD3NK60ZT4	ST Microelectronics	MOSFET N-CH 600V 2.4A DPAK	DPAK
R1	1	37.4k	CRCW060337K4FKEA	Vishay-Dale	RES, 37.4 k, 1%, 0.1 W, 0603	0603
R2	1	432k	CRCW1206432KFKEA	Vishay-Dale	RES, 432k ohm, 1%, 0.25W, 1206	1206
R3	1	18.7k	CRCW060318K7FKEA	Vishay-Dale	RES, 18.7k ohm, 1%, 0.1W, 0603	0603
R4	1	301	CRCW0603301RFKEA	Vishay-Dale	RES, 301 ohm, 1%, 0.1W, 0603	0603
R5	1	0.51	CRM0805-FX-R510ELF	Bourns	RES, 0.51, 1%, 0.25 W, 0805	0805
R6	1	0.68	ERJ-6RQFR68V	Panasonic	RES, 0.68, 1%, 0.125 W, 0805	0805
R7, R8	2	5.1k	CRCW12065K10JNEA	Vishay-Dale	RES, 5.1k ohm, 5%, 0.25W, 1206	1206
RF1	1	4.7	PNP300JR-73-4R7	Yageo America	RES, 4.7, 5%, 3 W, 3W Axial resistor	3W Axial resistor
TP1, TP2	2	Red	5000	Keystone	Test Point, Miniature, Red, TH	Red Miniature Testpoint
TP3, TP4	2	Black	5001	Keystone	Test Point, TH, Miniature, Black	Keystone5001
U1	1		UCC28710D	Texas Instruments	Constant-Voltage, Constant-Current Controller With Primary-Side Regulation, D0007A	D0007A

IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Designer(s)") who are developing systems that incorporate TI products. TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.

TI's provision of reference designs and any other technical, applications or design advice, quality characterization, reliability data or other information or services does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such reference designs or other items.

TI reserves the right to make corrections, enhancements, improvements and other changes to its reference designs and other items.

Designer understands and agrees that Designer remains responsible for using its independent analysis, evaluation and judgment in designing Designer's systems and products, and has full and exclusive responsibility to assure the safety of its products and compliance of its products (and of all TI products used in or for such Designer's products) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to its applications, it has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any systems that include TI products, Designer will thoroughly test such systems and the functionality of such TI products as used in such systems. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

Designers are authorized to use, copy and modify any individual TI reference design only in connection with the development of end products that include the TI product(s) identified in that reference design. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of the reference design or other items described above may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS AND OTHER ITEMS DESCRIBED ABOVE ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNERS AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS AS DESCRIBED IN A TI REFERENCE DESIGN OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

TI's standard terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products. Additional terms may apply to the use or sale of other types of TI products and services.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2016, Texas Instruments Incorporated