

PMP30763 REV c Bill of Materials

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
IPCB1	1		PMP30763	Any	Printed Circuit Board	
C1	1	470uF	LGU2F471MELA	Nichicon	CAP ALUM 470UF 20% 315V SNAP	25x52mm
C2, C3	2	0.068uF	B32642B6683J	EPCOS (TDK)	CAP FILM 0.047UF 10% 630VDC RAD	18x8mm
C4, C5, C61	3	0.33uF	ECW-FE2W334K	Panasonic Electronic Compon	0.33uF Film Capacitor 450V Polypropylene (PP), Metallized Radial	13x12x6mm
C6, C8, C11, C47, C49	5	2200pF	AY2222M35Y5US63L7	Vishay-Bccomponents	CAP, CERM, 2200 pF, 300 V, +/- 20%, Y5U, AEC-Q200 Grade 1, D9.5xT5mm	D9.5xT5mm
C7, C65	2	0.01uF	VJ1210Y103KXEAT5Z	Vishay-Vitramon	CAP, CERM, 0.01 uF, 500 V, +/- 10%, X7R, 1210	1210
C9, C10	2	0.33uF	B32922C3334K	TDK	CAP, Film, 0.33 uF, 630 V, +/- 10%, TH	B32922 14.5mm
C12, C13, C14, C76	4	680uF	EEU-FS1H681B	Panasonic	CAP, AL, 680 uF, 50 V, +/- 20%, TH	D12.5xL25mm
C15, C30, C55, C57	4	1uF	GRM188R71E105KA12D	MuRata	CAP, CERM, 1 uF, 25 V, +/- 10%, X7R, 0603	603
C16, C27, C28, C32, C52, C63	6	0.1uF	C1608X7R1H104K080AA	TDK	CAP, CERM, 0.1 uF, 50 V, +/- 10%, X7R, 0603	603
C17, C34	2	0.01uF	GRM188R71C103KA01D	MuRata	CAP, CERM, 0.01 uF, 16 V, +/- 10%, X7R, 0603	603
C18	1	100pF	8.85012E+11	Würth Electronics Inc.	CAP CER 100PF 16V C0G/NP0 0603	603
C19	1	3.3pF	08055A3R3CAT2A	AVX	CAP, CERM, 3.3 pF, 50 V, +/- 8%, C0G/NP0, 0805	805
C20, C50	2	10pF	06035A100JAT2A	AVX	CAP, CERM, 10 pF, 50 V, +/- 5%, C0G/NP0, 0603	603
C21	1	1200pF	GRM1885C1H122JA01D	MuRata	CAP, CERM, 1200 pF, 50 V, +/- 5%, C0G/NP0, 0603	603
C22	1	8200pF	GRM188R71H822KA01D	MuRata	CAP, CERM, 8200 pF, 50 V, +/- 10%, X7R, 0603	603
C23, C59	2	2.2uF	08053C225KAT2A	AVX	CAP, CERM, 2.2 uF, 25 V, +/- 10%, X7R, 0805	805
C24, C25	2	33pF	C0603C330J5GACTU	Kemet	CAP, CERM, 33 pF, 50 V, +/- 5%, C0G/NP0, 0603	603
C26	1	0.1uF	C0805C104K1RACTU	Kemet	CAP, CERM, 0.1 uF, 100 V, +/- 10%, X7R, 0805	805
C29	1	1000pF	C1608X7R1H102K	TDK	CAP, CERM, 1000 pF, 50 V, +/- 10%, X7R, 0603	603
C31, C64	2	0.47uF	C1608X7R1H474K080AC	TDK	CAP, CERM, 0.47 uF, 50 V, +/- 10%, X7R, 0603	603
C33	1	470pF	GRM1885C1H471JA01D	MuRata	CAP, CERM, 470 pF, 50 V, +/- 5%, C0G/NP0, 0603	603
C35, C56	2	4.7uF	GRM188R61E475KE11D	MuRata	CAP, CERM, 4.7 uF, 25 V, +/- 10%, X5R, 0603	603
C36	1	0.68uF	08053D684KAT2A	AVX	CAP, CERM, 0.68 uF, 25 V, +/- 10%, X5R, 0805	805
C37, R37	2	DNP	DNP	DNP	DNP	603
C38	1	0.22uF	GRM188R71H224KAC4D	MuRata	CAP, CERM, 0.22 uF, 50 V, +/- 10%, X7R, 0603	603
C39	1	150pF	GRM31A7U3A151JW31D	MuRata	CAP, CERM, 150 pF, 1000 V, +/- 5%, U2J, 1206	1206
C40	1	82pF	GRM31A7U3A820JW31D	MuRata	CAP CER 82PF 1KV U2J 1206	1206
C41	1	1000pF	C1608X7R2A102K080AA	TDK	CAP, CERM, 1000 pF, 100 V, +/- 10%, X7R, 0603	603
C42	1	0.047uF	06033C473JAT2A	AVX	CAP, CERM, 0.047 uF, 25 V, +/- 5%, X7R, 0603	603
C43	1	680pF	GRM188R71H681KA01D	MuRata	CAP, CERM, 680 pF, 50 V, +/- 10%, X7R, 0603	603
C44, C45	2	330pF	12061A331JAT2A	AVX	CAP, CERM, 330 pF, 100 V, +/- 5%, C0G/NP0, 1206	1206
C46, C48	2	1uF	C0805C105K3RACTU	Kemet	CAP, CERM, 1 uF, 25 V, +/- 10%, X7R, 0805	805
C51	1	1uF	GRM319R61E105KC36D	MuRata	CAP, CERM, 1 uF, 25 V, +/- 10%, X5R, 1206	1206
C53, C54	2	2.2uF	GRM188R6YA225KA12D	MuRata	CAP, CERM, 2.2 uF, 35 V, +/- 10%, X5R, 0603	603
C58, C62	2	100pF	06035A101JAT2A	AVX	CAP, CERM, 100 pF, 50 V, +/- 5%, C0G/NP0, 0603	603
C60	1	1000uF	EEU-FS1V102LB	Panasonic	1000uF 35V Aluminum Electrolytic Capacitors Radial, Can 10000 Hrs @ 105°C	
C67, C68, C72, C73	4	4.7uF	C3225X7S2A475K200AE	TDK	CAP, CERM, 4.7 uF, 100 V, +/- 10%, X7S, 1210	1210
C100, C101	2	100pF	GRM21A5C2E101JW01D	MuRata	CAP, CERM, 100 pF, 250 V, +/- 5%, C0G/NP0, 0805	805
D1, D5	2	MUR860G	MUR860G	ON Semiconductor	Diode, Ultrafast, 600 V, 8 A, TH	TO-220AC

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
D2, D6, D12, D13, D15	5	BAT54HT1G	BAT54HT1G	ON Semiconductor	Diode, Schottky, 30 V, 0.2 A, SOD-323	SOD-323
D3	1	GBU2510-G	GBU2510-G	Comchip Technology	RECT BRIDGE GPP 1000V 25A GBU	GBU
D4	1	15V	BZX384-C15,115	NXP Semiconductor	Diode, Zener, 15 V, 300 mW, SOD-323	SOD-323
D7, D8	2	SD103BW-7-F	SD103BW-7-F	Diodes Inc.	Diode, Schottky, 30 V, 0.35 A, SOD-123	SOD-123
D9, D10	2	RS1MB-13-F	RS1MB-13-F	Diodes Inc.	Diode, P-N, 1000 V, 1 A, SMB	SMB
D11	1	PMEG6010CEH,115	PMEG6010CEH,115	Nexperia	Diode, Schottky, 60 V, 1 A, SOD-123F	SOD-123F
D14	1	BAS20HT1G	BAS20HT1G	ON Semiconductor	Diode, Switching, 200 V, 0.2 A, AEC-Q101, SOD-323	SOD-323
D18	1	US1J-13-F	US1J-13-F	Diodes Inc.	Diode, Ultrafast, 600 V, 1 A, SMA	SMA
D20	1	LM4040D50	LM4040D50QDBZRG4	Texas Instruments	Precision Micropower Shunt Voltage Reference, 1% accuracy, 5 V, 15 ppm / degC, 15 mA, -40 to 125 degC, 3-pin SOT-23 (DBZ), Green (RoHS & no Sb/Br)	DBZ0003A
D100	1	S3J-E3/57T	S3J-E3/57T	Vishay-Semiconductor	Diode, Switching, 600 V, 3 A, SMC	SMC
F1	1	10A	3832100000	LITTELFUSE INC	FUSE, BOARD MOUNT, 10 A, 300 V, TH-2P	
H1, H2, H3, H4, H5, H6	6		SJ-5303 (CLEAR)	3M	Bumpon, Hemisphere, 0.44 X 0.20, Clear	Transparent Bumpon
H7	1	7C/W	V6560Y	Assman WSW	Heat Sink TO-220	Heat Sink TO-220
H8, H9, H10, H11	4		3114	Keystone	Flat Washer, #2 Nylon	
J1	1		61300111121	Würth Elektronik	Header, 2.54 mm, 1x1, Gold, TH	Header, 2.54 mm, 1x1, TH
J2	1		800-10-002-10-001000	Mill-Max	Header, 100mil, 2x1, TH	Header, 2x1, 100mil, TH
J3	1		ED120/3DS	On-Shore Technology	Terminal Block, 5.08 mm, 3x1, Brass, TH	3x1 5.08 mm Terminal Block
J4	1		22284033	Molex	Header, 2.54mm, 3x1, Tin, TH	Header, 2.54mm, 3x1, TH
J5	1		22284023	Molex	Header, 2.54mm, 2x1, Tin, TH	Header, 2.54mm, 2x1, TH
L1, L6	2	150µH	750318973r00	Würth Electronics	INDUCTOR	PTH_30MM35_29MM2
L2	1	150uH	7447076	Würth Elektronik	Inductor, Toroid, Powdered Iron, 150 uH, 5 A, 0.045 ohm, TH	D27.5xT13mm
L3, L5	2	1mH	7448031501	Würth Elektronik	FILTER, WE-CMBNC COMMON MODE POWER LINE CHOKE, 1mH, 15A, VERTICAL, TH-4P	
L4	1	300nH	PA2607.301NLT	Pulse Engineering	Inductor, Ferrite, 300 nH, 32 A, 0.00031 ohm, SMD	10.31x7.65mm
L7	1	17uH	750318974r00	Würth Electronics	INDUCTOR, 17uH, 20A	PTH_23MM88_23MM36
M1, M2, M3, M4, M5, M6, M7, M8	8		WA-T220-101E	OHMITE	HEATSINK, ALUMINIUM WITH CLIP, VERTICAL MOUNT, SOLDERABLE PIN, TO-220	
Q1, Q12	2	IPA60R120P7XKSA1	IPA60R120P7XKSA1	Infineon Technologies	MOSFET N-CHANNEL 600V 26A TO220	TO-220AB
Q2, Q3	2	IPP60R070CFD7	IPP60R070CFD7XKSA1	Infineon Technologies	MOSFET N-CHANNEL 600V 26A TO220	TO-220AB
Q4	1	MMBTA05LT1G	MMBTA05LT1G	ON Semiconductor	Transistor, NPN, 60 V, 0.5 A, AEC-Q101, SOT-23	SOT-23
Q5, Q7	2	CSD19531KCS	CSD19531KCS	Texas Instruments	MOSFET, N-CH, 100 V, 100 A, KCS0003B (TO-220-3)	KCS0003B
Q6	1	MMBT2222LT1G	MMBT2222LT1G	ON Semiconductor	Transistor, NPN, 30 V, 0.6 A, SOT-23	SOT-23

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
Q8	1	BSS84-7-F	BSS84-7-F	Diodes Inc.	MOSFET, P-CH, -50 V, -0.13 A, SOT-23	SOT-23
Q9	1	MMBT3904 LT1G	MMBT3904LT1G	ON Semiconductor	Transistor, NPN, 40 V, 0.2 A, SOT-23	SOT-23
Q10	1	IPD60R360 P7S	IPD60R360P7SAUMA1	Infineon Technologies	MOSFET, N-CH, 600 V, 9 A, DPAK	DPAK
Q11	1	MMBT3906- 7-F	MMBT3906-7-F	Diodes Inc.	Transistor, PNP, 40 V, 0.2 A, SOT-23	SOT-23
Q13, Q14	2	BC858C-7- F	BC858C-7-F	Diodes Inc.	Transistor, PNP, 30 V, 0.1 A, SOT-23	SOT-23
R1, R11	2	0	RMCF0603ZT0R00	Stackpole Electronics Inc	RES, 0, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R2	1	4.53k	ERJ-3EKF4531V	Panasonic	RES, 4.53 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R3	1	150	CRCW0805150RFKEA	Vishay-Dale	RES, 150, 1%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R4, R54	2	18	ERJ-6GEYJ180V	Panasonic	RES, 18, 5%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R5	1	18.2	CRCW080518R2FKEA	Vishay-Dale	RES, 18.2, 1%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R6, R19, R74	3	10.0k	CRCW080510K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R7, R8	2	0.03	CSRN2512FK30L0	Stackpole Electronics Inc	RES, 0.03, 1%, 2 W, 2512	2512
R9	1	44.2k	CRCW060344K2FKEA	Vishay-Dale	RES, 44.2 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R10, R22, R31	3	1.00k	CRCW12061K00FKEA	Vishay-Dale	RES, 1.00 k, 1%, 0.25 W, AEC-Q200 Grade 0, 1206	1206
R12	1	8.06k	RC0603FR-078K06L	Yageo	RES, 8.06 k, 1%, 0.1 W, 0603	603
R13, R57	2	2.2	RC0805JR-072R2L	Yageo America	RES, 2.2, 5%, 0.125 W, 0805	805
R14	1	49.9k	ERJ-3EKF4992V	Panasonic	RES, 49.9 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R15, R79	2	100k	CRCW0603100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R16	1	44.2k	RC0603FR-0744K2L	Yageo	RES, 44.2 k, 1%, 0.1 W, 0603	603
R17	1	12.0k	RC0603FR-0712KL	Yageo	RES, 12.0 k, 1%, 0.1 W, 0603	603
R18	1	51.1k	CRCW060351K1FKEA	Vishay-Dale	RES, 51.1 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R20	1	3.0Meg	CRCW12063M00JNEA	Vishay-Dale	RES, 3.0 M, 5%, 0.25 W, AEC-Q200 Grade 0, 1206	1206
R21, R23, R33	3	2.20Meg	RC0805FR-072M2L	Yageo America	RES, 2.20 M, 1%, 0.125 W, 0805	805
R24, R26	2	6.81k	CRCW06036K81FKEA	Vishay-Dale	RES, 6.81 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R25	1	213k	RT0603DRE07213KL	Yageo America	RES, 213 k, 0.5%, 0.1 W, 0603	603
R27, R34, R46, R86	4	2.74Meg	CRCW08052M74FKEA	Vishay-Dale	RES, 2.74 M, 1%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R28, R77	2	511k	CRCW1206511KFKEA	Vishay-Dale	RES, 511 k, 1%, 0.25 W, AEC-Q200 Grade 0, 1206	1206
R29, R36, R43	3	330k	CRCW1206330KJNEA	Vishay-Dale	RES, 330 k, 5%, 0.25 W, AEC-Q200 Grade 0, 1206, RES, 330 k, 5%, 0.25 W, 1206	1206
R30	1	100	CRCW0603100RFKEA	Vishay-Dale	RES, 100, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R32	1	120k	RC0603FR-07120KL	Yageo	RES, 120 k, 1%, 0.1 W, 0603	603
R35	1	215k	RT0603DRE07215KL	Yageo America	RES, 215 k, 0.5%, 0.1 W, 0603	603
R38, R40	2	22	CRCW060322R0JNEA	Vishay-Dale	RES, 22, 5%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R39	1	200k	RC0603FR-07200KL	Yageo	RES, 200 k, 1%, 0.1 W, 0603	603
R41	1	80.6k	CRCW060380K6FKEA	Vishay-Dale	RES, 80.6 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R42	1	27.0k	RC0603FR-0727KL	Yageo	RES, 27.0 k, 1%, 0.1 W, 0603	603
R44, R45	2	4.7k	CR0603-JW-472GLF	Bourns	RES, 4.7 k, 5%, 0.1 W, 0603	603
R47, R71, R73	3	6.04k	CRCW06036K04FKEA	Vishay-Dale	RES, 6.04 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R48	1	147k	CRCW0603147KFKEA	Vishay-Dale	RES, 147 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R49	1	10.0k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R50	1	13.3k	RC0603FR-0713K3L	Yageo	RES, 13.3 k, 1%, 0.1 W, 0603	603
R51, R63	2	113k	CRCW0603113KFKEA	Vishay-Dale	RES, 113 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R52, R53	2	10	CRCW080510R0JNEA	Vishay-Dale	RES, 10, 5%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R55, R64	2	10.0k	RNCF0603TKY10K0	Stackpole Electronics Inc	RES, 10.0 k, 0.01%, 0.063 W, 0603	603
R56	1	100k	RT0603BRD07100KL	Yageo America	RES, 100 k, 0.1%, 0.1 W, 0603	603
R58, R59	2	100	ERJ-3EKF1000V	Panasonic	RES, 100, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R60, R61	2	4.7	CRCW08054R70JNEA	Vishay-Dale	RES, 4.7, 5%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R62	1	6.81k	RC0603FR-076K81L	Yageo	RES, 6.81 k, 1%, 0.1 W, 0603	603

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
R65	1	0.0005	WSL2512L5000FEA18	Vishay-Dale	RES, 0.0005, 1%, 2 W, 2512	2512
R66, R78	2	10	CRCW060310R0FKEAHP	Vishay-Dale	RES, 10.0, 1%, 0.25 W, AEC-Q200 Grade 0, 0603	603
R67	1	1.00Meg	CRCW08051M00FKEA	Vishay-Dale	RES, 1.00 M, 1%, 0.125 W, AEC-Q200 Grade 0, 0805	805
R68	1	1.00Meg	MCT06030C1004FP500	Vishay/Beyschlag	RES, 1.00 M, 1%, 0.125 W, 0603	603
R69	1	330k	ERJ-3EKF3303V	Panasonic	RES, 330 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R70	1	487k	CRCW0603487KFKEA	Vishay-Dale	RES, 487 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R72	1	234k	RT0603DRE07234KL	Yageo America	RES, 234 k, 0.5%, 0.1 W, 0603	603
R75	1	1.10Meg	CRCW06031M10FKEA	Vishay-Dale	RES, 1.10 M, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R76	1	90.9k	CRCW060390K9FKEA	Vishay-Dale	RES, 90.9 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R80	1	75.0k	RC0603FR-0775KL	Yageo	RES, 75.0 k, 1%, 0.1 W, 0603	603
R81	1	390k	CRCW0603390KJNEA	Vishay-Dale	RES, 390 k, 5%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R82	1	49.9k	RC0603FR-0749K9L	Yageo	RES, 49.9 k, 1%, 0.1 W, 0603	603
R83	1	22.0k	ERJ-3EKF2202V	Panasonic	RES, 22.0 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R87	1	2.7Meg	CRCW12062M70JNEA	Vishay-Dale	RES, 2.7 M, 5%, 0.25 W, AEC-Q200 Grade 0, 1206	1206
R88	1	97.6k	CRCW060397K6FKEA	Vishay-Dale	RES, 97.6 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R89	1	82.0k	RC0603FR-0782KL	Yageo	RES, 82.0 k, 1%, 0.1 W, 0603	603
R90	1	130k	CRCW0603130KFKEA	Vishay-Dale	RES, 130 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	603
R100, R101	2	1.00k	ERJ-3EKF1001V	Panasonic	RES, 1.00 k, 1%, 0.1 W, 0603	603
RF1	1	47	EMC2-47RKI	TT Electronics/IRC	RES, 47, 10%, 2 W, Axial resistor	Axial resistor
RV1	1	275V	S10K275E2	TDK	Varistor 275V RMS 10MM Radial, TH	10mm Radial
T1	1	750318984r00	750318984r00	Würth Electronics	TRANSFORMER	PTH_41MM9_49MM0
TP1, TP2, TP3, TP4	4		5006	Keystone	Test Point, Compact, Black, TH	Black Compact Testpoint
U1, U9	2	UCC27517	UCC27517DBVR	Texas Instruments	4A/4A Single Channel High-speed Low-side Gate Driver, DBV0005A (SOT-23-5)	DBV0005A
U2	1	UCC256404	UCC256404ADDBR	Texas Instruments	Enhanced LLC Resonant Controller with Driver, DDB0014A (SOIC-14)	DDB0014A
U3	1	UCC28064A	UCC28064ADR	Texas Instruments	Natural Interleaving Transition Mode PFC Controller with Improved Light Load Efficiency, D0016A (SOIC-16)	D0016A
U4	1	LP2951-N	LP2951ACMX/NOPB	Texas Instruments	Series of Adjustable Micropower Voltage Regulators, D0008A (SOIC-8)	D0008A
U5	1	TL431LIAIDBZR	TL431LIAIDBZR	Texas Instruments	Programmable Shunt Regulator with Optimized Reference Current, DBZ0003A (SOT-23-3)	DBZ0003A
U6	1	VO618A-3	VO618A-3	Vishay-Semiconductor	Optocoupler, 5.3 kV, 50-600% CTR, TH	DIP, 4-Leads, Body 6.86x4.83mm, Pitch 2.54mm
U7, U8	2	UCC24612-1	UCC24612-1DBVR	Texas Instruments	High-Frequency Multi-Mode Synchronous Rectifier Controller, DBV0005A (SOT-23-5)	DBV0005A
U10	1	LP2981-50	LP2981-50DBVR	Texas Instruments	Micropower 100 mA Ultra Low-Dropout Regulator, 5-pin SOT-23, Pb-Free	DBV0005A
U11	1	TL331IDBVR	TL331IDBVR	Texas Instruments	SINGLE DIFFERENTIAL COMPARATOR, DBV0005A (SOT-23-5)	DBV0005A
U12	1	VO618A	VO618A	Vishay-Semiconductor	Optocoupler, 5.3 kV, 50-600% CTR, TH	DIP, 4-Leads, Body 6.86x4.83mm, Pitch 2.54mm
U13	1	TLV1711	TLV1711IDBVR	Texas Instruments	36V, Low-Power, RRO, General-Purpose Operational Amplifier, DBV0005A (SOT-23-5)	DBV0005A
U14	1	INA181A	INA181A4IDBV	Texas Instruments	Bidirectional, Low- and High-Side Measurement, Multichannel, Voltage Output, Current-Sense Amplifier, DBV0006A (SOT-6)	DBV0006A

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (<https://www.ti.com/legal/termsofsale.html>) or other applicable terms available either on [ti.com](https://www.ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2021, Texas Instruments Incorporated