


PMP22087 REV A Bill of Materials



Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
IPC8100	1		PMP22087	Any	Printed Circuit Board	
C100, C110	2	100pF	DE1B3RA101KN4AN01F	MuRata	CAP, CERM, 100 pF, X1 440 VAC/Y1 250 VAC, +/- 10%, B, D6xT4mm	D6xT4mm
C101, C102, C111, C112	4	220pF	DE1B3RA221KN4AN01F	MuRata	CAP CER 220PF 250V RAD	D6xT4mm
C103	1	150uF	450MXK150MEFCSN25X25	Rubycon	CAP, AL, 150 uF, 450 V, +/- 20%, TH	25.4x25mm
C104	1	0.22uF	890324023028CS	Wurth Elektronik	CAP, Film, 0.22 uF, X2 275 VAC, +/- 10%, TH	13x7mm
C105, C106	2	0.47uF	890324024005	Wurth Elektronik	CAP, Film, 0.47 uF, X2 275 VAC, +/- 10%, TH	15x10mm
C107	1	0.47uF	450MPK474J	Rubycon	CAP, Film, 0.47 uF, 450 V, +/- 5%, TH	18x6.5mm
C108	1	1uF	450MPK105J	Rubycon	CAP, Film, 1 uF, 450 V, +/- 5%, TH	18x9.5mm
C109	1	10pF	VJ1206A100JXGAT5Z	Vishay-Vitramon	CAP, CERM, 10 pF, 1000 V,+/- 5%, C0G/NP0, 1206	1206
C113	1	0.1uF	GRM188R61E104KA01D	MuRata	CAP, CERM, 0.1 uF, 25 V,+/- 10%, X5R, 0603	0603
C114	1	3900pF	GRM188R71E392KA01D	MuRata	CAP, CERM, 3900 pF, 25 V,+/- 10%, X7R, 0603	0603
C115	1	560pF	06035A561JAT2A	AVX	CAP, CERM, 560 pF, 50 V,+/- 5%, C0G/NP0, 0603	0603
C117	1	0.47uF	12063C474KAT2A	AVX	CAP, CERM, 0.47 uF, 25 V,+/- 10%, X7R, 1206	1206
C118	1	0.22uF	885012206048	Wurth Elektronik	CAP, CERM, 0.22 uF, 16 V,+/- 10%, X7R, 0603	0603
C119	1	10uF	ECA-1HHG100	Panasonic	CAP, AL, 10 uF, 50 V, +/- 20%, TH	D5xL11mm
C120	1	0.068uF	C1608X5R1H683K080AA	TDK	CAP, CERM, 0.068 uF, 50 V,+/- 10%, X5R, 0603	0603
C121	1	0.47uF	CGA5L2X7R1H474K160AA	TDK	CAP, CERM, 0.47 uF, 50 V,+/- 10%, X7R, AEC-Q200 Grade 1, 1206	1206
C122	1	10pF	0603ZC100KAT2A	AVX	CAP, CERM, 10 pF, 10 V,+/- 10%, X7R, 0603	0603
C123	1	1000pF	06031C102KAT2A	AVX	CAP, CERM, 1000 pF, 100 V,+/- 10%, X7R, 0603	0603
C200	1	2200pF	DE1E3KX222MA5BA01	MuRata	CAP, CERM, 2200 pF, 250 V, +/- 20%, E, Disc 10x8mm	Disc 10x8mm
C201, C204	2	0.022uF	ECW-F6223HL	Panasonic	CAP, Film, 0.022 uF, 630 V, +/- 3%, TH	12.5x6.2mm
C202, C203, C211, C212	4	4.7uF	UMK316AB7475KL-T	Taiyo Yuden	CAP, CERM, 4.7 uF, 50 V,+/- 10%, X7R, 1206	1206
C205	1	150pF	GRM31A5C2J151JW01D	MuRata	CAP, CERM, 150 pF, 630 V, +/- 5%, C0G/NP0, 1206	1206
C206	1	100pF	VJ1210A101JXGAT5Z	Vishay-Vitramon	CAP, CERM, 100 pF, 1000 V,+/- 5%, C0G/NP0, 1210	1210
C207, C208, C209, C210	4	680uF	EEU-FR1V681	Panasonic	CAP, AL, 680 uF, 35 V, +/- 20%, TH	Cap 10x20mm
C213, C216, C218	3	0.1uF	CC1206KRX7R9BB104	Yageo America	CAP, CERM, 0.1 uF, 50 V,+/- 10%, X7R, 1206	1206
C214	1	330uF	EEU-FM1V331L	Panasonic	CAP, AL, 330 uF, 35 V, +/- 20%, 0.03 ohm, TH	8.0x20mm
C215, C217	2	2.2uF	885012106018	Wurth Elektronik	CAP, CERM, 2.2 uF, 16 V,+/- 20%, X5R, 0603	0603
C219	1	2.2uF	C1206C225K4RACTU	Kemet	CAP, CERM, 2.2 uF, 16 V, +/- 10%, X7R, 1206	1206
C221	1	470pF	C0603X471K5RACTU	Kemet	CAP, CERM, 470 pF, 50 V,+/- 10%, X7R, 0603	0603
C222	1	470uF	EEU-FR1V471B	Panasonic	CAP ALUM 470UF 20% 35V RADIAL	
C223	1	2.2uF	GRM188R6YA225KA12D	MuRata	CAP, CERM, 2.2 uF, 35 V, +/- 10%, X5R, 0603	0603
C224	1	47pF	GRM1885C1H470FA01J	MuRata	CAP, CERM, 47 pF, 50 V, +/- 1%, C0G/NP0, 0603	0603
C225	1	1uF	GRM31MR71H105KA88L	MuRata	CAP, CERM, 1 uF, 50 V,+/- 10%, X7R, 1206	1206
C226	1	220pF	C0603X221K5RACTU	Kemet	CAP, CERM, 220 pF, 50 V,+/- 10%, X7R, 0603	0603
C227, C228, C229	3	4.7uF	GRM188R61C475KAAJ	MuRata	CAP, CERM, 4.7 uF, 16 V, +/- 10%, X5R, 0603	0603
C230	1	0.01uF	06031C103JAT2A	AVX	CAP, CERM, 0.01 uF, 100 V,+/- 5%, X7R, 0603	0603
C231	1	0.082uF	GRM188R71E823KA01D	MuRata	CAP, CERM, 0.082 uF, 25 V,+/- 10%, X7R, 0603	0603
C232	1	0.01uF	06031C103KAT2A	AVX	CAP, CERM, 0.01 uF, 100 V,+/- 10%, X7R, 0603	0603
C233	1	47pF	GRM1885C1H470FA01J	MuRata	CAP, CERM, 47 pF, 50 V,+/- 1%, C0G/NP0, 0603	0603
C234	1	4700pF	06031C472JAT2A	AVX	CAP, CERM, 4700 pF, 100 V,+/- 5%, X7R, 0603	0603
C235	1	2.2uF	C3216X5R1H225K160AB	TDK	CAP, CERM, 2.2 uF, 50 V,+/- 10%, X5R, 1206	1206
D100	1	600V	STTH8L06FP	STMicroelectronics	DIODE GEN PURP 600V 8A TO220FP	TO-220AC

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
D101	1	420V	GBU8J-BP	Micro Commercial Component	Diode, Switching-Bridge, 420 V, 8 A, TH	GBU
D102, D105, D202, D203	4	100V	MMDL914-TP	Micro Commercial Component	Diode, Switching, 100 V, 0.2 A, SOD-323	SOD-323
D103, D104	2	1.05V	MURA160T3G	ON Semiconductor	Diode, Ultrafast, 600V, 1A, SMA	SMA
D106	1	100V	1N4148WFL-G3-08	Vishay-Semiconductor	Diode, Switching, 100 V, 0.15 A, SOD-123FL	SOD-123FL
D200	1	20V	MMSZ5250BS-7-F	Diodes Inc.	Diode, Zener, 20 V, 200 mW, SOD-323	SOD-323
D204	1	60V	STPS160UY	STMicroelectronics	Diode, Schottky, 60 V, 1 A, AEC-Q101, SMB	SMB
D208	1	600V	ES1JAF	Fairchild Semiconductor	Diode, Ultrafast, 600 V, 1 A, AEC-Q101, SMAF	SMAF
D209	1	100V	1N4148W-7-F	Diodes Inc.	Diode, Ultrafast, 100 V, 0.15 A, SOD-123	SOD-123
F100	1		37215000001	Littelfuse	Fuse, 5 A, 250VAC/VDC, TH	TR5 fuse 8.5mm DIA
J200	1		ED120/4DS	On-Shore Technology	Terminal Block, 5.08 mm, 4x1, Brass, TH	4x1 5.08 mm Terminal Block
L100	1	120uH	750317259	Würth Elektronik	Inductor, 120 µH, 4 A, 0.055 ohm, TH	31.75x31.75mm
L101	1	100µH	7447021	Würth Elektronik	100µH Unshielded Toroidal Inductor 2A 80 mOhm Max Radial	IND_TORROID_15.8x7.5mm
L102	1	1mH	744822301	Würth Elektronik	Coupled inductor, 1 mH, 3 A, 0.035 ohm, TH	17.5x22x13 mm
L103	1	10mH	744824310	Würth Elektronik	Coupled inductor, 10 mH, 3 A, 0.105 ohm, TH	18.5x33x27.5 mm
Q100	1	650V	STB26NM60N	STMicroelectronics	MOSFET N-CH 600V 20A D2PAK	DDPAK
Q101	1	600V	IPP60R099C7	Infineon Technologies	MOSFET, N-CH, 600 V, 22 A, TO-220AB	TO-220AB
Q102	1	-60V	SI2309CDS-T1-E3	Vishay-Siliconix	MOSFET, P-CH, -60 V, -1.6 A, SOT-23	SOT-23
Q103	1	40 V	MMBT4401-7-F	Diodes Inc.	Transistor, NPN, 40 V, 0.15 A, SOT-23	SOT-23
Q200, Q202	2	650V	IPB65R150CFDATMA1	Infineon Technologies	MOSFET N-CH 650V 22.4A TO-263	DDPAK
Q201, Q203	2	80V	CSD19502Q5B	Texas Instruments	MOSFET, N-CH, 80 V, 100 A, DNK0008A (VSON-CLIP-8)	DNK0008A
Q204	1	60 V	FZT651TA	Zetex	Transistor, NPN, 60 V, 3 A, SOT-223	SOT-223
R100, R106	2	3.09Meg	CRCW12063M09FKEA	Vishay-Dale	RES, 3.09 M, 1%, 0.25 W, 1206	1206
R101, R105, R109, R116	4	3.3Meg	CRCW12063M30JNEA	Vishay-Dale	RES, 3.3 M, 5%, 0.25 W, 1206	1206
R102, R201, R204	3	10.0	CRCW060310R0FKEA	Vishay-Dale	RES, 10.0, 1%, 0.1 W, 0603	0603
R103	1	1.00Meg	CRCW06031M00FKEA	Vishay-Dale	RES, 1.00 M, 1%, 0.1 W, 0603	0603
R104	1	82.5k	CRCW060382K5FKEA	Vishay-Dale	RES, 82.5 k, 1%, 0.1 W, 0603	0603
R107	1	1.00	CRCW06031R00FKEA	Vishay-Dale	RES, 1.00, 1%, 0.1 W, 0603	0603
R108	1	24.3k	CRCW060324K3FKEA	Vishay-Dale	RES, 24.3 k, 1%, 0.1 W, 0603	0603
R110	1	3.0k	CRCW06033K00JNEA	Vishay-Dale	RES, 3.0 k, 5%, 0.1 W, 0603	0603
R111	1	100k	CRCW0603100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.1 W, 0603	0603
R112, R113	2	0.13	CSR1206FTR130	Stackpole Electronics Inc	RES, 0.13, 1%, 0.5 W, 1206	1206
R114, R115	2	0.15	ERJ-8BSFR15V	Panasonic	RES, 0.15, 1%, 0.5 W, 1206	1206
R117, R124	2	75.0k	CRCW060375K0FKEA	Vishay-Dale	RES, 75.0 k, 1%, 0.1 W, 0603	0603
R118	1	36.5k	CRCW060336K5FKEA	Vishay-Dale	RES, 36.5 k, 1%, 0.1 W, 0603	0603
R119	1	120k	RC0603FR-07120KL	Yageo America	RES, 120 k, 1%, 0.1 W, 0603	0603
R120	1	49.9k	CRCW060349K9FKEA	Vishay-Dale	RES, 49.9 k, 1%, 0.1 W, 0603	0603
R121, R125	2	390k	RC0603FR-07390KL	Yageo America	RES, 390 k, 1%, 0.1 W, 0603	0603
R122	1	10.0	CRCW080510R0FKEA	Vishay-Dale	RES, 10.0, 1%, 0.125 W, 0805	0805
R123	1	140k	CRCW0603140KFKEA	Vishay-Dale	RES, 140 k, 1%, 0.1 W, 0603	0603
R200, R203	2	10.0k	CRCW080510K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.125 W, 0805	0805
R202	1	0	CRCW12060000Z0EA	Vishay-Dale	RES, 0, 5%, 0.25 W, 1206	1206
R205	1	40.2k	CRCW060340K2FKEA	Vishay-Dale	RES, 40.2 k, 1%, 0.1 W, 0603	0603
R206	1	0	CRCW20100000Z0EF	Vishay-Dale	RES, 0, 5%, 0.75 W, AEC-Q200 Grade 0, 2010	2010
R207	1	5.36k	CRCW06035K36FKEA	Vishay-Dale	RES, 5.36 k, 1%, 0.1 W, 0603	0603
R208	1	7.15k	CRCW06037K15FKEA	Vishay-Dale	RES, 7.15 k, 1%, 0.1 W, 0603	0603
R210, R211	2	0	CRCW04020000Z0ED	Vishay-Dale	RES, 0, 5%, 0.063 W, 0402	0402
R214	1	2.2	CRCW06032R20JNEA	Vishay-Dale	RES, 2.2, 5%, 0.1 W, 0603	0603
R215	1	20.0	CRCW060320R0FKEA	Vishay-Dale	RES, 20.0, 1%, 0.1 W, 0603	0603
R216, R222, R225	3	4.99Meg	CRCW12064M99FKEA	Vishay-Dale	RES, 4.99 M, 1%, 0.25 W, 1206	1206

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
R218	1	12.4k	CRCW060312K4FKEA	Vishay-Dale	RES, 12.4 k, 1%, 0.1 W, 0603	0603
R219, R220, R221	3	1.65k	CRCW12061K65FKEA	Vishay-Dale	RES, 1.65 k, 1%, 0.25 W, 1206	1206
R223	1	20.0k	CRCW120620K0FKEA	Vishay-Dale	RES, 20.0 k, 1%, 0.25 W, 1206	1206
R224	1	324k	RC0603FR-07324KL	Yageo America	RES, 324 k, 1%, 0.1 W, 0603	0603
R226	1	324k	CRCW0603324KFKEA	Vishay-Dale	RES, 324 k, 1%, 0.1 W, 0603	0603
R227	1	274k	CRCW0603274KFKEA	Vishay-Dale	RES, 274 k, 1%, 0.1 W, 0603	0603
R228	1	0	CRCW06030000Z0EA	Vishay-Dale	RES, 0, 5%, 0.1 W, 0603	0603
R229	1	301k	CRCW0603301KFKEA	Vishay-Dale	RES, 301 k, 1%, 0.1 W, 0603	0603
R230	1	100	CRCW0603100RFKEA	Vishay-Dale	RES, 100, 1%, 0.1 W, 0603	0603
R231	1	44.2k	CRCW060344K2FKEA	Vishay-Dale	RES, 44.2 k, 1%, 0.1 W, 0603	0603
R232	1	37.4k	CRCW060337K4FKEA	Vishay-Dale	RES, 37.4 k, 1%, 0.1 W, 0603	0603
R298	1	10.0k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, 0603	0603
R299	1	4.99k	CR0603-FX-4991ELF	Bourns	RES, 4.99 k, 1%, 0.1 W, 0603	0603
RT100	1	10 ohm	B57236S0100M000	TDK	Thermistor NTC, 10 ohm, 20%, Disc 11.5mmx6mm	Disc 11.5mmx6mm
RV100	1		S10K275E2	EPCOS Inc	Varistor 275V RMS 10MM Radial, TH	10mm Radial
T200	1		750317258	Würth Elektronik	Transformer, 490 uH, TH	53.98x41.91mm
TP200	1		5000	Keystone	Test Point, Miniature, Red, TH	Red Miniature Testpoint
TP201	1		5001	Keystone	Test Point, Miniature, Black, TH	Black Miniature Testpoint
TP_L100	1		5010	Keystone	Test Point, Multipurpose, Red, TH	Red Multipurpose Testpoint
TP_N100	1		5011	Keystone	Test Point, Multipurpose, Black, TH	Black Multipurpose Testpoint
TP_PE100	1		5012	Keystone	Test Point, Multipurpose, White, TH	White Multipurpose Testpoint
U100	1		UCC28056DBV	Texas Instruments	6-Pin Single-Phase Transition-Mode PFC Controller, DBV0006A (SOT-23-6)	DBV0006A
U200, U201	2		UCC24612-2DBVR	Texas Instruments	UCC24612-2DBV, DBV0005A (SOT-23-5)	DBV0005A
U202	1		UCC256404DDBR	Texas Instruments	Enhanced LLC Resonant Controller with Driver, DDB0014A	DDB0014A
U203	1		VO618A-3	Vishay-Semiconductor	OPTOISOLATOR 5.3KV TRANS 4-DIP	DIP, 4-Leads, Body 6.86x4.83mm, Pitch 2.54mm
U204	1		ATL432LIAQDBZR	Texas Instruments	PWR MGMT SWITCHING REGULATOR	DBZ0003A
C116	0	0.01uF	885012206040	Würth Elektronik	CAP, CERM, 0.01 uF, 16 V,+/- 10%, X7R, 0603	0603
C220	0	220pF	C0603X221K5RACTU	Kemet	CAP, CERM, 220 pF, 50 V,+/- 10%, X7R, 0603	0603
C300, C301	0	0.1uF	GRM155R61C104KA88D	MuRata	CAP, CERM, 0.1uF, 16V, +/-10%, X5R, 0402	0402
C302	0	47pF	GRM1885C2A470JA01D	MuRata	CAP, CERM, 47 pF, 100 V,+/- 5%, C0G/NP0, 0603	0603
C303	0	10pF	GRM1555C1H100RA01D	MuRata	CAP, CERM, 10 pF, 50 V,+/- 4%, C0G/NP0, 0402	0402
C304	0	100pF	GRM1555C1H101JA01D	MuRata	CAP, CERM, 100 pF, 50 V,+/- 5%, C0G/NP0, 0402	0402
C305	0	0.1uF	GRM155R61E104KA87D	MuRata	CAP, CERM, 0.1 uF, 25 V, +/- 10%, X5R, 0402	0402
C306	0	0.01uF	C0603C103J3GECAUTO	Kemet	CAP, CERM, 0.01 uF, 25 V,+/- 5%, C0G/NP0, AEC-Q200 Grade 1, 0603	0603
C307	0	0.47uF	08053D474KAT2A	AVX	CAP, CERM, 0.47 uF, 25 V,+/- 10%, X5R, 0805	0805
C308	0	0.022uF	C0603C223K5RACTU	Kemet	CAP, CERM, 0.022 uF, 50 V,+/- 10%, X7R, 0603	0603
D210	0	6.2V	MMSZ5234B-7-F	Diodes Inc.	Diode, Zener, 6.2 V, 500 mW, SOD-123	SOD-123
D300	0	1V	BAT42WS	Diodes Inc.	Diode, Schottky, 30V, 0.2A, SOD-323	SOD-323
D301	0	70V	BAS70-06-7-F	Diodes Inc.	Diode, Schottky, 70 V, 0.07 A, SOT-23	SOT-23
D302	0	15V	MM5Z15VT1G	ON Semiconductor	DIODE ZENER 15V 200MW SOD523	SOD-523
D303	0	100V	MMDL914-TP	Micro Commercial Component	Diode, Switching, 100 V, 0.2 A, SOD-323	SOD-323
Q300	0	40 V	MMBT3906	Fairchild Semiconductor	Transistor, PNP, 40 V, 0.2 A, SOT-23	SOT-23
Q301	0	60V	2N7002ET1G	ON Semiconductor	MOSFET, N-CH, 60V, 0.26A, SOT-23	SOT-23
Q302, Q303	0	40 V	MMBT4401-7-F	Diodes Inc.	Transistor, NPN, 40 V, 0.15 A, SOT-23	SOT-23
R217	0	10.0k	ERJ-3EKF1002V	Panasonic	RES, 10.0 k, 1%, 0.1 W, 0603	0603

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
R300	0	2.21Meg	CRCW06032M21FKEA	Vishay-Dale	RES, 2.21 M, 1%, 0.1 W, 0603	0603
R301	0	619k	CRCW0402619KFKED	Vishay-Dale	RES, 619k ohm, 1%, 0.063W, 0402	0402
R302	0	0	ERJ-2GE0R00X	Panasonic	RES, 0 ohm, 5%, 0.063W, 0402	0402
R303, R304	0	10.0k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, 0603	0603
R305	0	100k	CRCW0402100KFKED	Vishay-Dale	RES, 100 k, 1%, 0.063 W, 0402	0402
R306, R307	0	4.75	CRCW04024R75FKED	Vishay-Dale	RES, 4.75, 1%, 0.063 W, 0402	0402
R308	0	2.00k	CPF0603B2K0E	TE Connectivity	RES, 2.00 k, 0.1%, 0.063 W, 0603	0603
R309	0	3.01k	CRCW06033K01FKEA	Vishay-Dale	RES, 3.01 k, 1%, 0.1 W, 0603	0603
R310	0	42.2k	CRCW120642K2FKEA	Vishay-Dale	RES, 42.2 k, 1%, 0.25 W, 1206	1206
R311	0	7.50k	RC0603FR-077K5L	Yageo America	RES, 7.50 k, 1%, 0.1 W, 0603	0603
R312	0	432k	CRCW0603432KFKEA	Vishay-Dale	RES, 432 k, 1%, 0.1 W, 0603	0603
R313	0	2.0k	RC0603JR-072KL	Yageo America	RES, 2.0 k, 5%, 0.1 W, 0603	0603
R314	0	2.2Meg	CRCW06032M20JNEA	Vishay-Dale	RES, 2.2 M, 5%, 0.1 W, 0603	0603
R315	0	30.1k	CRCW060330K1FKEA	Vishay-Dale	RES, 30.1 k, 1%, 0.1 W, 0603	0603
R316, R317	0	41.2k	CRCW060341K2FKEA	Vishay-Dale	RES, 41.2 k, 1%, 0.1 W, 0603	0603
R318	0	100k	CRCW0603100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.1 W, 0603	0603
R319	0	40.2k	CRCW060340K2FKEA	Vishay-Dale	RES, 40.2 k, 1%, 0.1 W, 0603	0603
U300	0		TMP300BIDCKR	Texas Instruments	Resistor-Programmable, up to 18V-Capable Temp Switch and Analog Out Sensor, DCK0006A (SOT-SC70-6)	DCK0006A
U301	0		TL331IDBVR	Texas Instruments	SINGLE DIFFERENTIAL COMPARATOR, DBV0005A (SOT-23-5)	DBV0005A
U302	0		INA180A4IDBV	Texas Instruments	Low- and High-Side Measurement, Multichannel, Voltage Output, Current-Sense Amplifier, DBV0005A (SOT-23-5)	DBV0005A
U303	0		FOD817D	Fairchild Semiconductor	OPTOISOLATOR 5KV TRANSISTOR 4DIP	DIP, 4-Leads, Body 6.86x4.83mm, Pitch 2.54mm
U304	0		LM4040DIM3-5.0/NOPB	Texas Instruments	Precision Micropower Shunt Voltage Reference, DBZ0003A (SOT-23-3)	DBZ0003A

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2019, Texas Instruments Incorporated