

Variant: 001
Generated: 12/5/2025 2:40 PM
TID #: PMP41140

PMP41140 REV E1 Bill of Materials



Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	C1, C2, C10, C13, C14, C17, C18, C21, C49	9	0.1uF	06035C104KA22A	AVX	CAP, CERM, 0.1 uF, 50 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0603	0603
2	C3, C6, C19, C22, C23	5	2.2uF	EMK107BB7225MA-T	Taiyo Yuden	CAP, CERM, 2.2 uF, 16 V, +/- 10%, X7R, 0603	0603
3	C4	1	0.47uF	450MPK474J	Rubycon	CAP, Film, 0.47 uF, 450 V, +/- 5%, TH	18x6.5mm
4	C5	1	0.33uF	B32522N6334J000	TDK	CAP, Film, 0.33 uF, 450 V, +/- 5%, AEC-Q200 Grade 1, TH	18x7mm
5	C8	1	33pF	C0603C330J5GACTU	Kemet	CAP, CERM, 33 pF, 50 V, +/- 5%, COG/NP0, 0603	0603
6	C9	1	0.1uF	GCM188R71C104KA37J	MuRata	CAP, CERM, 0.1 uF, 16 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0603	0603
7	C11	1	75pF	GRM1885C1H750JA01D	MuRata	CAP, CERM, 75 pF, 50 V, +/- 5%, COG/NP0, 0603	0603
8	C12	1	10uF	GRM188R61E106KA73D	MuRata	CAP, CERM, 10 uF, 25 V, +/- 10%, X5R, 0603	0603
9	C15, C16	2	22uF	GRM21BR61E226ME44L	MuRata	CAP, CERM, 22 uF, 25 V, +/- 20%, X5R, 0805	0805
10	C20	1	0.01uF	CL10B103K88NCNC	Samsung Electro-Mechanics	CAP, CERM, 0.01 uF, 50 V, +/- 10%, X7R, 0603	0603
11	C24	1	0.022uF	GRM158R71H223KA12D	MuRata	CAP, CERM, 0.022 uF, 50 V, +/- 10%, X7R, 0402	0402
12	C26, C27, C28, C30, C41, C42, C43, C44	8	4.7uF	GRM31CC72A475KE11L	Murata	4.7uF ±10% 100V Ceramic Capacitor X7S 1206 (3216 Metric)	1206
13	C36, C37, C38	3	0.022uF	V31206V22KXGAT5Z	Vishay-Vitramon	CAP, CERM, 0.022 uF, 1000 V, +/- 10%, X7R, 1206	1206
14	C39	1	1uF	C1608X7R1E105K080AB	TDK	CAP, CERM, 1 uF, 25 V, +/- 10%, X7R, 0803	0803
15	C45, C47	2	88pF	C105C0G1H880J050A	Yageo	CAP, CERM, 88 pF, 50 V, +/- 5%, COG/NP0, 0402	0402
16	C52, C53	2	680uF	A750MW687M1VAAED13	KEMET	CAP, 680 uF, 35 V, +/- 20%, TH	D10xL25mm
17	C58	1	1uF	CGA3E1X7R1V105K080AE	TDK	CAP, CERM, 1 uF, 35 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0603	0603
18	C59, C60	2	0.1uF	C1210V104KCRACU	Kemet	CAP, CERM, 0.1 uF, 500 V, +/- 10%, X7R	
19	C61	1	1000pF	CC0805KRX7R9BB102	Yageo America	CAP, CERM, 1000 pF, 50 V, +/- 10%, X7R, 0805	0805
20	C62	1	82uF	450XW82MEFC16X40	Rubycon	82 uF 450 V Aluminum Electrolytic Capacitors Radial, Can 2000 Hrs @ 105°C	RADIAL
21	C66	1	470pF	CGA2B2X7RHJ471K050BA	TDK	CAP, CERM, 470 pF, 50 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0402	0402
22	C68	1	0.1uF	0603YC104JA72A	AVX	CAP, CERM, 0.1 uF, 16 V, +/- 5%, X7R, 0603	0603
23	C75, C81	2	2200pF	C0603X222K5RACU	Kemet	CAP, CERM, 2200 pF, 50 V, +/- 10%, X7R, 0603	0603
24	C78	1	4700pF	GRM188R71H472KA01D	MuRata	CAP, CERM, 4700 pF, 50 V, +/- 10%, X7R, 0603	0603
25	C79	1	1000pF	C0603C102F3GACU	Kemet	CAP, CERM, 1000 pF, 25 V, +/- 1%, COG/NP0, 0603	0603
26	C82, C83	2	10uF	EMK107BBJ106MA-T	Taiyo Yuden	CAP, CERM, 10 uF, 16 V, +/- 20%, X5R, 0603	0603
27	C86	1	1uF	CC0603MRX5R7BB105	Yageo America	CAP, CERM, 1 uF, 16 V, +/- 20%, X5R, 0603	0603
28	C88	1	470pF	GCM1885C1H471JA16D	MuRata	CAP, CERM, 470 pF, 50 V, +/- 5%, COG/NP0, AEC-Q200 Grade 1, 0603	0603
29	C90	1	1uF	C1608X7R1E105K080AB	TDK	CAP, CERM, 1 uF, 25 V, +/- 10%, X7R, 0603	0603
30	D2	1	200V	RF071M2S	Rohm	Diode, Ultrafast, 200 V, 1 A, SOD-123	SOD-123
31	D3	1	100V	BAV99.215	Neperia	Diode, Switching, 100 V, 0.215 A, SOT-23	SOT-23
32	D4	1	200V	BAS20HT1G	ON Semiconductor	Diode, Switching, 200 V, 0.2 A, AEC-Q101, SOD-323	SOD-323
33	J1	1		HSEC8-160-01-L-DV-A-BL	Samtec	C2000 controlCARD-120HSEC connector, SMT	C2000 pin numbering
34	J2, J3	2		TSW-102-07-G-S	Samtec	Header, 100mil, 2x1, Gold, TH	2x1 Header
35	J4	1		PBC030AAN	Sullins Connector Solutions	Header, 100mil, 3x2, Gold, TH	Sullins 100mil, 2x3, 230 mil above insulator
36	J5	1		PBC020AAN	Sullins Connector Solutions	Header, 2.54mm, 2x2, Gold, TH	Header, 2.54mm, 2x2, TH
37	L2	1	15uH	744771A150	Würth Elektronik	Inductor, Shielded Drum Core, Ferrite, 15 uH, 3.5 A, 0.036 ohm, SMD	SMD
38	OUT, VIN	2		282843-2	TE Connectivity	Terminal Block, 10.16mm, 2x1, Tin, TH	Terminal Block, 10.16mm, 2x1, TH
39	Q1, Q2	2			Infineon Technologies	Insulated-Gate Field-Effect Transistor (IGFET), N-Channel, Enhancement, Body Diode, Pin 1 Source, 2 Source, 3 Source, 4 Gate, 5 Drain, 6 Drain, 7 Drain, 8 Drain, 9 Pins	PG-TDSON-8-59
40	Q3	1	60V	2N7002KW	Fairchild Semiconductor	MOSFET, N-CH, 60 V, 0.31 A, SOT-323	SOT-323
41	Q4	1	30V	CSD87312Q3E	Texas Instruments	MOSFET, 2-CH, N-CH, 30 V, 27 A, DPB00008A (VSON-8)	DPB00008A
42	R1	1	100	CRCW0603100RJNEA	Vishay-Dale	RES, 100, 5%, 0.1 W, 0603	0603
43	R2, R11	2	100k	CRCW0603100KJNEAC	Vishay-Dale	RES, 100 k, 5%, 0.1 W, 0603	0603
44	R3, R4	2	1.0Meg	CRCW06031M00JNEA	Vishay-Dale	RES, 1.0 M, 5%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
45	R5	1	0.10k	RC0603FR-0710KL	Yageo	RES, 10.0 k, 1%, 0.1 W, 0603	0603
46	R6	1	100k	CRCW0603100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.1 W, 0603	0603
47	R7	1	105k	CRCW0603105KFKEA	Vishay-Dale	RES, 105 k, 1%, 0.1 W, 0603	0603
48	R8	1	13.3k	CRCW060313K3FKEA	Vishay-Dale	RES, 13.3 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
49	R12, R19	2	0	ERJ-2GE0R00X	Panasonic	RES, 0, 5%, 0.1 W, AEC-Q200 Grade 0, 0402	0402
50	R13	1	10.0k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, 0603	0603
51	R15, R16	2	49.9	CRCW040249R9FKED	Vishay-Dale	RES, 49.9, 1%, 0.063 W, AEC-Q200 Grade 0, 0402	0402
52	R17, R56, R65	3	0	RMCF06032TOR00	Stackpole Electronics Inc.	RES, 0, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
53	R18	1	10.0Meg	CRCW120610M0FKEA	Vishay-Dale	RES, 10.0 M, 1%, 0.25 W, AEC-Q200 Grade 0, 1206	1206
54	R20	1	402k	ERJ-3EK-F4023V	Panasonic	RES, 402 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
55	R22	1	300	RC0603FR-07300RL	Yageo	RES, 300, 1%, 0.1 W, 0603	0603
56	R25, R26, R29, R31, R41, R44, R63, R67	8	0	ERJ-3GEY0R00V	Panasonic	RES, 0, 5%, 0.1 W, 0603	0603
57	R27	1	47.0k	RT0603DRE0747KL	Yageo America	RES, 47.0 k, 0.5%, 0.1 W, 0603	0603
58	R28	1	20.0k	ERJ-3EK-F2002V	Panasonic	RES, 20.0 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
59	R30	1	1	RC0603FR-0710RL	Yageo	RES, 1.00, 1%, 0.1 W, 0603	0603
60	R35	1	10	CRCW120610R0JNEA	Vishay-Dale	RES, 10, 5%, 0.25 W, AEC-Q200 Grade 0, 1206	1206
61	R36, R37, R40	3	3.32Meg	CRCW12063M32FKEA	Vishay-Dale	RES, 3.32 M, 1%, 0.25 W, 1206	1206
62	R38, R62, R66, R69	4	10.0k	M55342K12B10E0T	TT Electronics/IRC	RES, 10.0 k, 1%, 0.1 W, 0603	0603
63	R42, R49, R73, R77	4	10k	CRCW060310K0JNEA	Vishay-Dale	RES, 10 k, 5%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
64	R43	1	66.5k	RC0603FR-0766KSL	Yageo	RES, 66.5 k, 1%, 0.1 W, 0603	0603
65	R58	1	1.65k	RC0603FR-071K6SL	Yageo	RES, 1.65 k, 1%, 0.1 W, 0603	0603
66	R61, R70	2	20.0k	CRCW060320K0FKEA	Vishay-Dale	RES, 20.0 k, 1%, 0.1 W, 0603	0603
67	R71, R79	2	56k	CRCW060356K0JNEA	Vishay-Dale	RES, 56 k, 5%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
68	R81	1	47k	CRCW040247K0JNEA	Vishay-Dale	RES, 47 k, 5%, 0.063 W, AEC-Q200 Grade 0, 0402	0402
69	RB2, RB3	2	0.2	CSR1206FKR200	Stackpole Electronics Inc.	RES, 0.2, 1%, 0.5 W, 1206	1206
70	RT1	1		TMP6131DECR	Texas Instruments	Thermistor, DECO002A (X1SON-2)	DECO002A
71	T2	1		PMP41140XFMRE1	3L Electronic	PMP41140XFMRE1	PTH10
72	TP1, TP2, TP3, TP4, TP5, TP6, TP7, TP8, TP18	9		5003	Keystone	Test Point, Miniature, Orange, TH	Orange Miniature Testpoint
73	TP9, TP10, TP11, TP12, TP13, TP14, TP15, TP16, TP17	9		5006	Keystone Electronics	Test Point, Compact, Black, TH	Black Compact Testpoint
74	U1, U4, U5	3		TLV74332PDBVR	Texas Instruments	Low-Dropout Regulator, DBV0005A (SOT-23-5)	DBV0005A
75	U2	1		TLVH431BCDBZT	Texas Instruments	Low-Voltage Adjustable Precision Shunt Regulator, 80 mA, 0 to 70 degC, 3-pin SOT-23 (DB2), Green (RoHS & no Sb/Bi)	DB20003A
76	U3	1		TPS54202DDCR	Texas Instruments	4.5V to 28V Input, 2A Output, EMI Friendly Synchronous Step-Down Converter, DDC0006A (SOT-23-THIN-6)	DDC0006A
77	U6	1		LMG2650	Texas Instruments	650-V 100-mA GaN Half Bridge with Integrated Driver and Current Sense Emulation	VQFN19
78	U7	1		MP6908AGJ-Z	Monolithic Power Systems	FAST TURN-OFF INTELLIGENT RECTIF	TSOT23-6
79	U10	1		TLV9061IDBVR	Texas Instruments	10-MHz, RRIO, CMOS Operational Amplifier for Cost-Sensitive Systems, DBV0005A (SOT-23-5)	DBV0005A
80	U11	1		AMC1311BDWVR	Texas Instruments	Precision, 2-V Input, Reinforced Isolated Amplifier, DAW0008A (SOIC-8)	DAW0008A
81	U14	1		OPA2365AID	Texas Instruments	50 MHz, Low-Noise Single-Supply Rail-to-Rail Operational Amplifier, 2.2 to 5.5 V, -40 to 125 degC, 8-pin SOIC (DB), Green (RoHS & no Sb/Bi)	DO0008A

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#), [TI's General Quality Guidelines](#), or other applicable terms available either on [ti.com](#) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2026, Texas Instruments Incorporated

Last updated 10/2025